

Gallium Arsenide CATV Amplifier Module

Features



- 79-, 112- and 132-Channel Loading
- Excellent Distortion Performance
- Integrated ESD Protection Diodes
- GaAs FET Transistor Technology
- Unconditionally Stable Under All Load Conditions

Applications

- CATV Systems Operating in the 40 to 870 MHz Frequency Range
- Input Stage Amplifier in Optical Nodes, Line Extenders and Trunk Distribution Amplifiers for CATV Systems
- Driver Amplifier in Linear General Purpose Applications

Description

- 24 Vdc Supply, 40 to 870 MHz, CATV GaAs Forward Amplifier Module
- Replaced MHW9276. There are no form, fit or function changes with this part replacement.
- RoHS Compliant



ARCHIVE INFORMATION

ARCHIVE INFORMATION

Table 1. Maximum Ratings

| Rating | Symbol | Value | Unit |
|----------------------------------|-----------|-------------|------|
| RF Voltage Input (Single Tone) | V_{in} | +65 | dBmV |
| DC Supply Voltage | V_{CC} | +26 | Vdc |
| Operating Case Temperature Range | T_C | -20 to +100 | °C |
| Storage Temperature Range | T_{stg} | -40 to +100 | °C |

Table 2. ESD Maximum Ratings

| Rating | Input Value | Output Value | Unit |
|-------------------------------------|-------------|--------------|------|
| Surge Voltage per IEC 1000-4-5 | 200 | 200 | V |
| Human Body Model per Mil. Std. 1686 | 2 | 2 | kV |


Table 3. Electrical Characteristics ($V_{CC} = 24$ Vdc, $T_C = +30^\circ\text{C}$, 75 Ω system unless otherwise noted)

| Characteristic | Symbol | Min | Typ | Max | Unit |
|--|--------|-----|------|------|------|
| Frequency Range | BW | 40 | — | 870 | MHz |
| Power Gain | G_p | 27 | 27.9 | 28.5 | dB |
| Slope | S | 0.4 | 0.95 | 1.4 | dB |
| Gain Flatness (40-870 MHz, Peak-to-Valley) | G_F | — | — | 0.8 | dB |

Table 3. Electrical Characteristics ($V_{CC} = 24 \text{ Vdc}$, $T_C = +30^\circ\text{C}$, 75Ω system unless otherwise noted) (continued)

| Characteristic | Symbol | Min | Typ | Max | Unit | |
|--|------------------|--------------------|-----|-----|------|-----|
| Input Return Loss ($Z_o = 75 \text{ Ohms}$) | IRL | 20 | — | — | dB | |
| 40-200 MHz | | 19 | — | — | | |
| 201-600 MHz 601-870 MHz | | 18 | — | — | | |
| Output Return Loss ($Z_o = 75 \text{ Ohms}$) | ORL | 20 | — | — | dB | |
| 40-200 MHz | | 18 | — | — | | |
| 201-600 MHz 601-870 MHz | | 18 | — | — | | |
| Composite Second Order ($V_{out} = +44 \text{ dBmV/ch.}$, Worst Case) | 79-Channel FLAT | CSO ₇₉ | — | -70 | -64 | dBc |
| ($V_{out} = +44 \text{ dBmV/ch.}$, Worst Case) | 112-Channel FLAT | CSO ₁₁₂ | — | -66 | -62 | |
| ($V_{out} = +44 \text{ dBmV/ch.}$, Worst Case) | 132-Channel FLAT | CSO ₁₃₂ | — | -66 | -60 | |
| Cross Modulation Distortion @ Ch 2 ($V_{out} = +44 \text{ dBmV/ch.}$, FM = 55.25 MHz) | 79-Channel FLAT | XMD ₇₉ | — | -60 | -53 | dBc |
| ($V_{out} = +44 \text{ dBmV/ch.}$, FM = 55.25 MHz) | 112-Channel FLAT | XMD ₁₁₂ | — | -60 | -53 | |
| ($V_{out} = +44 \text{ dBmV/ch.}$, FM = 55.25 MHz) | 132-Channel FLAT | XMD ₁₃₂ | — | -60 | -53 | |
| Composite Triple Beat ($V_{out} = +44 \text{ dBmV/ch.}$, Worst Case) | 79-Channel FLAT | CTB ₇₉ | — | -71 | -65 | dBc |
| ($V_{out} = +44 \text{ dBmV/ch.}$, Worst Case) | 112-Channel FLAT | CTB ₁₁₂ | — | -68 | -61 | |
| ($V_{out} = +44 \text{ dBmV/ch.}$, Worst Case) | 132-Channel FLAT | CTB ₁₃₂ | — | -66 | -60 | |
| Noise Figure | NF | 50 MHz | — | 5.0 | 5.5 | dB |
| | | 550 MHz | — | 5.0 | — | |
| | | 750 MHz | — | 5.0 | — | |
| | | 870 MHz | — | 5.0 | 6.5 | |
| DC Current ($V_{DC} = 24 \text{ V}$, $T_C = 45^\circ\text{C}$) | I_{DC} | 235 | 250 | 265 | mA | |

PACKAGE DIMENSIONS



NOTES:
 1. DIMENSIONS ARE IN INCHES.
 2. INTERPRET DIMENSIONS AND TOLERANCES PER ASME Y14.5M, 1994.

| DIM | INCHES | | MILLIMETERS | |
|-----|-----------|-------|-------------|--------|
| | MIN | MAX | MIN | MAX |
| A | --- | 1.775 | --- | 45.085 |
| B | --- | 1.085 | --- | 27.559 |
| C | --- | 0.840 | --- | 21.336 |
| D | 0.015 | 0.021 | 0.381 | 0.533 |
| E | 0.465 | 0.510 | 11.811 | 12.954 |
| F | 0.300 | 0.325 | 7.62 | 8.255 |
| G | 0.100 BSC | | 2.540 BSC | |
| J | 0.156 BSC | | 3.962 BSC | |
| K | 0.315 | 0.355 | 8.001 | 9.017 |
| L | 1.000 BSC | | 25.400 BSC | |
| N | 0.165 BSC | | 4.191 BSC | |
| P | 0.100 BSC | | 2.540 BSC | |
| Q | 0.148 | 0.168 | 3.759 | 4.267 |
| R | --- | 0.600 | --- | 15.24 |
| S | 1.500 BSC | | 38.100 BSC | |
| U | 0.200 BSC | | 5.080 BSC | |
| V | --- | 0.250 | --- | 6.350 |
| W | 0.435 | --- | 11.049 | --- |
| X | 0.400 BSC | | 10.160 BSC | |
| Y | 0.152 | 0.163 | 3.861 | 4.140 |
| Z | 0.009 | 0.011 | 0.229 | 0.279 |

STYLE 1:
 PIN 1. RF INPUT
 2. GROUND
 3. GROUND
 4. DELETED
 5. VDC
 6. DELETED
 7. GROUND
 8. GROUND
 9. RF OUTPUT

CASE 1302-01
 ISSUE E

ARCHIVE INFORMATION

ARCHIVE INFORMATION

How to Reach Us:

Home Page:
www.freescale.com

E-mail:
support@freescale.com

USA/Europe or Locations Not Listed:
Freescale Semiconductor
Technical Information Center, CH370
1300 N. Alma School Road
Chandler, Arizona 85224
+1-800-521-6274 or +1-480-768-2130
support@freescale.com

Europe, Middle East, and Africa:
Freescale Halbleiter Deutschland GmbH
Technical Information Center
Schatzbogen 7
81829 Muenchen, Germany
+44 1296 380 456 (English)
+46 8 52200080 (English)
+49 89 92103 559 (German)
+33 1 69 35 48 48 (French)
support@freescale.com

Japan:
Freescale Semiconductor Japan Ltd.
Headquarters
ARCO Tower 15F
1-8-1, Shimo-Meguro, Meguro-ku,
Tokyo 153-0064
Japan
0120 191014 or +81 3 5437 9125
support.japan@freescale.com

Asia/Pacific:
Freescale Semiconductor Hong Kong Ltd.
Technical Information Center
2 Dai King Street
Tai Po Industrial Estate
Tai Po, N.T., Hong Kong
+800 2666 8080
support.asia@freescale.com

For Literature Requests Only:
Freescale Semiconductor Literature Distribution Center
P.O. Box 5405
Denver, Colorado 80217
1-800-441-2447 or 303-675-2140
Fax: 303-675-2150
LDCForFreescaleSemiconductor@hibbertgroup.com

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals", must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.

Freescale™ and the Freescale logo are trademarks of Freescale Semiconductor, Inc. All other product or service names are the property of their respective owners.
© Freescale Semiconductor, Inc. 2006, 2008. All rights reserved.

RoHS-compliant and/or Pb-free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb-free counterparts. For further information, see <http://www.freescale.com> or contact your Freescale sales representative.

For information on Freescale's Environmental Products program, go to <http://www.freescale.com/epp>.

