

---

## Designated client product

This product will be discontinued its production in the near term.  
And it is provided for customers currently in use only, with a time limit.  
It can not be available for your new project. Please select other new or existing products.

For more information, please contact our sales office in your region.

New Japan Radio Co.,Ltd.


<http://www.njr.com/>

## 2-INPUT 3CHANNEL VIDEO SWITCH


### ■ GENERAL DESCRIPTION

**NJM2284** is a switching IC for switching over from one audio or video input signal to another. Internalizing 2 inputs, 1 output, and then each set of 3 can be operated independently. One of them is a Clamp type and it can be operated while DC level fixed in position of the video signal. It is a higher efficiency video switch, featuring the operating supply voltage 4.75 to 13.0V, the frequency feature 10MHz, and then the Crosstalk 75dB (at 4.43MHz).


### ■ PACKAGE OUTLINE



**NJM2284D**



**NJM2284M**



**NJM2284V**

### ■ FEATURES

- 2 Input-1 Output Internalizing 3 Circuits (one of them is a Clamp type).
- Wide Operating Voltage
- Crosstalk 75dB (at 4.43MHz)
- Wide Bandwidth Frequency Feature 10MHz (2V<sub>P-P</sub> Input)
- Package Outline                   DIP-16, DMP-16, SSOP-16


### ■ RECOMMENDED OPERATING CONDITION

- Supply Voltage                   V<sup>+</sup>                   4.75 to 13.0V

### ■ APPLICATIONS

- VCR, Video Camera, AV-TV, Video Disk Player.

### ■ BLOCK DIAGRAM



**NJM2284D**  
**NJM2284M**  
**NJM2284V**

# NJM2284

## ■ MAXIMUM RATINGS

( $T_a = 25^\circ\text{C}$ )

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	$V^+$	14	V
Power Dissipation	$P_D$	(DIP16) 700 (DMP16) 350 (SSOP16) 300	mW mW mW
Operating Temperature Range	$T_{opr}$	-40 to +85	$^\circ\text{C}$
Storage Temperature Range	$T_{stg}$	-40 to +125	$^\circ\text{C}$

## ■ ELECTRICAL CHARACTERISTICS

( $V^+ = 5\text{V}, T_a = 25^\circ\text{C}$ )

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Operating Current (1)	$I_{CC1}$	$V^+ = 5\text{V}$ (Note1)	8.1	11.6	15.1	mA
Operating Current (2)	$I_{CC2}$	$V^+ = 9\text{V}$ (Note1)	10.2	14.6	19.0	mA
Voltage Gain	$G_V$	$V_I = 100\text{kHz}, 2V_{P,P}, V_O / V_I$	-0.6	-0.1	+0.4	dB
Frequency Gain	$G_F$	$V_I = 2V_{P,P}, V_O (10\text{MHz}) / V_O (100\text{kHz})$	-1.0	0	+1.0	dB
Differential Gain	DG	$V_I = 2V_{P,P}$ , Standard Staircase Signal	-	0.3	-	%
Differential Phasa	DP	$V_I = 2V_{P,P}$ , Standard Staircase Signal	-	0.3	-	deg
Output Offset Voltage	$V_{OS}$	(Note2)	-10	0	+10	mV
Crosstalk	CT	$V_I = 2V_{P,P}, 4.43\text{MHz}, V_O / V_I$	-	-75	-	dB
Switch Change Over Voltage	$V_{CH}$	All inside Switch ON	2.5	-	-	V
Switch Change Over Voltage	$V_{CL}$	All inside Switch OFF	-	-	1.0	V

(Note1)  $S1 = S2 = S3 = S4 = S5 = S6 = S7 = 1$


(Note2)  $S1 = S2 = S3 = S4 = S5 = S6 = 1, S7 = 1 \rightarrow 2$  Measure the output DC voltage difference

## ■ TERMINAL EXPLANATION

PIN No.	PIN NAME	VOLTAGE	INSIDE EQUIVALENT CIRCUIT
16 1 11 14	IN 1 A IN 1 B IN 2 A IN 2 B [Input]	2.5V	
8 9	IN 3 A IN 3 B [Input]	1.5V	
2 12 7	CTL 1 CTL 2 CTL 3 [Switching]		
3 5	OUT1 OUT2	1.8V	
6	OUT3 [Output]	0.8V	
13	V <sup>+</sup>	5V	
15 4 10	GND 1 GND 2 GND 3		

# NJM2284

## TEST CIRCUIT




Parameter	S1	S2	S3	S4	S5	S6	S7	S8	Test Part
$I_{CC1}$	1	1	1	1	1	1	1	1	$V^+$
$I_{CC2}$	1	1	1	1	1	1	1	1	
$G_{v1}$	2	1	1	1	1	1	1	1	$v_o$
$G_{F1}$	2	1	1	1	1	1	1	1	
$DG_1$	2	1	1	1	1	1	1	1	
$DP_1$	2	1	1	1	1	1	1	1	
CT1	2	1	1	1	1	1	2	1	$v_o$
CT2	1	2	1	1	1	1	1	1	
CT3	1	1	2	1	1	1	2	2	
CT4	1	1	1	2	1	1	1	2	
CT5	1	1	1	1	2	1	2	3	
CT6	1	1	1	1	1	2	1	3	
$V_{OS1}$	1	1	1	1	1	1	1/2	1	$V_o$
$V_{C1}$	1/2	2/1	1	1	1	1	$V_c$	1	$V_c$
THD	2	1	1	1	1	1	1	1	$v_o$

## ■ TYPICAL CHARACTERISTICS


**Operating Current 1 vs. Temperature**

( $V^+ = 9V$ )




**Operating Current 2 vs. Temperature**

( $V^+ = 5V$ )




**Voltage Gain 1 vs. Temperature**

( $V^+ = 5V$ )




**Frequency Gain 1 vs. Temperature**

( $V^+ = 5V$ )




**Differential Gain 1 vs. Temperature**

( $V^+ = 5V$ )



**Differential Phase 1 vs. Temperature**


( $V^+ = 5V$ )



## ■ TYPICAL CHARACTERISTICS


**Offset Voltage 1 vs. Temperature**

( $V^+ = 5V$ )




**Crosstalk 1 vs. Temperature**

( $V^+ = 5V$ )




**Crosstalk 2 vs. Temperature**

( $V^+ = 5V$ )




**Crosstalk 3 vs. Temperature**

( $V^+ = 5V$ )




**Crosstalk 4 vs. Temperature**

( $V^+ = 5V$ )




**Crosstalk 5 vs. Temperature**

( $V^+ = 5V$ )




## ■ TYPICAL CHARACTERISTICS


### Crosstalk 6 vs. Temperature




### Switch Change Over 1 vs. Temperature




### Operating Current vs. Operating Voltage




### Voltage Gain 1 vs. Operating Voltage



### Frequency Gain 1 vs. Operating Voltage



### Differential Gain 1 vs. Operating Voltage






## ■ TYPICAL CHARACTERISTICS


**Differential Phase 1 vs. Operating Voltage**

( $T_a = 25^\circ\text{C}$ )




**Offset Voltage 1 vs. Operating Voltage**

( $T_a = 25^\circ\text{C}$ )




**Crosstalk 1 vs. Operating Voltage**

( $T_a = 25^\circ\text{C}$ )




**Crosstalk 2 vs. Operating Voltage**

( $T_a = 25^\circ\text{C}$ )




**Crosstalk 3 vs. Operating Voltage**

( $T_a = 25^\circ\text{C}$ )



**Crosstalk 4 vs. Operating Voltage**


( $T_a = 25^\circ\text{C}$ )



## ■ TYPICAL CHARACTERISTICS


### Crosstalk 5 vs. Operating Voltage

( $T_a = 25^\circ\text{C}$ )




### Crosstalk 6 vs. Operating Voltage

( $T_a = 25^\circ\text{C}$ )




### Switch Change Over 1 vs. Operating Voltage

( $T_a = 25^\circ\text{C}$ )




### Differential Gain vs. APL

( $T_a = 25^\circ\text{C}$ )




### Voltage Gain 1 vs. Frequency Feature

( $T_a = 25^\circ\text{C}$ )




### Differential Gain 1 vs. Load Resistor

( $T_a = 25^\circ\text{C}$ )




## ■ TYPICAL CHARACTERISTICS


### Differential Gain 5 vs. Load Resistor




### Differential Phase 1 vs. Load Resistor




### Differential Phase 5 vs. Load Resistor




### Differential Gain 1 vs. APL



### Differential Phase 1 vs. APL




### Differential Phase 5 vs. APL



## ■ TYPICAL CHARACTERISTICS


**Total Harmonic Distortion 1 vs. Load Resistor**  
( $T_a = 25^\circ\text{C}$ )




# NJM2284

## ■ APPLICATION


This IC requires  $1M\Omega$  resistance between INPUT and GND pin for clamp type input since the minute current causes an unstable pin voltage.



This IC requires  $0.1\mu\text{F}$  capacitor between INPUT and GND,  $1M\Omega$  resistance between INPUT and GND for clamp type input at mute mode.



This IC requires  $0.1\mu\text{F}$  capacitor between INPUT and GND for bias type input at mute mode.



[CAUTION]  
The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.