



The following document contains information on Cypress products. The document has the series name, product name, and ordering part numbering with the prefix “MB”. However, Cypress will offer these products to new and existing customers with the series name, product name, and ordering part number with the prefix “CY”.

#### **How to Check the Ordering Part Number**

1. Go to [www.cypress.com/pcn](http://www.cypress.com/pcn).
2. Enter the keyword (for example, ordering part number) in the **SEARCH PCNS** field and click **Apply**.
3. Click the corresponding title from the search results.
4. Download the Affected Parts List file, which has details of all changes

#### **For More Information**

Please contact your local sales office for additional information about Cypress products and solutions.

#### **About Cypress**

Cypress is the leader in advanced embedded system solutions for the world's most innovative automotive, industrial, smart home appliances, consumer electronics and medical products. Cypress' microcontrollers, analog ICs, wireless and USB-based connectivity solutions and reliable, high-performance memories help engineers design differentiated products and get them to market first. Cypress is committed to providing customers with the best support and development resources on the planet enabling them to disrupt markets by creating new product categories in record time. To learn more, go to [www.cypress.com](http://www.cypress.com).

January 30, 2015

## Chip Errata for the MB90880/910/920/930/950/990 Series, F<sup>2</sup>MC-16LX Family, 16-Bit Microcontroller

This document describes the chip errata for the MB90880/910/920/930/950/990 Series, F<sup>2</sup>MC-16LX Family, 16-Bit Microcontroller. Compare this document to the device's data sheet for a complete functional description.

Contact your local Cypress Sales Representative if you have questions.

### Part Numbers Affected

Part Number
MB90880/910/920/930/950/990 Series

### Problem Description

The functional limitation of PLL stop mode was found. It is rare problem that CPU does not return to PLL clock mode normally when it returns from PLL stop mode by external interrupt. Details of the functional limitation and workaround are provided in this errata.

No limitation occurs, if one of the following conditions met:

- PLL stop mode is not used
- PLL stop mode is released by external reset or power on reset
- PLL clock multiplication rate: 1 or 2 or 3 or 4

### Affected Devices

Table 1. Affected Devices

Series	Part Number
MB90880 series	MB90882/S, MB90F882A/S, MB90F883B/S, MB90F883BH/S, MB90F883C/S, MB90F884B/S, MB90F884BH/S, MB90F884C/S
MB90910 series	MB90911AS, MB90F912BS
MB90920 series	MB90922NCS, MB90F922NC/S, MB90F923NC/S, MB90F924NC/S
MB90930 series	MB90931/S, MB90F931/S
MB90950 series	MB90F952JDS/MDS
MB90990 series	MB90F997JBS/MBS

## Details of the Limitation

When CPU returns from PLL stop mode by external interrupt, it usually starts to execute program in PLL clock mode after the oscillation stable waiting time progress set up in CKSCR:WS1,0 bit.

However, Table 1 Affected devices may perform operation (1) or (2) or (3) immediately after external interrupt input.

1. Reset start without reset source
2. Start in Main clock mode, then change to PLL clock mode after PLL clock oscillation stabilization wait time ( $2^{14}$ /Main clock) progress
3. Start in PLL clock mode without clock oscillation stabilization wait time
4. In (3) case, CPU may execute incorrect instruction because it operates by unstable PLL clocks. As a result, user system may malfunction.

No limitation occurs, if one of the following conditions met:

- PLL stop mode is not used
- PLL stop mode is released by external reset or power on reset
- PLL clock multiplication rate: 1 or 2 or 3 or 4

## Workaround

Use on the conditions of 1) or 2) or 3)

1. Use Main stop mode instead of PLL STOP mode
2. Use by the following state transition
3. PLL clock mode => Main clock mode => Main stop mode => Main clock mode => PLL clock mode
4. PLL stop mode is released by external reset or power on reset
5. PLL clock multiplication rate: 1 or 2 or 3 or 4

## Corrective Action by Spansion

We will release errata sheet of each Hardware manuals to prohibit PLL stop mode.

## Document History Page

<b>Document Title: MB90880/900 Series - Chip Errata for the MB90880/910/920/930/950/990 Series, F<sup>2</sup>MC-16LX Family, 16-Bit Microcontroller</b>			
<b>Document Number: 002-04398</b>			
Rev.	ECN No.	Orig. of Change	Description of Change
**	—	YUIS	Initial Release
*A	5233073	YUIS	Migrated to Cypress format

Cypress Semiconductor  
 198 Champion Court  
 San Jose, CA 95134-1709  
 Phone: 408-943-2600  
 Fax: 408-943-4730  
<http://www.cypress.com>

© Cypress Semiconductor Corporation, 2015-2016. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you under its copyright rights in the Software, a personal, non-exclusive, nontransferable license (without the right to sublicense) (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units. Cypress also grants you a personal, non-exclusive, nontransferable, license (without the right to sublicense) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely to the minimum extent that is necessary for you to exercise your rights under the copyright license granted in the previous sentence. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and Company shall and hereby does release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. Company shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit [cypress.com](http://cypress.com). Other names and brands may be claimed as property of their respective owners.