To our customers,

Old Company Name in Catalogs and Other Documents

On April 1st, 2010, NEC Electronics Corporation merged with Renesas Technology Corporation, and Renesas Electronics Corporation took over all the business of both companies. Therefore, although the old company name remains in this document, it is a valid Renesas Electronics document. We appreciate your understanding.

Renesas Electronics website: http://www.renesas.com

April 1st, 2010
Renesas Electronics Corporation

Issued by: Renesas Electronics Corporation (http://www.renesas.com)

Send any inquiries to http://www.renesas.com/inquiry.

Notice

1. All information included in this document is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas Electronics products listed herein, please confirm the latest product information with a Renesas Electronics sales office. Also, please pay regular and careful attention to additional and different information to be disclosed by Renesas Electronics such as that disclosed through our website.
2. Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
3. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part.
4. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
5. When exporting the products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations. You should not use Renesas Electronics products or the technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations.
6. Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
7. Renesas Electronics products are classified according to the following three quality grades: "Standard", "High Quality", and "Specific". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below. You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application categorized as "Specific" without the prior written consent of Renesas Electronics. Further, you may not use any Renesas Electronics product for any application for which it is not intended without the prior written consent of Renesas Electronics. Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for an application categorized as "Specific" or for which the product is not intended where you have failed to obtain the prior written consent of Renesas Electronics. The quality grade of each Renesas Electronics product is "Standard" unless otherwise expressly specified in a Renesas Electronics data sheets or data books, etc.

   "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots.

   "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; safety equipment; and medical equipment not specifically designed for life support.

   "Specific": Aircraft; aerospace equipment; submersible repeaters; nuclear reactor control systems; medical equipment or systems for life support (e.g. artificial life support devices or systems), surgical implantations, or healthcare intervention (e.g. excision, etc.), and any other applications or purposes that pose a direct threat to human life.
8. You should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics.
12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.

(Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.

(Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

HA1630Q04/05/06 Series

Low Voltage Operation CMOS Quad Operational Amplifier

REJ03D0803-0100
Rev.1.00
Mar 10, 2006

Description

The HA1630Q04/05/06 are high slew rate single CMOS Operational Amplifiers realizing low voltage operation, low input offset voltage and low supply current. In addition to a low operating voltage from 1.8V, these device output can achieve full swing output voltage capability extending to either supply. Available in an ultra-small TSSOP-14 package that occupies only 1/4 the area of the SOP-14 package.

Features

- Low power and single supply operation — V_{DD} = 1.8 to 5.5 V
- Low input offset voltage — V_{IO} = 4.0 mV Max
- Low supply current (per channel) — I_{DD} = 200 ∝A Typ (HA1630Q04)
  I_{DD} = 400 ∝A Typ (HA1630Q05)
  I_{DD} = 800 ∝A Typ (HA1630Q06)
- High slew rate — SR = 2 V/∝s Typ (HA1630Q04)
  SR = 4 V/∝s Typ (HA1630Q05)
  SR = 8 V/∝s Typ (HA1630Q06)
- Maximum output voltage — V_{OH} = 2.9 V Min (at V_{DD} = 3.0 V)
- Low input bias current — I_{IB} = 1 pA Typ

Ordering Information

Type No.	Package Name	Package Code
HA1630Q04T	TTP-14D	PTSP0014JA-B
HA1630Q05T	TTP-14D	PTSP0014JA-B
HA1630Q06T	TTP-14D	PTSP0014JA-B

Pin Arrangement



Equivalent Circuit (per one channel)



Absolute Maximum Ratings

(Ta = 25°C)

Items	Symbol	Ratings	Unit	Note
Supply voltage	V_{DD}	7	V	
Differential input voltage	$V_{IN(diff)}$	$-V_{DD}$ to $+V_{DD}$	V	
Input voltage	V_{IN}	–0.3 to $+V_{DD}$	V	1
Power dissipation	P_T	400	mW	
Operating temp. Range	Topr	–40 to +85	°C	
Storage temp. Range	Tstg	–55 to +125	°C	

Note: 1. Do not apply Input Voltage exceeding V_{DD} or 7 V.

Electrical Characteristics

(V_{DD} = 3.0 V, Ta = 25°C)

Items	Symbol	Min	Typ	Max	Unit	Test Condition
Input offset voltage	V_{IO}	—	—	4.0	mV	Vin = 1.5 V
Input offset current	I_{IO}	—	(1.0)	—	pA	Vin = 1.5 V
Input bias current	I_{IB}	—	(1.0)	—	pA	Vin = 1.5 V
Output high voltage	V_{OH}	2.9	—	—	V	R_L = 100 kΩ
Output source current	$I_{O\ SOURCE}$	100	200	—	∝A	V_{OH} = 2.5 V (HA1630Q04)
		200	400	—		V_{OH} = 2.5 V (HA1630Q05)
		400	800	—		V_{OH} = 2.5 V (HA1630Q06)
Output low voltage	V_{OL}	—	—	0.1	V	R_L = 100 kΩ
Output sink current	$I_{O\ SINK}$	—	(5.0)	—	mA	V_{OL} = 0.5 V (HA1630Q04)
		—	(6.0)	—		V_{OL} = 0.5 V (HA1630Q05)
		—	(6.5)	—		V_{OL} = 0.5 V (HA1630Q06)
Common mode input voltage range	V_{CM}	–0.05 to 2.1	—	—	V	(HA1630Q04, HA1630Q05)
		0 to 1.9	—	—		(HA1630Q06)
Slew rate	SR	—	(2.0)	—	V/∝s	C_L = 20 pF (HA1630Q04)
		—	(4.0)	—		C_L = 20 pF (HA1630Q05)
		—	(8.0)	—		C_L = 20 pF (HA1630Q06)
Voltage gain	A_V	60	90	—	dB	
Gain bandwidth product	BW	—	(2100)	—	kHz	C_L = 20 pF (HA1630Q04)
		—	(3300)	—		C_L = 20 pF (HA1630Q05)
		—	(3600)	—		C_L = 20 pF (HA1630Q06)
Power supply rejection ratio	PSRR	50	70	—	dB	
Common mode rejection ratio	CMRR	50	70	—	dB	
Supply current	I_{DD}	—	0.8	1.6	mA	R_L = ∞ (HA1630Q04)
		—	1.6	3.2		R_L = ∞ (HA1630Q05)
		—	3.2	6.8		R_L = ∞ (HA1630Q06)

Notes: 1. In the case of continuous current flow, use a sink current of under 4 mA.
2. ( ) : Design specification

Table of Graphs

Electrical Characteristics			HA1630Q04 Figure	HA1630Q05 Figure	HA1630Q06 Figure	Test Circuit
Supply current	I_{DD}	vs Supply voltage	1-1	2-1	3-1	2
		vs Ambient temperature	1-2	2-2	3-2	
Output high voltage	V_{OH}	vs Output source current	1-3	2-3	3-3	4
		vs Supply voltage	1-4	2-4	3-4	
Output source current	$I_{O\ SOURCE}$	vs Ambient temperature	1-5	2-5	3-5	6
Output low voltage	V_{OL}	vs Output sink current	1-6	2-6	3-6	5
Output sink current	$I_{O\ SINK}$	vs Ambient temperature	1-7	2-7	3-7	6
Input offset voltage	V_{IO}	Distribution	1-8	2-8	3-8	1
		vs Supply voltage	1-9	2-9	3-9	
		vs Ambient temperature	1-10	2-10	3-10	
Common mode input voltage range	V_{CM}	vs Ambient temperature	1-11	2-11	3-11	7
Power supply rejection ratio	PSRR	vs Frequency	1-12	2-12	3-12	1
Common mode rejection ratio	CMRR	vs Frequency	1-13	2-13	3-13	7
Voltage gain & phase angle	A_V	vs Frequency	1-14	2-14	3-14	10
Input bias current	I_{IB}	vs Ambient temperature	1-15	2-15	3-15	3
		vs Input voltage	1-16	2-16	3-16	
Slew Rate (rising)	SRr	vs Ambient temperature	1-17	2-17	3-17	9
Slew Rate (falling)	SRf	vs Ambient temperature	1-18	2-18	3-18	
Slew rate		Large signal transient response	1-19	2-19	3-19	
		Small signal transient response	1-20	2-20	3-20	
Total harmonic distortion + noise	(0 dB)	vs. Output voltage p-p	1-21	2-21	3-21	8
	(40 dB)	vs. Output voltage p-p	1-22	2-22	3-22	
Maximum p-p output voltage		vs Frequency	1-23	2-23	3-23	
Voltage noise density		vs Frequency	1-24	2-24	3-24	

Main Characteristics (HA1630Q04)

Figure 1-1. HA1630Q04
Supply Current vs. Supply Voltage



Figure 1-2. HA1630Q04
Supply Current vs. Ambient Temperature



Figure 1-3. HA1630Q04
Output High Voltage vs. Output Source Current



Figure 1-4. HA1630Q04
Output High Voltage vs. Supply Voltage



Figure 1-5. HA1630Q04
Output Source Current vs. Ambient Temperature



Figure 1-6. HA1630Q04
Output Low Voltage vs. Output Sink Current



Figure 1-7. HA1630Q04
Output Sink Current vs. Ambient Temperature



Figure 1-8. HA1630Q04
Input Offset Voltage Distribution



Figure 1-9. HA1630Q04
Input Offset Voltage vs. Supply Voltage



Figure 1-10. HA1630Q04
Input Offset Voltage vs. Ambient Temperature



Figure 1-11. HA1630Q04
Common Mode Input Voltage vs.
Ambient Temperature



Figure 1-12. HA1630Q04
Power Supply Rejection Ratio vs. Frequency



Figure 1-13. HA1630Q04
Common Mode Rejection Ratio vs. Frequency



Figure 1-14. HA1630Q04
Open Loop Voltage Gain and Phase Angle vs. Frequency



Figure 1-15. HA1630Q04
Input Bias Current vs. Ambient Temperature



Figure 1-16. HA1630Q04
Input Bias Current vs. Input Voltage



Figure 1-17. HA1630Q04
Slew Rate (rising) vs. Ambient Temperature



Figure 1-18. HA1630Q04
Slew Rate (falling) vs. Ambient Temperature



Figure 1-19. HA1630Q04
Large Signal Transient Response



Figure 1-20. HA1630Q04
Small Signal Transient Response



Figure 1-21. HA1630Q04
Total Harmonic Distortion + Noise vs.
Output Voltage p-p



Figure 1-22. HA1630Q04
Total Harmonic Distortion + Noise vs.
Output Voltage p-p



Figure 1-23. HA1630Q04
Voltage Output p-p vs. Frequency



Figure 1-24. HA1630Q04
Voltage Noise Density vs. Frequency



Main Characteristics (HA1630Q05)

Figure 2-1. HA1630Q05
Supply Current vs. Supply Voltage



Figure 2-2. HA1630Q05
Supply Current vs. Ambient Temperature



Figure 2-3. HA1630Q05
Output High Voltage vs. Output Source Current



Figure 2-4. HA1630Q05
Output High Voltage vs. Supply Voltage



Figure 2-5. HA1630Q05
Output Source Current vs. Ambient Temperature



Figure 2-6. HA1630Q05
Output Low Voltage vs. Output Sink Current



Figure 2-7. HA1630Q05
Output Sink Current vs. Ambient Temperature



Figure 2-8. HA1630Q05
Input Offset Voltage Distribution



Figure 2-9. HA1630Q05
Input Offset Voltage vs. Supply Voltage



Figure 2-10. HA1630Q05
Input Offset Voltage vs. Ambient Temperature



Figure 2-11. HA1630Q05
Common Mode Input Voltage vs.
Ambient Temperature



Figure 2-12. HA1630Q05
Power Supply Rejection Ratio vs. Frequency



Figure 2-13. HA1630Q05
Common Mode Rejection Ratio vs. Frequency



Figure 2-14. HA1630Q05
Open Loop Voltage Gain and Phase Angle vs. Frequency



Figure 2-15. HA1630Q05
Input Bias Current vs. Ambient Temperature



Figure 2-16. HA1630Q05
Input Bias Current vs. Input Voltage



Figure 2-17. HA1630Q05
Slew Rate (rising) vs. Ambient Temperature



Figure 2-18. HA1630Q05
Slew Rate (falling) vs. Ambient Temperature



Figure 2-19. HA1630Q05
Large Signal Transient Response



Figure 2-20. HA1630Q05
Small Signal Transient Response



Figure 2-21. HA1630Q05
Total Harmonic Distortion + Noise vs.
Output Voltage p-p



Figure 2-22. HA1630Q05
Total Harmonic Distortion + Noise vs.
Output Voltage p-p



Figure 2-23. HA1630Q05
Voltage Output p-p vs. Frequency



Figure 2-24. HA1630Q05
Voltage Noise Density vs. Frequency



Main Characteristics (HA1630Q06)

Figure 3-1. HA1630Q06
Supply Current vs. Supply Voltage



Figure 3-2. HA1630Q06
Supply Current vs. Ambient Temperature



Figure 3-3. HA1630Q06
Output High Voltage vs. Output Source Current



Figure 3-4. HA1630Q06
Output High Voltage vs. Supply Voltage



Figure 3-5. HA1630Q06
Output Source Current vs. Ambient Temperature



Figure 3-6. HA1630Q06
Output Low Voltage vs. Output Sink Current



Figure 3-7. HA1630Q06
Output Sink Current vs. Ambient Temperature



Figure 3-8. HA1630Q06
Input Offset Voltage Distribution



Figure 3-9. HA1630Q06
Input Offset Voltage vs. Supply Voltage



Figure 3-10. HA1630Q06
Input Offset Voltage vs. Ambient Temperature



Figure 3-11. HA1630Q06
Common Mode Input Voltage vs.
Ambient Temperature



Figure 3-12. HA1630Q06
Power Supply Rejection Ratio vs. Frequency



Figure 3-13. HA1630Q06
Common Mode Rejection Ratio vs. Frequency



Figure 3-14. HA1630Q06
Open Loop Voltage Gain and Phase Angle vs. Frequency



Figure 3-15. HA1630Q06
Input Bias Current vs. Ambient Temperature



Figure 3-16. HA1630Q06
Input Bias Current vs. Input Voltage



Figure 3-17. HA1630Q06
Slew Rate (rising) vs. Ambient Temperature



Figure 3-18. HA1630Q06
Slew Rate (falling) vs. Ambient Temperature



Figure 3-19. HA1630Q06
Large Signal Transient Response



Figure 3-20. HA1630Q06
Small Signal Transient Response



Figure 3-21. HA1630Q06
Total Harmonic Distortion + Noise vs.
Output Voltage p-p



Figure 3-22. HA1630Q06
Total Harmonic Distortion + Noise vs.
Output Voltage p-p



Figure 3-23. HA1630Q06
Voltage Output p-p vs. Frequency



Figure 3-24. HA1630Q06
Voltage Noise Density vs. Frequency



Test Circuits

1. Power Supply Rejection Ratio, PSRP & Voltage Offset, V_{IO}



V_{IO}

$$V_{IO} = \left(V_O - \frac{V_{DD}}{2}\right) \times \frac{R_S}{R_S + R_F}$$

PSRR

$$PSRR = -20\log\left(\left|\frac{V_{O1} - V_{O2}}{V_{DD1} - V_{DD2}}\right| \times \frac{R_S}{R_S + R_F}\right)$$

Measure V_O corresponding to V_{DD1} = 2.95 V and V_{DD2} = 3.05 V

2. Supply Current, I_{DD}



3. Input Bias Current, I_{IB}



4. Output High Voltage, V_{OH}



V_{OH}

R_L = 1 MΩ
$V_{IN1} = V_{DD} / 2 - 0.05$ V
$V_{IN2} = V_{DD} / 2 + 0.05$ V

5. Output Low Voltage, V_{OL}



V_{OL}

R_L = 1 MΩ
$V_{IN1} = V_{DD} / 2 + 0.05$ V
$V_{IN2} = V_{DD} / 2 - 0.05$ V

6. Output Source Current, $I_{OSOURCE}$ & Output Sink Current, I_{OSINK}



$I_{OSOURCE}$

$V_O = V_{DD} - 0.5$ V
$V_{IN1} = V_{DD} / 2 - 0.05$ V
$V_{IN2} = V_{DD} / 2 + 0.05$ V

I_{OSINK}

$V_O = + 0.5$ V
$V_{IN1} = V_{DD} / 2 + 0.05$ V
$V_{IN2} = V_{DD} / 2 - 0.05$ V

7. Common Mode Input Voltage, V_{CM} & Common Mode Rejection Ratio, CMRR



CMRR

$$CMRR = -20\log\left(\left|\frac{V_{O1} - V_{O2}}{V_{IN1} - V_{IN2}}\right| \times \frac{R_S}{R_S + R_F}\right)$$

Measure V_O corresponding to $V_{IN1} = 0$ V and $V_{IN2} = 2.1$ V

8. Total Harmonic Distortion, THD





THD

Gain Variable
$1 + R_F / R_S = 100$
freq = 100 Hz, 1 kHz, 10 kHz

9. Slew Rate, SR



10. Gain, A_V & Phase, GBW



Package Dimensions

JEITA Package Code	RENESAS Code	Previous Code	MASS[Typ.]
P-TSSOP14-4.4x5-0.65	PTSP0014JA-B	TTP-14DV	0.05g





Terminal cross section
(Ni/Pd/Au plating)



Detail F

NOTE)
1. DIMENSIONS"*1 (Nom)"AND"*2" DO NOT INCLUDE MOLD FLASH.
2. DIMENSION"*3"DOES NOT INCLUDE TRIM OFFSET.

Reference Symbol	Dimension in Millimeters		
	Min	Nom	Max
D	—	5.00	5.30
E	—	4.40	—
A_2	—	—	—
A_1	0.03	0.07	0.10
A	—	—	1.10
b_p	0.15	0.20	0.25
b_1	—	—	—
c	0.10	0.15	0.20
c_1	—	—	—
θ	0°	—	8°
H_E	6.20	6.40	6.60
e	—	0.65	—
x	—	—	0.13
y	—	—	0.10
Z	—	—	0.83
L	0.4	0.5	0.6
L_1	—	1.0	—

Taping & Reel Specification

[Taping]

Package Code	W	P	Ao	Bo	Ko	E	F	D1	Maximum Storage No.
TSSOP-14	12	8	6.5	5.1	1.5	—	5.5	1.6	2,000 pcs/reel

Unit: mm



[Reel]

Package	Tape width	W1	W2
TSSOP-14	12	17.4	13.4



[Ordering Information]

Ordering Unit
2,000 pcs

Mark Indication



(1) to (4)	Week code		
(5),(8) to (10)	Space		
(6), (7) (11), (12)	Product Name	0Q04	HA1630Q04
		0Q05	HA1630Q05
		0Q06	HA1630Q06

Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!
1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.
Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials
1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors.
Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (http://www.renesas.com).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.

RENESAS SALES OFFICES

http://www.renesas.com

Refer to "**http://www.renesas.com/en/network**" for the latest and detailed information.

Renesas Technology America, Inc.
450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology (Shanghai) Co., Ltd.
Unit 204, 205, AZIACenter, No.1233 Lujiazui Ring Rd, Pudong District, Shanghai, China 200120
Tel: <86> (21) 5877-1818, Fax: <86> (21) 6887-7898

Renesas Technology Hong Kong Ltd.
7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd.
10th Floor, No.99, Fushing North Road, Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology Singapore Pte. Ltd.
1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001

Renesas Technology Korea Co., Ltd.
Kukje Center Bldg. 18th Fl., 191, 2-ka, Hangang-ro, Yongsan-ku, Seoul 140-702, Korea
Tel: <82> (2) 796-3115, Fax: <82> (2) 796-2145

Renesas Technology Malaysia Sdn. Bhd
Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No.18, Jalan Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia
Tel: <603> 7955-9390, Fax: <603> 7955-9510

© 2006. Renesas Technology Corp., All rights reserved. Printed in Japan.

Colophon .6.0