

## VL53L4CX STM32 Nucleo pack with X-NUCLEO-53L4A2 expansion board and NUCLEO-F401RE development board



### Features

- VL53L4CX Time-of-Flight sensor with extended range measurement expansion board (X-NUCLEO-53L4A2)
- NUCLEO-F401RE development board
- 0.25, 0.5, and 1 mm spacers to simulate air gaps
- Two different cover glasses to protect the sensor from the dust
- Equipped with Arduino UNO R3 connectors
- Full system software supplied, including code examples and graphical user interface
- RoHS, CE, UKCA, and China RoHS compliant

### Description

The P-NUCLEO-53L4A2 is a complete evaluation kit that allows you to learn, evaluate, and develop applications using the VL53L4CX Time-of-Flight sensor with extended range measurement.

Specifically designed for long-range, multitarget measurements, the VL53L4CX provides very accurate distance measurements up to 6 m with excellent results over short distances.

A new generation laser emitter with 18° FoV improves the performance under the ambient light.

Thanks to ST patented algorithms and innovative module construction, the VL53L4CX is also able to detect multiple objects within the FoV with depth understanding.

ST histogram algorithms ensure cover glass crosstalk immunity beyond 80 cm and dynamic smudge compensation for targets below 80 cm.

Like all Time-of-Flight sensors based on ST FlightSense technology, the VL53L4CX records an absolute distance measurement regardless of the target color and reflectance.

The NUCLEO-F401RE STM32 Nucleo development board provides an affordable and flexible way for users to try out new ideas and build prototypes with any STM32 microcontroller, choosing from the various combinations of performance, power consumption, and features.

Product summary	
VL53L4CX STM32 Nucleo pack with X-NUCLEO-53L4A2 expansion board and NUCLEO-F401RE development board	P-NUCLEO-53L4A2
P-NUCLEO-53L4A2 pack graphical user interface (GUI)	STSW-IMG030
Time-of-Flight high accuracy proximity sensor	VL53L4CXV0DH/1
STM32 Nucleo-64 development board with STM32F401RE MCU	NUCLEO-F401RE
Time-of-Flight sensor with extended range measurement expansion board based on the VL53L4CX for STM32 Nucleo	X-NUCLEO-53L4A2
Applications	Personal Electronics - Audio and Video/Gaming and Drones/Virtual - Augmented Reality/Wearable

## 1 Laser safety considerations

The VL53L4CX contains a laser emitter and the corresponding drive circuitry.

The laser output is designed to remain within Class 1 laser safety limits under all reasonable foreseeable conditions, including single faults, in compliance with the IEC 60825-1:2014 (third edition).

The laser output remains within Class 1 limits as long as you use the STMicroelectronics recommended device settings and respect the operating conditions specified in the data sheet.

The laser output power must not be increased and no optics should be used with the intention of focusing the laser beam.

**Figure 1. Class 1 laser product label**



## 2 X-NUCLEO-53L4A2 expansion board

---

The [X-NUCLEO-53L4A2](#) expansion board allows you to test the [VL53L4CX](#) functionality and to program it, to understand how to develop an application using the [VL53L4CX](#). It integrates a 3.3 V voltage regulator to supply the [VL53L4CX](#) on the expansion board and the necessary connectivity for the application.

You have to program the [NUCLEO-F401RE](#) development board to control the [X-NUCLEO-53L4A2](#) expansion board.

[X-NUCLEO-53L4A2](#) expansion board and the [NUCLEO-F401RE](#) are connected through the Arduino compatible connectors CN5, CN6, CN8, and CN9.

The Arduino connectors on the [NUCLEO-F401RE](#) support the Arduino Uno revision 3.

### **3 Optional VL53L4CX breakout board**

---

The [SATEL-VL53L4CX](#) is designed to connect remotely the [VL53L4CX](#) sensor to any type of electronic controller. The [VL53L4CX](#) breakout boards can be directly plugged onto the [VL53L4CX](#) expansion board through two 6-pin connectors or can be connected to the [VL53L4CX](#) expansion board through flying wires. Breakout boards can be purchased separately using the reference: [SATEL-VL53L4CX](#). In this pack, two breakout boards are provided.

## 4 Schematic diagrams

---

The P-NUCLEO-53L4A2 kit consists of an X-NUCLEO-53L4A2 expansion board and a NUCLEO-F401RE development board.

You can find the related schematic diagrams at the following links:

- [X-NUCLEO-53L4A2 schematic diagrams](#)
- [NUCLEO-F401RE schematic diagrams](#)

## Revision history

**Table 1. Document revision history**

Date	Revision	Changes
28-Jun-2022	1	Initial release.

**IMPORTANT NOTICE – READ CAREFULLY**

STMicroelectronics NV and its subsidiaries (“ST”) reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST’s terms and conditions of sale in place at the time of order acknowledgment.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of purchasers’ products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, refer to [www.st.com/trademarks](http://www.st.com/trademarks). All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2022 STMicroelectronics – All rights reserved