

Consumer-band BPSK 7.2 kbps PLM PICtail™ Plus Daughter Board Information Sheet

The Consumer-band BPSK 7.2 kbps PLM PICtail™ Plus Daughter Board provides a low cost method for the development and testing of consumer applications implementing a Powerline Communication Softmodem, which is driven by a dsPIC33F device. The daughter board operates at a consumer-band carrier frequency of 129.6 kHz.

Any dsPIC33F device with at least 2 Kbytes RAM, 16 Kbytes of Flash memory, four Output Compare channels, one DMA channel, and one 12-bit ADC input (at least 500 kbps), can be used with this daughter board. Please refer to the user's guide for more details regarding the resource requirements.

The evaluation kit includes a pair of daughter boards and two High Voltage (HV) AC power line adapter cables. Two Explorer 16 boards (purchased separately – PN: DM240001) are required to evaluate the daughter boards. A Microchip programming/debugging tool is also required to program/debug the firmware on the dsPIC33F device.

Installing MPLAB® IDE and C Compilers

The MPLAB Integrated Development Environment (IDE) should be installed prior to using a daughter board for application development. While MPLAB IDE provides the assembler tools for development, demo applications are written in the C language and require a C compiler to be installed. Microchip's MPLAB C Compiler seamlessly integrates into MPLAB IDE. Both the MPLAB IDE and MPLAB C compiler are free (see the note below) and are available for download at www.microchip.com/MPLAB and www.microchip.com/compilers, respectively.

Note: Standard Evaluation (Free) – All optimization levels are enabled for 60 days, but then revert to optimization level 1 only.

Demo Applications and More Information

For free demo source code and more information, please visit the related web page at www.microchip.com/powerline. From the landing page, select **Consumer-band BPSK 7.2 kbps PLM PICtail Plus Daughter Board**. In the download section, select a demo application (such as the Ping-Pong demo), to download an archive file that contains the related demo source code files. Refer to the user's guide in the download section for additional information.

Running the Demo Application

After downloading the ping-pong demo application code and installing the development tools, use the following procedure to run the demonstration:

1. Insert a dsPIC33FJ256GP710A PIM into the first Explorer 16 Development Board.
2. Plug a daughter board into the PICtail Plus expansion slot on this Explorer 16 Development Board and connect the RCA jack of the HV adapter cable (provided in the kit) to the daughter board.
3. Plug the AC end of the HV adapter cable into an 110V/220V power outlet.
4. Connect a Microchip programming/debugging tool to the Explorer 16 Development Board and power up the Explorer 16 Development Board.
5. Double-click the `pingpong.mcp` file to load the ping-pong demo project into MPLAB IDE.
6. Choose your programming tool in MPLAB IDE by selecting *Programmer > Select Programmer*, and then select the tool you are using to program the dsPIC33F device.
7. Build the project by selecting *Project > Build All*.
8. Download your code into the dsPIC33F device by selecting *Programmer > Program*.
9. Repeat steps 1 through 8 for the second daughter board.
10. The demo code previously downloaded pings frames of data back and forth between the two evaluation kits. Initiate the demonstration by pressing the S5 button on either of the Explorer 16 Development Boards. The transmit frame count (TX) and the receive frame count (RX) displayed on the Explorer 16 Development Board LCD screen should increment for both of the daughter boards.

Americas

Atlanta - 678-957-9614
Boston - 774-760-0087
Chicago - 630-285-0071
Cleveland - 216-447-0464
Dallas - 972-818-7423
Detroit - 248-538-2250
Kokomo - 765-864-8360
Los Angeles - 949-462-9523
Phoenix - 480-792-7200
Santa Clara - 408-961-6444
Toronto - 905-673-0699

Asia/Pacific

Australia - Sydney - 61-2-9868-6733
China - Beijing - 86-10-8528-2100
China - Chengdu - 86-28-8665-5511
China - Chongqing - 86-23-8980-9588
China - Hong Kong SAR - 852-2401-1200
China - Nanjing - 86-25-8473-2460
China - Qingdao - 86-532-8502-7355
China - Shanghai - 86-21-5407-5533
China - Shenyang - 86-24-2334-2829
China - Shenzhen - 86-755-8203-2660
China - Wuhan - 86-27-5980-5300
China - Xiamen - 86-592-2388138
China - Xian - 86-29-8833-7252
China - Zhuhai - 86-756-3210040
India - Bangalore - 91-80-3090-4444
India - New Delhi - 91-11-4160-8631
India - Pune - 91-20-2566-1512
Japan - Yokohama - 81-45-471-6166
Korea - Daegu - 82-53-744-4301
Korea - Seoul - 82-2-554-7200
Malaysia - Kuala Lumpur - 60-3-6201-9857
Malaysia - Penang - 60-4-227-8870
Philippines - Manila - 63-2-634-9065
Singapore - 65-6334-8870
Taiwan - Hsin Chu - 886-3-6578-300
Taiwan - Kaohsiung - 886-7-213-7830
Taiwan - Taipei - 886-2-2500-6610
Thailand - Bangkok - 66-2-694-1351

Europe

Austria - Weis - 43-7242-2244-39
Denmark - Copenhagen - 45-4450-2828
France - Paris - 33-1-69-53-63-20
Germany - Munich - 49-89-627-144-0
Italy - Milan - 39-0331-742611
Netherlands - Drunen - 31-416-690399
Spain - Madrid - 34-91-708-08-90
UK - Wokingham - 44-118-921-5869

08/04/10



Microchip Technology Inc. • 2355 West Chandler Blvd. • Chandler, AZ 85224-6199

www.microchip.com

The Microchip name and logo, the Microchip logo, and MPLAB are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. All other trademarks mentioned herein are property of their respective companies.

© 2011, Microchip Technology Incorporated, Printed in the U.S.A. All Rights Reserved. 08/10

DS51954A