

TL592B DIFFERENTIAL VIDEO AMPLIFIER

SLFS001A – JUNE 1985 – REVISED APRIL 1988

- Adjustable Gain to 400 Typ
- No Frequency Compensation Required
- Low Noise ... 3 μ V Typ V_n

description

This device is a monolithic two-stage video amplifier with differential inputs and differential outputs. It features internal series-shunt feedback that provides wide bandwidth, low phase distortion, and excellent gain stability. Emitter-follower outputs enable the device to drive capacitive loads. All stages are current-source biased to obtain high common-mode and supply-voltage rejection ratios.


The differential gain is typically 400 when the gain adjust pins are connected together, or amplification may be adjusted for near 0 to 400 by the use of a single external resistor connected between the gain adjustment pins A and B. No external frequency-compensating components are required for any gain option.

The device is particularly useful in magnetic-tape or disk-file systems using phase or NRZ encoding and in high-speed thin-film or plated-wire memories. Other applications include general-purpose video and pulse amplifiers.


The device achieves low equivalent noise voltage through special processing and a new circuit layout incorporating input transistors with low base resistance.

The TL592B is characterized for operation from 0°C to 70°C.

D8T OR P PACKAGE (TOP VIEW)




D14† OR N PACKAGE (TOP VIEW)



† D8 and D14 are the codes to differentiate the 8-pin and 14-pin versions, respectively.


symbol



TL592B DIFFERENTIAL VIDEO AMPLIFIER

SLFS001A - JUNE 1985 - REVISED APRIL 1988

schematic



Pin numbers are for D8 and P packages.

absolute maximum ratings over operating free-air temperature (unless otherwise noted)

Supply voltage, V_{CC+} (see Note 1)	8 V
Supply voltage, V_{CC-}	-8 V
Differential input voltage	± 5 V
Voltage range, any input	V_{CC+} to V_{CC-}
Output current	10 mA
Continuous total power dissipation	See Dissipation Rating Table
Operating free-air temperature range	0°C to 70°C
Storage temperature range	-65°C to 150°C
Lead temperature 1.6 mm (1/16 inch) from case for 10 seconds	260°C

NOTES: 1. All voltage values except differential input voltages are with respect to the midpoint between V_{CC+} and V_{CC-} .

DISSIPATION RATING TABLE

PACKAGE	$T_A \leq 25^\circ\text{C}$ POWER RATING	DERATING FACTOR	DERATE ABOVE T_A	$T_A = 70^\circ\text{C}$ POWER RATING
D8	530 mW	5.8 mW/ $^\circ\text{C}$	59°C	464 mW
D14	530 mW	N/A	N/A	530 mW
N	530 mW	N/A	N/A	530 mW
P	530 mW	N/A	N/A	530 mW

■ 8961724 0108328 765 ■



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TL592B
DIFFERENTIAL VIDEO AMPLIFIER

SLFS001A – JUNE 1985 – REVISED APRIL 1988

recommended operating conditions

		MIN	NOM	MAX	UNIT
Supply voltage, V _{CC+}		3	6	8	V
Supply voltage, V _{CC-}		-3	-6	-8	V
Operating free-air temperature, T _A		0	70		°C

electrical characteristics at specified free-air temperature, V_{CC} = ±6 V, R_L = 2 kΩ (unless otherwise noted)

PARAMETER	TEST FIGURE	TEST CONDITIONS†	T _A	MIN	TYP	MAX	UNIT
AvD	1	V _{OOPP} = 3 V, R _L = 2 kΩ, R _{AB} = 0	25°C	300	400	500	V/V
			0°C to 70°C	250	600		
AvD2	1	V _{OOPP} = 3 V, R _L = 2 kΩ, R _{AB} = 1 kΩ	25°C		13		V/V
BW	2	V _{OOPP} = 1 V, R _{AB} = 0	25°C		50		MHz
I _{IO}			25°C		0.4	5	μA
			0°C to 70°C			6	
I _{IB}			25°C		9	30	μA
			0°C to 70°C			40	
V _{ICR}	3		25°C	±1			V
			0°C to 70°C	±1			
V _{OC}	1	R _L = ∞	25°C	2.4	2.9	3.4	V
V _{OO}	1	V _{ID} = 0, R _{AB} = ∞, R _L = ∞	25°C		0.35	0.75	V
			0°C to 70°C			1.5	
V _{OOPP}	1	R _L = 2 kΩ, R _{AB} = 0	25°C	3	4		V
			0°C to 70°C		2.8		
r _i		V _{OD} = 1 V, R _{AB} = 0	25°C		4		kΩ
			0°C to 70°C		3.6		
r _o			0°C to 70°C			30	Ω
C _i			25°C		5		pF
CMRR	3	V _{IC} = ±1 V, R _{AB} = 0	25°C	60	86		dB
			f = 5 MHz		60		
			f = 100 kHz	50			
			0°C to 70°C		60		
k _{SVR}	4	ΔV _{CC+} = ±0.5 V, R _{AB} = 0 ΔV _{CC-} = ±0.5 V,	25°C	50	70		dB
			0°C to 70°C	50			
V _n	4	BW = 1 kHz to 10 MHz	25°C		3		μV
t _{pd}	2	ΔV _O = 1 V	25°C		7.5		ns
t _r	2	ΔV _O = 1 V	25°C		10.5		ns
I _{sink(max)}		V _{ID} = 1 V, V _O = 3 V			3	4	mA
I _{CC}		No load, No signal	25°C		18	24	mA
			0°C to 70°C			27	

† R_{AB} is the gain-adjustment resistor connected between gain-adjust pins A and B. If not specified for a particular parameter, its value is irrelevant to that parameter.

■ 8961724 0108329 6T1 ■



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TL592B DIFFERENTIAL VIDEO AMPLIFIER

SLFS001A - JUNE 1985 - REVISED APRIL 1988

PARAMETER MEASUREMENT INFORMATION




Figure 1




Figure 2




Figure 3




Figure 4

8961724 0108330 313

**TEXAS
INSTRUMENTS**

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TYPICAL CHARACTERISTICS

LARGE-SIGNAL DIFFERENTIAL
VOLTAGE AMPLIFICATION
VS
SUPPLY VOLTAGE




Figure 5

LARGE-SIGNAL DIFFERENTIAL
VOLTAGE AMPLIFICATION
VS
GAIN-ADJUSTMENT RESISTANCE




Figure 6

SUPPLY CURRENT
VS
SUPPLY VOLTAGE




Figure 7

■ 8961724 0108331 25T ■

**TEXAS
INSTRUMENTS**

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265