



BGU7004

SiGe:C Low Noise Amplifier MMIC for GPS, GLONASS, Galileo and Compass

Rev. 3 — 18 January 2017

Product data sheet

1. Product profile

1.1 General description

The BGU7004 is, also known as the GPS1103M, an AEC-Q100 qualified Low Noise Amplifier (LNA) for GNSS receiver applications in a plastic leadless 6-pin, extremely small SOT886 package. The BGU7004 requires only one external matching inductor and one external decoupling capacitor.

The BGU7004 adapts itself to the changing environment resulting from co-habitation of different radio systems in modern cellular handsets. It has been designed for low power consumption and optimal performance when jamming signals from co-existing cellular transmitters are present. At low jamming power levels it delivers 16.5 dB gain at a noise figure of 0.85 dB. During high jamming power levels, resulting for example from a cellular transmit burst, it temporarily increases its bias current to improve sensitivity.

1.2 Features and benefits

- AEC-Q100 qualified (see [Section 9.1](#))
- Covers full GNSS L1 band, from 1559 MHz to 1610 MHz
- Noise figure (NF) = 0.85 dB and gain (G_p) = 16.5 dB
- High input 1 dB compression point P_i (1dB) of -11 dBm
- High out of band $IP3_i$ of 9 dBm
- Supply voltage 1.5 V to 2.85 V
- Power-down mode current consumption < 1 μ A
- Optimized performance at low supply current of 4.5 mA
- Integrated matching for the output
- Requires only one input matching inductor and one supply decoupling capacitor
- Input and output DC decoupled
- ESD protection on all pins (HBM > 2 kV)
- Integrated temperature stabilized bias for easy design
- Small 6-pin leadless package 1 mm \times 1.45 mm \times 0.5 mm
- 110 GHz transit frequency - SiGe:C technology

1.3 Applications

- LNA for GPS, GLONASS, Galileo and Compass (BeiDou) in automotive applications like Toll Collection and Emergency Call.



- LNA for GPS, GLONASS, Galileo and Compass (BeiDou) in smart phones, feature phones, tablet PCs, Personal Navigation Devices, Digital Still Cameras, Digital Video Cameras, RF Front End modules, complete GPS chipset modules and theft protection (laptop, ATM).

1.4 Quick reference data

Table 1. Quick reference data

$f = 1559 \text{ MHz to } 1610 \text{ MHz}$; $V_{CC} = 1.8 \text{ V}$; $P_i < -40 \text{ dBm}$; $T_{amb} = 25^\circ\text{C}$; input matched to 50Ω using a 5.6 nH inductor; unless otherwise specified.

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|------------------|--------------------------------------|---|-----|------|------|------|
| V_{CC} | supply voltage | RF input AC coupled | 1.5 | - | 2.85 | V |
| I_{CC} | supply current | $V_{ENABLE} \geq 0.8 \text{ V}$ | | | | |
| | | $P_i < -40 \text{ dBm}$ | 3.2 | 4.5 | 5.7 | mA |
| | | $P_i = -20 \text{ dBm}$ | 8.1 | 11.6 | 14.4 | mA |
| G_p | power gain | $P_i < -40 \text{ dBm}$, no jammer | 14 | 16.5 | 19 | dB |
| | | $P_i = -20 \text{ dBm}$, no jammer | 15 | 17.5 | 20 | dB |
| NF | noise figure | $P_i < -40 \text{ dBm}$, no jammer [1] | - | 0.85 | 1.2 | dB |
| | | $P_i < -40 \text{ dBm}$, no jammer [2] | - | 0.9 | 1.3 | dB |
| | | $P_i = -20 \text{ dBm}$, no jammer | - | 1.2 | 1.6 | dB |
| $P_{i(1dB)}$ | input power at 1 dB gain compression | $f = 1559 \text{ MHz to } 1610 \text{ MHz}$ | | | | |
| | | $V_{CC} = 1.5 \text{ V}$ | -15 | -12 | - | dBm |
| | | $V_{CC} = 1.8 \text{ V}$ | -14 | -11 | - | dBm |
| | | $V_{CC} = 2.85 \text{ V}$ | -11 | -8 | - | dBm |
| IP3 _i | input third-order intercept point | $f = 1.575 \text{ GHz}$ | | | | |
| | | $V_{CC} = 1.5 \text{ V}$ [3] | 5 | 8 | - | dBm |
| | | $V_{CC} = 1.8 \text{ V}$ [3] | 5 | 9 | - | dBm |
| | | $V_{CC} = 2.85 \text{ V}$ [3] | 5 | 12 | - | dBm |

[1] PCB losses are subtracted.

[2] Including PCB losses.

[3] $f_1 = 1713 \text{ MHz}$; $f_2 = 1851 \text{ MHz}$; $P_1 = P_2 = -30 \text{ dBm}$.

2. Pinning information

Table 2. Pinning

| Pin | Description | Simplified outline | Graphic symbol |
|-----|-------------|-----------------------------|----------------|
| 1 | GND | <p>Transparent top view</p> | |
| 2 | GND | | |
| 3 | RF_IN | | |
| 4 | V_{CC} | | |
| 5 | ENABLE | | |
| 6 | RF_OUT | | |

3. Ordering information

Table 3. Ordering information

| Type number | Package | | Version |
|-------------|---------|---|---------|
| | Name | Description | |
| BGU7004 | XSON6 | plastic extremely thin small outline package; no leads; 6 terminals; body 1 × 1.45 × 0.5 mm | SOT886 |

4. Marking

Table 4. Marking codes

| Type number | Marking code |
|-------------|--------------|
| BGU7004 | UY |

5. Limiting values

Table 5. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).

| Symbol | Parameter | Conditions | Min | Max | Unit |
|---------------|-------------------------|----------------------|-------------|----------------|------|
| V_{CC} | supply voltage | RF input AC coupled | -0.5 | 3.1 | V |
| V_{ENABLE} | voltage on pin ENABLE | $V_{CC} \geq 2.5$ V | -0.5 | 3.1 | V |
| | | $V_{CC} < 2.5$ V | [2] -0.5 | $V_{CC} + 0.6$ | V |
| V_{RF_IN} | voltage on pin RF_IN | DC | | | |
| | | $V_{CC} \geq 3.0$ V | [3] -0.5 | 3.6 | V |
| | | $V_{CC} < 3.0$ V | [2][3] -0.5 | $V_{CC} + 0.6$ | V |
| V_{RF_OUT} | voltage on pin RF_OUT | DC | | | |
| | | $V_{CC} \geq 1.8$ V | [3] -0.5 | 3.6 | V |
| | | $V_{CC} < 1.8$ V | [2][3] -0.5 | $V_{CC} + 1.8$ | V |
| P_i | input power | | - | 0 | dBm |
| P_{tot} | total power dissipation | $T_{sp} \leq 130$ °C | [1] | 55 | mW |
| T_{stg} | storage temperature | | -65 | 150 | °C |
| T_j | junction temperature | | - | 150 | °C |

[1] T_{sp} is the temperature at the soldering point of the emitter lead.

[2] Due to internal ESD diode protection, the applied voltage should not exceed the specified maximum in order to avoid excess current.

[3] The RF input and RF output are AC coupled through internal DC blocking capacitors.

6. Thermal characteristics

Table 6. Thermal characteristics

| Symbol | Parameter | Conditions | Typ | Unit |
|----------------|--|------------|-----|------|
| $R_{th(j-sp)}$ | thermal resistance from junction to solder point | | 225 | K/W |

7. Characteristics

Table 7. Characteristics

$f = 1559 \text{ MHz to } 1610 \text{ MHz}$; $V_{CC} = 1.8 \text{ V}$; $V_{ENABLE} \geq 0.8 \text{ V}$; $P_i < -40 \text{ dBm}$; $T_{amb} = 25 \text{ }^\circ\text{C}$; input matched to $50 \text{ } \Omega$ using a 5.6 nH inductor; unless otherwise specified.

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|--|---------------------|--|-----|------|------|------------------|
| V_{CC} | supply voltage | RF input AC coupled | 1.5 | - | 2.85 | V |
| I_{CC} | supply current | $V_{ENABLE} \geq 0.8 \text{ V}$ | | | | |
| | | $P_i < -40 \text{ dBm}$ | 3.2 | 4.5 | 5.7 | mA |
| | | $P_i = -20 \text{ dBm}$ | 8.1 | 11.6 | 14.4 | mA |
| | | $V_{ENABLE} \leq 0.3 \text{ V}$ | - | - | 1 | μA |
| T_{amb} | ambient temperature | | -40 | +25 | +125 | $^\circ\text{C}$ |
| G_p | power gain | $T_{amb} = 25 \text{ }^\circ\text{C}$ | | | | |
| | | $P_i < -40 \text{ dBm}$, no jammer | 14 | 16.5 | 19 | dB |
| | | $P_i = -20 \text{ dBm}$, no jammer | 15 | 17.5 | 20 | dB |
| | | $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 850 \text{ MHz}$ | 15 | 17.5 | 20 | dB |
| | | $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 1850 \text{ MHz}$ | 15 | 17.5 | 20 | dB |
| | | $-40 \text{ }^\circ\text{C} \leq T_{amb} \leq +125 \text{ }^\circ\text{C}$ | | | | |
| | | $P_i < -40 \text{ dBm}$, no jammer | 13 | - | 20 | dB |
| | | $P_i = -20 \text{ dBm}$, no jammer | 14 | - | 21 | dB |
| | | $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 850 \text{ MHz}$ | 14 | - | 21 | dB |
| | | $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 1850 \text{ MHz}$ | 14 | - | 21 | dB |
| RL_{in} | input return loss | $P_i < -40 \text{ dBm}$ | 5 | 8 | - | dB |
| | | $P_i = -20 \text{ dBm}$ | 6 | 10 | - | dB |
| RL_{out} | output return loss | $P_i < -40 \text{ dBm}$ | 10 | 20 | - | dB |
| | | $P_i = -20 \text{ dBm}$ | 10 | 14 | - | dB |
| ISL | isolation | | 20 | 23 | - | dB |
| NF | noise figure | $T_{amb} = 25 \text{ }^\circ\text{C}$ | | | | |
| | | $P_i < -40 \text{ dBm}$, no jammer [1] | - | 0.85 | 1.2 | dB |
| | | $P_i < -40 \text{ dBm}$, no jammer [2] | - | 0.9 | 1.3 | dB |
| | | $P_i = -20 \text{ dBm}$, no jammer | - | 1.2 | 1.6 | dB |
| | | $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 850 \text{ MHz}$ | - | 1.1 | 1.5 | dB |
| | | $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 1850 \text{ MHz}$ | - | 1.3 | 1.7 | dB |
| | | $-40 \text{ }^\circ\text{C} \leq T_{amb} \leq +125 \text{ }^\circ\text{C}$ | | | | |
| | | $P_i < -40 \text{ dBm}$, no jammer | - | - | 1.8 | dB |
| | | $P_i = -20 \text{ dBm}$, no jammer | - | - | 2.0 | dB |
| | | $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 850 \text{ MHz}$ | - | - | 1.9 | dB |
| $P_{jam} = -20 \text{ dBm}$; $f_{jam} = 1850 \text{ MHz}$ | - | - | 2.1 | dB | | |

Table 7. Characteristics ...continued

$f = 1559 \text{ MHz to } 1610 \text{ MHz}$; $V_{CC} = 1.8 \text{ V}$; $V_{ENABLE} \geq 0.8 \text{ V}$; $P_i < -40 \text{ dBm}$; $T_{amb} = 25 \text{ }^\circ\text{C}$; input matched to $50 \text{ } \Omega$ using a 5.6 nH inductor; unless otherwise specified.

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit |
|--------------|--------------------------------------|---|---------|-----|-----|---------------|
| $P_{i(1dB)}$ | input power at 1 dB gain compression | $f = 1559 \text{ MHz to } 1610 \text{ MHz}$ | | | | |
| | | $V_{CC} = 1.5 \text{ V}$ | -15 | -12 | - | dBm |
| | | $V_{CC} = 1.8 \text{ V}$ | -14 | -11 | - | dBm |
| | | $V_{CC} = 2.85 \text{ V}$ | -11 | -8 | - | dBm |
| | | $f = 806 \text{ MHz to } 928 \text{ MHz}$ | | | | |
| | | $V_{CC} = 1.5 \text{ V}$ | [3] -15 | -12 | - | dBm |
| | | $V_{CC} = 1.8 \text{ V}$ | [3] -14 | -11 | - | dBm |
| | | $V_{CC} = 2.85 \text{ V}$ | [3] -14 | -11 | - | dBm |
| | | $f = 1612 \text{ MHz to } 1909 \text{ MHz}$ | | | | |
| | | $V_{CC} = 1.5 \text{ V}$ | [3] -13 | -10 | - | dBm |
| | | $V_{CC} = 1.8 \text{ V}$ | [3] -12 | -9 | - | dBm |
| | | $V_{CC} = 2.85 \text{ V}$ | [3] -10 | -7 | - | dBm |
| $IP3_i$ | input third-order intercept point | $f = 1.575 \text{ GHz}$ | | | | |
| | | $V_{CC} = 1.5 \text{ V}$ | [4] 5 | 8 | - | dBm |
| | | $V_{CC} = 1.8 \text{ V}$ | [4] 5 | 9 | - | dBm |
| | | $V_{CC} = 2.85 \text{ V}$ | [4] 5 | 12 | - | dBm |
| t_{on} | turn-on time | | [5] - | - | 2 | μs |
| t_{off} | turn-off time | | [5] - | - | 1 | μs |
| K | Rollett stability factor | | 1 | - | - | |

- [1] PCB losses are subtracted.
- [2] Including PCB losses.
- [3] Out of band.
- [4] $f_1 = 1713 \text{ MHz}$; $f_2 = 1851 \text{ MHz}$; $P_1 = P_2 = -30 \text{ dBm}$.
- [5] Within 10 % of the final gain.

Table 8. ENABLE (pin 5)

$-40 \text{ }^\circ\text{C} \leq T_{amb} \leq +125 \text{ }^\circ\text{C}$; $1.5 \text{ V} \leq V_{CC} \leq 2.85 \text{ V}$

| $V_{ENABLE} \text{ (V)}$ | State |
|--------------------------|-------|
| ≤ 0.3 | OFF |
| ≥ 0.8 | ON |

8. Application information

8.1 GNSS LNA







Table 9. List of components

For schematics see [Figure 1](#).


| Component | Description | Value | Supplier | Remarks |
|-----------|--------------------------------|--------|---------------|---------|
| C1 | decoupling capacitor | 1 nF | various | |
| IC1 | BGU7004 | - | NXP | |
| L1 | high quality matching inductor | 5.6 nH | Murata LQW15A | |






$V_{CC} = 1.8 \text{ V}; P_i = -45 \text{ dBm}$.
 (1) $T_{amb} = -40 \text{ }^\circ\text{C}$
 (2) $T_{amb} = +25 \text{ }^\circ\text{C}$
 (3) $T_{amb} = +85 \text{ }^\circ\text{C}$
 (4) $T_{amb} = +125 \text{ }^\circ\text{C}$

Fig 4. Power gain as a function of frequency; typical values




$V_{CC} = 1.8 \text{ V}; T_{amb} = 25 \text{ }^\circ\text{C}$.
 (1) $P_i = -45 \text{ dBm}$
 (2) $P_i = -30 \text{ dBm}$
 (3) $P_i = -20 \text{ dBm}$
 (4) $P_i = -15 \text{ dBm}$

Fig 5. Power gain as a function of frequency; typical values




$P_i = -45 \text{ dBm}; T_{amb} = 25 \text{ }^\circ\text{C}$.
 (1) $V_{CC} = 1.5 \text{ V}$
 (2) $V_{CC} = 1.8 \text{ V}$
 (3) $V_{CC} = 2.85 \text{ V}$

Fig 6. Power gain as a function of frequency; typical values




$T_{amb} = 25 \text{ }^\circ\text{C}; f = 1575 \text{ MHz}$.
 (1) $V_{CC} = 1.5 \text{ V}$
 (2) $V_{CC} = 1.8 \text{ V}$
 (3) $V_{CC} = 2.85 \text{ V}$

Fig 7. Power gain and supply current as a function of input power; typical values




f = 1575 MHz; T_{amb} = 25 °C; no jammer.

Fig 8. Noise figure as a function of supply voltage; typical values




f = 1575 MHz; T_{amb} = 25 °C; no jammer.

Fig 9. Noise figure as a function of supply voltage; typical values



f = 1575 MHz; V_{CC} = 1.8 V; no jammer.


Fig 10. Noise figure as a function of ambient temperature; typical values



f_{jam} = 850 MHz; T_{amb} = 25 °C; f = 1575 MHz.


- (1) V_{CC} = 1.5 V
- (2) V_{CC} = 1.8 V
- (3) V_{CC} = 2.85 V

Fig 11. Noise figure as a function of jamming power; typical values




$f_{jam} = 1850 \text{ MHz}; T_{amb} = 25 \text{ }^\circ\text{C}; f = 1575 \text{ MHz}.$
 (1) $V_{CC} = 1.5 \text{ V}$
 (2) $V_{CC} = 1.8 \text{ V}$
 (3) $V_{CC} = 2.85 \text{ V}$

Fig 12. Noise figure as a function of jamming power; typical values




$V_{CC} = 1.8 \text{ V}; P_i = -45 \text{ dBm}.$
 (1) $T_{amb} = -40 \text{ }^\circ\text{C}$
 (2) $T_{amb} = +25 \text{ }^\circ\text{C}$
 (3) $T_{amb} = +85 \text{ }^\circ\text{C}$
 (4) $T_{amb} = +125 \text{ }^\circ\text{C}$

Fig 13. Input return loss as a function of frequency; typical values




$V_{CC} = 1.8 \text{ V}; T_{amb} = 25 \text{ }^\circ\text{C}.$
 (1) $P_i = -45 \text{ dBm}$
 (2) $P_i = -30 \text{ dBm}$
 (3) $P_i = -20 \text{ dBm}$
 (4) $P_i = -15 \text{ dBm}$

Fig 14. Input return loss as a function of frequency; typical values




$P_i = -45 \text{ dBm}; T_{amb} = 25 \text{ }^\circ\text{C}.$
 (1) $V_{CC} = 1.5 \text{ V}$
 (2) $V_{CC} = 1.8 \text{ V}$
 (3) $V_{CC} = 2.85 \text{ V}$

Fig 15. Input return loss as a function of frequency; typical values




$T_{amb} = 25\text{ }^{\circ}\text{C}$; $f = 1575\text{ MHz}$.
 (1) $V_{CC} = 1.5\text{ V}$
 (2) $V_{CC} = 1.8\text{ V}$
 (3) $V_{CC} = 2.85\text{ V}$

Fig 16. Input return loss as a function of input power; typical values




$V_{CC} = 1.8\text{ V}$; $P_i = -45\text{ dBm}$.
 (1) $T_{amb} = -40\text{ }^{\circ}\text{C}$
 (2) $T_{amb} = +25\text{ }^{\circ}\text{C}$
 (3) $T_{amb} = +85\text{ }^{\circ}\text{C}$
 (4) $T_{amb} = +125\text{ }^{\circ}\text{C}$

Fig 17. Output return loss as a function of frequency; typical values




$V_{CC} = 1.8\text{ V}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$.
 (1) $P_i = -45\text{ dBm}$
 (2) $P_i = -30\text{ dBm}$
 (3) $P_i = -20\text{ dBm}$
 (4) $P_i = -15\text{ dBm}$

Fig 18. Output return loss as a function of frequency; typical values




$P_i = -45\text{ dBm}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$.
 (1) $V_{CC} = 1.5\text{ V}$
 (2) $V_{CC} = 1.8\text{ V}$
 (3) $V_{CC} = 2.85\text{ V}$

Fig 19. Output return loss as a function of frequency; typical values




$T_{amb} = 25\text{ }^{\circ}\text{C}$; $f = 1575\text{ MHz}$.
 (1) $V_{CC} = 1.5\text{ V}$
 (2) $V_{CC} = 1.8\text{ V}$
 (3) $V_{CC} = 2.85\text{ V}$

Fig 20. Output return loss as a function of input power; typical values




$V_{CC} = 1.8\text{ V}$; $P_i = -45\text{ dBm}$.
 (1) $T_{amb} = -40\text{ }^{\circ}\text{C}$
 (2) $T_{amb} = +25\text{ }^{\circ}\text{C}$
 (3) $T_{amb} = +85\text{ }^{\circ}\text{C}$
 (4) $T_{amb} = +125\text{ }^{\circ}\text{C}$

Fig 21. Isolation as a function of frequency; typical values




$V_{CC} = 1.8\text{ V}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$.
 (1) $P_i = -45\text{ dBm}$
 (2) $P_i = -30\text{ dBm}$
 (3) $P_i = -20\text{ dBm}$
 (4) $P_i = -15\text{ dBm}$

Fig 22. Isolation as a function of frequency; typical values




$P_i = -45\text{ dBm}$; $T_{amb} = 25\text{ }^{\circ}\text{C}$.
 (1) $V_{CC} = 1.5\text{ V}$
 (2) $V_{CC} = 1.8\text{ V}$
 (3) $V_{CC} = 2.85\text{ V}$

Fig 23. Isolation as a function of frequency; typical values




$T_{amb} = 25\text{ }^{\circ}\text{C}$; $f = 1575\text{ MHz}$.
 (1) $V_{CC} = 1.5\text{ V}$
 (2) $V_{CC} = 1.8\text{ V}$
 (3) $V_{CC} = 2.85\text{ V}$

Fig 24. Isolation as a function of input power; typical values




$f = 850\text{ MHz}$.
 (1) $T_{amb} = -40\text{ }^{\circ}\text{C}$
 (2) $T_{amb} = +25\text{ }^{\circ}\text{C}$
 (3) $T_{amb} = +85\text{ }^{\circ}\text{C}$
 (4) $T_{amb} = +125\text{ }^{\circ}\text{C}$

Fig 25. Input power at 1 dB gain compression as a function of supply voltage; typical values







$f = 1850\text{ MHz}$.
 (1) $T_{amb} = -40\text{ }^{\circ}\text{C}$
 (2) $T_{amb} = +25\text{ }^{\circ}\text{C}$
 (3) $T_{amb} = +85\text{ }^{\circ}\text{C}$
 (4) $T_{amb} = +125\text{ }^{\circ}\text{C}$

Fig 26. Input power at 1 dB gain compression as a function of supply voltage; typical values



$f = 1575\text{ MHz}$.
 (1) $T_{amb} = -40\text{ }^{\circ}\text{C}$
 (2) $T_{amb} = +25\text{ }^{\circ}\text{C}$
 (3) $T_{amb} = +85\text{ }^{\circ}\text{C}$
 (4) $T_{amb} = +125\text{ }^{\circ}\text{C}$

Fig 27. Input power at 1 dB gain compression as a function of supply voltage; typical values



8.2 GPS front-end

The GPS LNA is typically used in a GPS front-end. A GPS front-end application circuit and its characteristics is provided here.




Table 10. List of components
For schematics see [Figure 32](#).

| Component | Description | Value | Supplier | Remarks |
|------------|--------------------------------|--------|------------------------|---|
| BPF1, BPF2 | GPS SAW filter | - | Murata SAFEA1G57KE0F00 | Alternatives from Epcos: <ul style="list-style-type: none"> B9444 Alternatives from Murata: <ul style="list-style-type: none"> SAFEA1G57KH0F00 SAFEA1G57KB0F00 Alternatives from Fujitsu: <ul style="list-style-type: none"> FAR-F6KA-1G5754-L4AA FAR-F6KA-1G5754-L4AJ |
| C1 | decoupling capacitor | 1 nF | Various | |
| IC1 | BGU7004 | - | NXP | |
| L1 | high quality matching inductor | 5.6 nH | Murata LQW15A | |

8.3 Characteristics GPS front-end

Table 11. Characteristics GPS front-end

$f = 1575$ MHz; $V_{CC} = 1.8$ V; $V_{ENABLE} \geq 0.8$ V; power at LNA input $P_i < -40$ dBm; $T_{amb} = 25$ °C; input and output matched to 50 Ω ; unless otherwise specified.

| Symbol | Parameter | Conditions | Min | Typ | Max | Unit | |
|--------------|--------------------------------------|------------------------------------|-----|------|------|---------|-----|
| V_{CC} | supply voltage | RF input AC coupled | 1.5 | - | 2.85 | V | |
| I_{CC} | supply current | | - | 4.5 | - | mA | |
| G_p | power gain | power at LNA input $P_i < -40$ dBm | [1] | - | 14.5 | - | dB |
| | | power at LNA input $P_i = -20$ dBm | [1] | - | 15.5 | - | dB |
| RL_{in} | input return loss | power at LNA input $P_i < -40$ dBm | [1] | - | 8.5 | - | dB |
| | | power at LNA input $P_i = -20$ dBm | [1] | - | 10.5 | - | dB |
| RL_{out} | output return loss | power at LNA input $P_i < -40$ dBm | [1] | - | 14.5 | - | dB |
| | | power at LNA input $P_i = -20$ dBm | [1] | - | 12.5 | - | dB |
| NF | noise figure | power at LNA input $P_i < -40$ dBm | [1] | - | 1.8 | - | dB |
| | | power at LNA input $P_i = -20$ dBm | [1] | - | 1.9 | - | dB |
| $P_{i(1dB)}$ | input power at 1 dB gain compression | $f = 1575$ MHz | | -8.2 | | dBm | |
| | | $f = 806$ MHz to 928 MHz | [2] | 31 | | dBm | |
| | | $f = 1612$ MHz to 1909 MHz | [2] | 40 | | dBm | |
| $IP3_i$ | input third-order intercept point | | [3] | 64 | | dBm | |
| α | attenuation | $f = 850$ MHz | [4] | 95 | - | - | dBc |
| | | $f = 1850$ MHz | [4] | 90 | - | - | dBc |
| t_{on} | turn-on time | | [5] | - | 2 | μ s | |
| t_{off} | turn-off time | | [5] | - | 1 | μ s | |

[1] Power at GPS front-end input = power at LNA input + attenuation BPF1.

[2] Out of band.

[3] $f_1 = 1713$ MHz; $f_2 = 1851$ MHz; $P_1 = P_2 = +10$ dBm.

[4] Relative to $f = 1575$ MHz.

[5] Within 10 % of the final gain.

9. Test information

9.1 Quality information

All qualification tests are performed according AEC-Q100 except for read point testing (final test of qualification sample). Which is done only at room temperature.

As part of the zero defect program, the following is part of the industrial test flow:

- Part Average Testing
- Maverick Lot Handling at assembly factory

10. Package outline

XSON6: plastic extremely thin small outline package; no leads; 6 terminals; body 1 x 1.45 x 0.5 mm

SOT886




Fig 33. Package outline SOT886 (XSON6)

11. Handling information

CAUTION



This device is sensitive to ElectroStatic Discharge (ESD). Observe precautions for handling electrostatic sensitive devices.

Such precautions are described in the *ANSI/ESD S20.20*, *IEC/ST 61340-5*, *JESD625-A* or equivalent standards.

12. Abbreviations

Table 12. Abbreviations

| Acronym | Description |
|---------|---|
| AEC | Automotive Electronics Council |
| ATM | Automated Teller Machine (cash dispenser) |
| BPF | Band-Pass Filter |
| ESD | ElectroStatic Discharge |
| GLONASS | GLObal NAvigation Satellite System |
| GNSS | Global Navigation Satellite System |
| GPS | Global Positioning System |
| HBM | Human Body Model |
| MMIC | Monolithic Microwave Integrated Circuit |
| PCB | Printed Circuit Board |
| SAW | Surface Acoustic Wave |
| SiGe:C | Silicon Germanium Carbon |

13. Revision history

Table 13. Revision history

| Document ID | Release date | Data sheet status | Change notice | Supersedes |
|----------------|---|--------------------|---------------|-------------|
| BGU7004 v.3 | 20170118 | Product data sheet | - | BGU7004 v.2 |
| Modifications: | <ul style="list-style-type: none"> Section 1: added GPS1103M according to our new naming convention | | | |
| BGU7004 v.2 | 20150220 | Product data sheet | - | BGU7004 v.1 |
| Modifications: | <ul style="list-style-type: none"> The title of this data sheet has been changed. Section 1.3 on page 1: Added GLONASS, Galileo and Compass (BeiDou) to the possible applications. Section 11 on page 17: ESD information has moved from Section 1.1 to this section. Section 14.3 on page 18: Adjusted the disclaimers with respect to “suitability to use in automotive applications” and “Translations”. | | | |
| BGU7004 v.1 | 20110705 | Product data sheet | - | - |

14. Legal information

14.1 Data sheet status

| Document status ^{[1][2]} | Product status ^[3] | Definition |
|-----------------------------------|-------------------------------|---|
| Objective [short] data sheet | Development | This document contains data from the objective specification for product development. |
| Preliminary [short] data sheet | Qualification | This document contains data from the preliminary specification. |
| Product [short] data sheet | Production | This document contains the product specification. |

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <http://www.nxp.com>.

14.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

14.3 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use in automotive applications — This NXP Semiconductors product has been qualified for use in automotive applications. Unless otherwise agreed in writing, the product is not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Translations — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

14.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

15. Contact information

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: salesaddresses@nxp.com

16. Contents

| | | |
|-----------|--|-----------|
| 1 | Product profile | 1 |
| 1.1 | General description | 1 |
| 1.2 | Features and benefits | 1 |
| 1.3 | Applications | 1 |
| 1.4 | Quick reference data | 2 |
| 2 | Pinning information | 2 |
| 3 | Ordering information | 3 |
| 4 | Marking | 3 |
| 5 | Limiting values | 3 |
| 6 | Thermal characteristics | 3 |
| 7 | Characteristics | 4 |
| 8 | Application information | 6 |
| 8.1 | GNSS LNA | 6 |
| 8.2 | GPS front-end | 14 |
| 8.3 | Characteristics GPS front-end | 15 |
| 9 | Test information | 15 |
| 9.1 | Quality information | 15 |
| 10 | Package outline | 16 |
| 11 | Handling information | 17 |
| 12 | Abbreviations | 17 |
| 13 | Revision history | 17 |
| 14 | Legal information | 18 |
| 14.1 | Data sheet status | 18 |
| 14.2 | Definitions | 18 |
| 14.3 | Disclaimers | 18 |
| 14.4 | Trademarks | 19 |
| 15 | Contact information | 19 |
| 16 | Contents | 20 |

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP Semiconductors N.V. 2017.

All rights reserved.

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 18 January 2017

Document identifier: BGU7004