

0.75 METER LENGTH



Connector A
132245
SMA Jack Right Angle
Bulkhead - Rear Mount Brass Gold + Heatshrink

50 Ohm RG-316
Continuity/Hi-Pot

Connector B
FA1-NZSJ-C01-0
FAKRA Jack Straight
Brass Nickel + Heatshrink

Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink
Assembly shall be built with SN96.5 LEAD FREE solder.
See Routing Notes for additional assembly & testing instructions.

Connector A		Cable		Connector B	
Part #:	132245	Part #:	RG-316	Part #:	FA1-NZSJ-C01-0
Description:	SMA R/A BHD JK RG174 RG316 LMR100 500	Description:	RG-316 - ST 0.102	Description:	FAKRA-Z JK RG174 RG316 500
Type:	SMA	Dielectric:	ST	Type:	FAKRA
Gender:	Jack	Shielding:	Braid	Gender:	Jack
Body Type:	Right Angle	Diameter:	0.102	Body Type:	Straight
Contact Type:	Solder	Impedance:	50 Ohm	Contact Type:	Crimp
Polarity:	Standard	Sheathing:	None	Polarity:	Standard
Impedance:	50 Ohm	Testing:	Continuity Hi-Pot	Impedance:	50 Ohm
Mounting:	Bulkhead - Rear Mount	Length:	0.75 Meter	Mounting:	Cable
Body Material:	Brass			Body Material:	Brass
Body Finish:	Gold			Body Finish:	Nickel
IP Rating:	None			IP Rating:	None
Contact Material:	Beryllium Copper			Contact Material:	Beryllium Copper
Contact Finish:	Gold			Contact Finish:	Gold
Max. Freq.:	12.4 GHz			Max. Freq.:	3 GHz
Booting:	SMA Jack Right Angle			Booting:	FAKRA-Z Jack Straight
				Clocking:	0°



CONTROLLED DOCUMENT - DO NOT COPY

THIS DRAWING MAY CONTAIN PATENTED OR PROPRIETARY INFORMATION AND MUST NOT BE USED FOR ANY PURPOSE DETRIMENTAL TO CUSTOM CABLE INC. IT MAY NOT BE REPRODUCED OR TRANSCRIBED IN ANY FORM WITHOUT THE WRITTEN CONSENT OF CUSTOM CABLE INC. ACCEPTANCE OF THIS DRAWING ESTABLISHES AND AGREEMENT OF THE FOREGOING.

Title:
SMA-RA-JK/FKRAZ-ST-JK G316 0.75M

Part No:
Q-2P05E0005.75M

UNLESS SPECIFIED
TOLERANCE:
0-18 inches +/- 1/2"
over 18" +/- 2%
ASSEMBLY:
CENTER LABEL IF LENGTH
IS LESS THAN 12 INCHES