

## 3-5/6 Digits 5999 Counts Smart True-RMS Flex Clamp Meter

Item: MT-3112

- 3-5/6 digits 5999 counts
- Frequency range: 40-2000 Hz
- Dual display with back-light
- Auto power off
- Low battery indication
- Data hold

The Smart True-RMS Flex Clamp Meter fits into tight spaces and around large conductors to detect readings of noisy, distorted or non-sinusoidal waveforms.



ACA True-RMS	60A/600A/3000A±(2%+5d) (40Hz -65Hz) 60A/600A/3000A±(3%+5d) (65Hz -200Hz) ≤1000A±(3%+5d), >1000A (200Hz -1000Hz) for reference
ACV True-RMS	6V /60V/600V ±(1.2%+3d) (45Hz~65Hz) 6V /60V/600V ±(2.0%+5d) (40Hz~45Hz,65Hz~2000Hz)
DCV	6V/60V/600V ±(0.8%+3d)
Resistance	6K/60K/600K/6M ±(1.0%+3d)
Frequency	40~10kHz ±(0.5%+2d)
Extra functions	Display hold, LCD Backlight, Low Battery, Auto power off, LED light
Safety	CE CATIV 600V
Power Supply	1.5V AAA x 3
Size HxWxD	12.8 x 7.0 x 1.2 in

**Order Today! [SalesSupport@EclipseTools.com](mailto:SalesSupport@EclipseTools.com)**

Eclipse Enterprises, Inc. • Tel: 804.561.2610 • Fax: 804.561.2642

13302 Chula Road, Amelia Court House, VA 23002 • [EclipseTools.com](http://EclipseTools.com)