



ALPHA & OMEGA
SEMICONDUCTOR

AO4728

30V N-Channel MOSFET

SRFET™

General Description

SRFET™ AO4728 uses advanced trench technology with a monolithically integrated Schottky diode to provide excellent $R_{DS(ON)}$, and low gate charge. This device is ideally suited for use as a low side switch in CPU core power conversion.



Product Summary

V_{DS} (V) = 30V
 I_D = 20A $(V_{GS} = 10V)$
 $R_{DS(ON)} < 4.3m\Omega$ $(V_{GS} = 10V)$
 $R_{DS(ON)} < 6m\Omega$ $(V_{GS} = 4.5V)$

100% UIS Tested
100% R_g Tested



SOIC-8



SRFET™
Soft Recovery MOSFET:
Integrated Schottky Diode

Absolute Maximum Ratings $T_A=25^\circ C$ unless otherwise noted

Parameter	Symbol	Maximum	Units
Drain-Source Voltage	V_{DS}	30	V
Gate-Source Voltage	V_{GS}	± 20	V
Continuous Drain Current ^A	I_D	20	A
$T_C=70^\circ C$		17	
Pulsed Drain Current ^C	I_{DM}	146	A
Avalanche Current ^C	I_{AR}	40	A
Repetitive avalanche energy $L=0.1mH$ ^C	E_{AR}	80	mJ
Power Dissipation ^B	P_D	3.1	W
$T_C=70^\circ C$		2	
Junction and Storage Temperature Range	T_J, T_{STG}	-55 to 150	°C

Thermal Characteristics

Parameter	Symbol	Typ	Max	Units
Maximum Junction-to-Ambient ^A	$R_{\theta JA}$	31	40	°C/W
Maximum Junction-to-Ambient ^{A,D}		59	75	°C/W
Maximum Junction-to-Lead	$R_{\theta JL}$	16	24	°C/W

Electrical Characteristics ($T_J=25^\circ\text{C}$ unless otherwise noted)

Symbol	Parameter	Conditions	Min	Typ	Max	Units
STATIC PARAMETERS						
BV_{DSS}	Drain-Source Breakdown Voltage	$I_D=250\mu\text{A}, V_{GS}=0\text{V}$	30			V
I_{DSS}	Zero Gate Voltage Drain Current	$V_{DS}=30\text{V}, V_{GS}=0\text{V}$ $T_J=125^\circ\text{C}$		0.1	20	mA
I_{GSS}	Gate-Body leakage current	$V_{DS}=0\text{V}, V_{GS}= \pm 20\text{V}$		0.1		μA
$V_{\text{GS(th)}}$	Gate Threshold Voltage	$V_{DS}=V_{GS}, I_D=250\mu\text{A}$	1.2	1.8	2.2	V
$I_{\text{D(ON)}}$	On state drain current	$V_{GS}=10\text{V}, V_{DS}=5\text{V}$	146			A
$R_{\text{DS(ON)}}$	Static Drain-Source On-Resistance	$V_{GS}=10\text{V}, I_D=20\text{A}$ $T_J=125^\circ\text{C}$	3.6	4.3		$\text{m}\Omega$
		$V_{GS}=4.5\text{V}, I_D=18\text{A}$	5.5	6.6		
g_{FS}	Forward Transconductance	$V_{DS}=5\text{V}, I_D=20\text{A}$	87			S
V_{SD}	Diode Forward Voltage	$I_S=1\text{A}, V_{GS}=0\text{V}$	0.4	0.7		V
I_S	Maximum Body-Diode Continuous Current			6		A
DYNAMIC PARAMETERS						
C_{iss}	Input Capacitance	$V_{GS}=0\text{V}, V_{DS}=15\text{V}, f=1\text{MHz}$	2975	3719	4463	pF
C_{oss}	Output Capacitance		485	693	900	pF
C_{rss}	Reverse Transfer Capacitance		204	340	476	pF
R_g	Gate resistance	$V_{GS}=0\text{V}, V_{DS}=0\text{V}, f=1\text{MHz}$	0.28	0.56	0.84	Ω
SWITCHING PARAMETERS						
$Q_g(10\text{V})$	Total Gate Charge	$V_{GS}=10\text{V}, V_{DS}=15\text{V}, I_D=20\text{A}$	48	60	72	nC
$Q_g(4.5\text{V})$	Total Gate Charge		20	25	30	nC
Q_{gs}	Gate Source Charge		12	15	18	nC
Q_{gd}	Gate Drain Charge		6	10	14	nC
$t_{\text{D(on)}}$	Turn-On Delay Time	$V_{GS}=10\text{V}, V_{DS}=15\text{V}, R_L=0.75\Omega, R_{\text{GEN}}=3\Omega$		9.2		ns
t_r	Turn-On Rise Time			10.7		ns
$t_{\text{D(off)}}$	Turn-Off Delay Time			40		ns
t_f	Turn-Off Fall Time			12.5		ns
t_{rr}	Body Diode Reverse Recovery Time	$I_F=20\text{A}, dI/dt=500\text{A}/\mu\text{s}$	10	13	16	ns
Q_{rr}	Body Diode Reverse Recovery Charge	$I_F=20\text{A}, dI/dt=500\text{A}/\mu\text{s}$	21	26.5	32	nC

A. The value of R_{BJA} is measured with the device mounted on 1in² FR-4 board with 2oz. Copper, in a still air environment with $T_A = 25^\circ\text{C}$. The value in any given application depends on the user's specific board design.

B. The power dissipation P_D is based on $T_{J(\text{MAX})}=150^\circ\text{C}$, using $\leq 10\text{s}$ junction-to-ambient thermal resistance.

C. Repetitive rating, pulse width limited by junction temperature $T_{J(\text{MAX})}=150^\circ\text{C}$. Ratings are based on low frequency and duty cycles to keep initial $T_J=25^\circ\text{C}$.

D. The R_{BJA} is the sum of the thermal impedance from junction to lead R_{BLJ} and lead to ambient.

E. The static characteristics in Figures 1 to 6 are obtained using $<300\mu\text{s}$ pulses, duty cycle 0.5% max.

F. These curves are based on the junction-to-ambient thermal impedance which is measured with the device mounted on 1in² FR-4 board with 2oz. Copper, assuming a maximum junction temperature of $T_{J(\text{MAX})}=150^\circ\text{C}$. The SOA curve provides a single pulse rating.

Rev1: Nov. 2010

COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS ARE NOT AUTHORIZED. AOS DOES NOT ASSUME ANY LIABILITY ARISING OUT OF SUCH APPLICATIONS OR USES OF ITS PRODUCTS. AOS RESERVES THE RIGHT TO IMPROVE PRODUCT DESIGN, FUNCTIONS AND RELIABILITY WITHOUT NOTICE.


TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS


Fig 1: On-Region Characteristics (Note E)




Figure 2: Transfer Characteristics (Note E)




Figure 3: On-Resistance vs. Drain Current and Gate Voltage (Note E)




Figure 4: On-Resistance vs. Junction Temperature (Note E)




Figure 5: On-Resistance vs. Gate-Source Voltage (Note E)




Figure 6: Body-Diode Characteristics (Note E)


TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS


Figure 7: Gate-Charge Characteristics




Figure 8: Capacitance Characteristics




Figure 9: Single Pulse Avalanche capability (Note C)




Figure 10: Maximum Forward Biased Safe Operating Area (Note F)




Figure 11: Single Pulse Power Rating Junction-to-Ambient (Note F)


TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS

Figure 12: Normalized Maximum Transient Thermal Impedance (Note F)


TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS

Figure 13: Diode Reverse Leakage Current vs. Junction Temperature




Figure 14: Diode Forward voltage vs. Junction Temperature




Figure 15: Diode Reverse Recovery Charge and Peak Current vs. Conduction Current




Figure 16: Diode Reverse Recovery Time and Softness Factor vs. Conduction Current




Figure 17: Diode Reverse Recovery Charge and Peak Current vs. di/dt








Figure 18: Diode Reverse Recovery Time and Softness Factor vs. di/dt



Gate Charge Test Circuit & Waveform



Resistive Switching Test Circuit & Waveforms



Unclamped Inductive Switching (UIS) Test Circuit & Waveforms



Diode Recovery Test Circuit & Waveforms

