6 INCHES LENGTH



Connector A 132260 SMA Jack Right Angle Bulkhead - Rear Mount Brass Gold + Heatshrink 50 Ohm RG-142 Continuity/Hi-Pot Connector B 142203 SMB Plug Right Angle Brass Gold + Heatshrink

Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

Connector B Connector			A		Cable		Connector B		
90° 45° 0° 225° 770° Connector A	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting:	132260 SMA R/A BHD JK RG55 RG142 RG223 500 SMA Jack Right Angle Solder Standard 50 Ohm Bulkhead - Rear Mount Brass Gold None : Beryllium Copper Gold 12.4 GHz SMA Jack Right Angle		Part #: Description: Dielectric: Shielding: Diameter: Impedance: Sheathing: Testing: Length:	RG-142 RG-142 - ST 0.195 ST Braid 0.195 50 Ohm None Continuity Hi-Pot 6 Inches	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting: Clocking:	142203 SMB PLUG RG55 RG142 RG223 500 SMB Plug Right Angle Solder Standard 50 Ohm Cable Brass Gold None Beryllium Copper Gold 4 GHz SMB Plug Right Angle 0°		
Amphenol CUSTOM CABLE CONTROLLED DOCUMENT - DO NOT COPY			AND MUST NOT BE U TAL TO CUSTOM CA CED OR TRANSCRIB VRITTEN CONSENT C NCE OF THIS DRAW	BLE ED DF ING Part No:	SMA-RA-JK/SMB-RA-PL G142 6I Part No:		UNLESS SPECIFIED TOLERANCE: 0-18 inches +/- 1/2" over 18" +/- 2% ASSEMBLY: CENTER LABEL IF LENGTH IS LESS THAN 12 INCHES		