


Circuit Protection Terminals

KDKS 1

Warning:

- Install AP partition after last ASK 1 or KDKS 1.
- Disconnect power before replacing the fuse.



Fuse terminals are available with LED blown fuse indicators, which speed identification of fuse failures and reduces costly down time. The maximum operating voltage for the indicator fuse blocks is determined by the LED's rating.

A 2 mA residual current passes through the LED when the fuse is blown, unless otherwise indicated.

	combi-foot		with power on indication		with blown fuse indicator (BFI) and circuit disconnect
Fuse & Feed Through 5 x 20, 5 x 25 mm fuse	Fuse & Feed Through 5 x 20, 5 x 25 mm fuse	Fuse & Feed Through 5 x 20, 5 x 25 mm fuse	Fuse & Feed Through 5 x 20, 5 x 25 mm fuse	Fuse & Feed Through 5 x 20 mm fuse	

Note:
In the event of a faulty fuse, the connected circuit has a max. leakage current of .55 mA. With lever open, load is disconnected completely.

Terminal Block Selection Data

Available Options	Version	Part No.	Part No.	Part No.	Part No.			
	Beige PA	950331	950335					
	Beige Wemid	953244						
	24 VDC Hinge -				990850			
	24 VDC Hinge +				990851			
	6 VDC / 12 VAC			9133151111				
	12 VDC / 24 VAC			9134521111				
	24 VDC / 48 VAC			9134531111				
	60 VDC / 120 VAC			9134551111				
	120 VDC / 240 VAC			9134561111	990960			
	48 VDC Hinge -			9134541111				
	120 VAC/DC				990852			
Dimensions								
Width / Length / Height mm (in.)	for TS 35	8/73.5/55.7 (.31/2.89/2.19)	8/73.5/55.7 (.31/2.89/2.19)	8/73.5/55.7 (.31/2.89/2.19)	8/73.5/55.7 (.31/2.89/2.19)			
Insulation stripping length	mm (in.)	9 (.35)	9 (.35)	9 (.35)	9 (.35)			
Technical Data								
Rated voltage / rated current / wire size	UL	300 V / 10/20 A† / #22...12 AWG	300 V / 10/20 A† / #22...12 AWG	300 V / 10/20 A† / #22...12 AWG	300 V / 10/20 A† / #22...12 AWG††			
	CSA	300 V / 10/25 A† / #22...12 AWG	300 V / 10/25 A† / #22...12 AWG	300 V / 10/25 A† / #22...12 AWG	300 V / 10/25 A† / #22...12 AWG			
	VDE	500 V / 6.3 A* / 4 mm²	500 V / 6.3 A* / 4 mm²					
Torque	Nm (lb. in.)	0.6 (5.5)	0.6 (5.5)	0.6 (5.5)	0.6 (5.5)			
Clamping screw	M	3	3	3	3			
Selected Accessory Data†								
End Plate (AP) (thickness mm)	Type	Part No.	Type	Part No.	Type	Part No.	Type	Part No.
	Beige PA	AP KDKS 1 (1.5) 950333	AP KDKS 1 (1.5) 950333	AP KDKS 1 (1.5) 950333	AP KDKS 1 (1.5) 950333	AP KDKS 1 (1.5) 950333	AP KDKS 1 (1.5) 950333	
	Beige Wemid	AP KDKS 1 (1.5) 953247						
Jumpers								
	2 pole	QB2 46110	QB2 46110	QB2 46110	QB2 46110	QB2 46110	QB2 46110	
	3 pole	QB3 46120	QB3 46120	QB3 46120	QB3 46120	QB3 46120	QB3 46120	
	4 pole	QB4 46130	QB4 46130	QB4 46130	QB4 46130	QB4 46130	QB4 46130	
G Fuse Cartridges, 5 x 20 mm								
Rated current (A): 0.10 rapid-blow		43030	43030	43030	43030	43030	43030	
Rated voltage 250 VAC	0.20 rapid-blow	43040	43040	43040	43040	43040	43040	
Note: For listing of 5 x 25 mm fuses see page 34.	0.25 rapid-blow	43050	43050	43050	43050	43050	43050	
	0.50 rapid-blow	43060	43060	43060	43060	43060	43060	
	1.0 rapid-blow	43070	43070	43070	43070	43070	43070	
	2.0 rapid-blow	43090	43090	43090	43090	43090	43090	
	3.15 rapid-blow	43110	43110	43110	43110	43110	43110	
	5.0 rapid-blow	43130	43130	43130	43130	43130	43130	
Disconnect Lever Accessories								
Spare lever	TH	37706	TH 37706	TH 37706	TH 37706	TH 37706	TH 37706	
Spare lever - BFI 24 VDC H-							990866	
Spare lever - BFI 24 VDC H+							990867	
Spare lever - BFI 120 VAC/DC							990868	
Red pull lever	SIHA	159302	SIHA 159302					
Brass slug (solid)	SBL	44610	SBL 44610					
Brass slug (hollow)	SBL	201275	SBL 201275					
Plastic strip for ganging levers**	Sch S2	33740	Sch S2 33740	Sch S2 33740	Sch S2 33740	Sch S2 33740	Sch S2 33740	
Tools								
Screwdriver	SD	903701	SD 903701	SD 903701	SD 903701	SD 903701	SD 903701	
Marking Tags								
	Print							
Consecutive horizontal	DEK 5/6.5	468160001	DEK 5/6.5 468160001	DEK 5/6.5 468160001	DEK 5/6.5 468160001	DEK 5/6.5 468160001	DEK 5/6.5 468160001	
Consecutive vertical	DEK 5/6.5	468260001	DEK 5/6.5 468260001	DEK 5/6.5 468260001	DEK 5/6.5 468260001	DEK 5/6.5 468260001	DEK 5/6.5 468260001	
Note: Part numbers shown are for a single card of pre-printed tags numbered 1-50. For additional information, see Accessories section.								

RAIL MOUNTED TERMINAL BLOCKS: W-SERIES

† See Accessories section for additional information.

†† Pending

*Rated thermal current to VDE 0611 = 6.3 A, when used for short-circuit fusing up to 15 A (VDE).

**Provided in one meter strips.

Note: For 13/32 x 1 1/2 fuses, use SAKS 4 (part no. 17822), ratings 600 V / 30 A / #20...8 AWG

† 10 A upper level (fused), 20 A lower level (feed-through) - UL

† 10 A upper level (fused), 25 A lower level (feed-through) - CSA