

## **LED Light Engine**

3.0" Round Module With 24 Nichia LEDs



Rev 8-10-2017









#### **Electrical Specifications** Constant-Current **Driver Type: Drive Current:** 350mA Nominal Nom. Forward Voltage: 17.9V **Total Board Power:** 6.3W Nominal 50,000 Hrs, 70% lumen maint. @ Ta max 40°C, used as specified Life: Input Current: 1.30 Amps max Max Junction Temp: 80°C Max Test Point Temp: -40°C to +60°C Ambient Operating Temp: -40°C to +80°C Storage Temp: Viewing Angle (FWHM): 120° Lambertian distribution CRI: 83 typical

#### 3.0 Inch Round DC LED Module @ 350mA

0.23 [5.84]

**Dimensions** 

R 0.07 [1.78]

Ø 3.00 [76.2]

| Model | Total Board<br>Power (W) | Total<br>Current (mA) | Color<br>Temp (K) | Lumens<br>(± 15%) | Board<br>LPW |
|-------|--------------------------|-----------------------|-------------------|-------------------|--------------|
| 98013 | 6.3                      | 350                   | 2700              | 769               | 123          |
| 98014 | 6.3                      | 350                   | 3000              | 820               | 131          |
| 98015 | 6.3                      | 350                   | 3500              | 860               | 137          |
| 98016 | 6.3                      | 350                   | 4000              | 883               | 141          |
| 98031 | 6.3                      | 350                   | 5000              | 910               | 144          |



- Constant-Current DC Array, 6 LED Series x 4 Parallel Strings
- Designed for easy use in standard luminaires
- Tight LED pitch eliminates pixelization, no complex lens or optics required
- Color: 1/4 ANSI Binning, 3 Step MacAdam Ellipse
- Applications: Commercial or Residential Downlights
- Customizable: Engines can be modified to your application. Contact us.
- Engineered by Norlux
- 5 yr. Warranty

# 0.15 [3.81] 1.00 [25.4] DC IN Red (+) 12" #22AWG Blue (-) 12" #22AWG

2.83 [71.88]

## **Connectivity Options** (blank)

12 IN, #22 AWG Stranded Leads No Leads Push-in Connectors

For Poke-In Connectors, use #24-18 AWG stranded or solid wire

 $\star$  MADE IN USA  $\star$ 

Ø 2.7 [68.58] B.C. For Cutouts Drawing N0900-0163-R02 IN [mm]

0.062 [1.58] FR-4 PCB 0.020 0.51 LEDs 0.082 [2.08] TOTAL



## **LED Light Engine**



3.0" Round Module With 24 Nichia LEDs

## **CIE Chromaticity Coordinates:**

### 2700K

3 Step Macadams Ellipse

| Х      | Υ      |
|--------|--------|
| 0.4576 | 0.4183 |
| 0.4698 | 0.4212 |
| 0.4478 | 0.3999 |
| 0.4591 | 0.4025 |
| 0.4591 | 0.4025 |

## 3000K

3 Step Macadams Ellipse

| Х      | Υ      |
|--------|--------|
| 0.4325 | 0.4101 |
| 0.4452 | 0.4146 |
| 0.4244 | 0.3923 |
| 0.4362 | 0.3965 |
|        |        |

## 3500K

3 Step Macadams Ellipse

| Х      | Υ      |
|--------|--------|
| 0.4045 | 0.3975 |
| 0.4189 | 0.4044 |
| 0.3989 | 0.3819 |
| 0.412  | 0.3875 |
|        |        |

### 4000K

3 Step Macadams Ellipse


| 0.3836 |
|--------|
|        |
| 0.3906 |
| 0.3687 |
| 0.3757 |
|        |

### 5000K

3 Step Macadams Ellipse

| X      | Υ      |  |
|--------|--------|--|
| 0.3408 | 0.3461 |  |
| 0.3485 | 0.3520 |  |
| 0.3416 | 0.3585 |  |
| 0.3499 | 0.3644 |  |

#### Relative Luminous Flux / Tc Temperature



## **Compatible TRP Drivers:**

The drivers listed here are all compatible with this module. Choose the best driver for your application.

• LED12W-36-C0350-D

## **Step Dimming:**


This Light Engine can be step-dimmed, with a recommended TRP dimmable driver and SD series step-dimming module. See the SD2 or SD3 data sheet for wiring information.


## Series/Parallel Configurations

Parallel: The positive and negative of one board is connected to the respective positive and negative of the next. Current adds, so the supply must be 2x the current for 2 boards.

Series:

The negative of one board is connected to the positive of the next. Voltage adds, so the supply must be 2x the voltage for 2 boards.





## Maximum Run Lengths

The max number of boards wired in a chain (series) is limited by the max current rating of the first board wired to the driver. The sum of the board currents, in the chain, funnels through the first board. Multiple chains can connect directly to the power supply in parallel. See table for max chain length.

| Product  | Series/Parallel       | Max Allowable Boards |             |  |
|----------|-----------------------|----------------------|-------------|--|
| Flouuct  | <u>Series/Faranei</u> | High Current (Nom)   | Low Current |  |
| 3" Round | Series                | 10                   | N/A         |  |

## **Mounting Notes**

The LED assembly is supplied with mounting holes, per the dimensional drawing. It is important to mount the board in such a way as to maintain the To point below the max. The steady state thermals in application will dictate if the board needs to be mounted directly to metallic housing and/or include a thermal pad. For example fully enclosed recessed fixture will require better thermal mounting than an open air pendant.

## Thermal Application Notes

This board requires additional heat sinking to run above 45°C ambient at nominal specifications. Heat sink is also required when operated above specified drive currents.

## **Maximum Current**

Max Current: 720mA

Voltage at max current: 20V, Power at max current: 14.4W

The total maximum current reflects the LED maximum forward current only. without considering thermal needs. Driving the LEDs this hard will likely violate their thermal limits, depending on the application. Tc point must remain at or below the max temperature, or the warranty will be voided. Temperature is directly correlated to LED current.

## **Static Sensitive Device**

Handle only at static-safe work stations.

### **Packaging**

50 per box standard.