

# Power Transformer Chassis Mount: Quick Pack

# F3-36

### **Description:**

The F3-36 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

## Electrical Specifications (@25C);

Maximum Power: 2.4VA

Input Voltage: 115VAC@50/60Hz Output Voltage: 36VCT@0.065A

Hipot: 2500VAC primary to secondary; 1500VAC windings to core.

#### Construction:

Split bobbin non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering. Built with UL Class B Insulation System.

#### Safety:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.



#### Dimensions:


Difficilisions:							
	Α	В	С	D	Е	F	G
	1.187	1.75±.03	2.062	1.187	1.625	.187 Dia	.562

Notes: 1. Units: inches.


2. Terminal size: .187" X 0.021".


3. Weight: .25 lbs


### **Schematic:**



Input: 1 to 3
Output: 4 to 6







**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

Web: www.TriadMagnetics.com Phone 951-277-0757

Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571

Publish Date: April 18, 2019