

# Model 2183



## USB2.0 to Fiber Optic Media Converter



### Features:

- Supports USB 2.0 over fiber
- Power, Link Status, and Host LED indicators
- LC optical connectors
- Din Rail Mounting Option
- Connects to UHCI, OHCI and EHCI Host
- Improved Operation for Vista Operating System
- Supports USB 1.1 and 2.0 Host Controller
- Works with National Instrument Controllers

S.I.Tech 2183/2184 USB media converter pair extends the range of USB 2.0 beyond the USB 5 meter limit. The USB media converters are compliant with the USB 2.0 specification supporting low speed(1.5 Mbps), full speed(12 Mbps), and high speed(480 Mbps) USB data transfer.

The 2183/2184 are enumerated as generic USB hub and provide a 4-port USB hub at distances up to 2 Km over fiber optic cable. The 2183 connects to host PC through USB type B connector. The 2184 connects to USB peripherals through USB type A connector.

- Operation Mode:** USB 2.0
- Input/Output Interface:** USB Type B
- Transmission Line Interface:** LC optical connector is standard
- Transmission Distance:** See distance chart
- Transmitter Output Power:** MMF -9dBm Minimum  
62.5micron  
SMF -9dBm Minimum
- System Wavelength:** 850 or 1300 nm
- Data Rate:** 1.5 (USB 1.0), 12 (USB 1.1), and 480 (USB 2.0) Mbps
- Bit Error Rate:** 10<sup>-9</sup>
- Receiver Sensitivity:** MMF(850nm) -17 dBm minimum  
MMF(1300nm) -20 dBm minimum  
SMF(1300nm) -20 dBm minimum
- Operating Temperature:** 0 °C to 70 °C
- Weight:** 0.75 lb (340 grams)
- Input Power:** 5 VDC Locking Power Jack & Conn.  
External with power supply - 5W typical (S.I.Tech #2166 - 100 to 240 VAC, 50/60 Hz, to 5VDC, UL, CE, & TUVGS Listed)
- Metal Enclosure:** Din Rail Mounting

### OPERATING DISTANCE FOR FIBER OPTIC CABLE

Fiber Size (Microns)	Attenuation dB/Km		Bandwidth MHz/Km		Distance Meters		Distance Feet	
	850nm	1300nm	850nm	1300nm	850nm	1300nm	850nm	1300nm
50	3.0	1.5	600	600	500	600	1650	1800
62.5	4.0	1.5	200	600	275	600	900	1800
10 SM	Unspecified	0.4	Unspecified	Unspecified	-	5000	-	16000

SM - Single mode option - 1300nm (Application limits may be exceeded)  
Optical Unit Connection: Connect the optical transmission line to the T and R receptacles. Note which cable channel goes to Tx or Rx by noting cable imprint  
If you are using Laser Enhanced multimode fiber, depending upon its bandwidth, longer distances may be possible.

Meets FCC requirements of Class B, Part 15 Computing Devices Standard, USB Standard.

Specifications subject to change without notice.



Note: 2183/2184 require USB2.0 root hub support from USB 2.0 host controller. The USB 2.0 host controller will be identified in the Windows Device Manager as "Enhanced" or EHCI controller.

