

# Power Transformer Chassis Mount: Quick Pack

# F5-24

# **Description:**

The F5-24 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

#### Electrical Specifications (@25C);

Maximum Power: 12.0VA Input Voltage: 115VAC@50/60Hz Output Voltage: 24VCT@0.5A<sup>1</sup>

Recommended Fuse: UL listed 250VAC, 700mA, Slo-Blo

Hipot: 2500VAC primary to secondary; 1500VAC windings to core.

## **Construction:**

Split bobbin non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering. Built with UL Class B Insulation System.

#### Safety:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.

UL: File E65390, UL5085-1 and 3, Class 3



## **Dimensions:**


1	A	В	С	D	Е	F	G
1.6	625	2.375	2.812	1.375	1.937	.187 Dia	.812

Notes: 1. Units: inches.

2. Terminal size: .187" X 0.021".

3. Weight: .70 lbs

#### **Schematic:**



Input: Input 2 & 3 Output: 5 to 8


**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.


\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

Web: www.TriadMagnetics.com
Phone 951-277-0757
Fax 951-277-2757

22520B Temescal Canyon Road
Corona, California
92883







<sup>&</sup>lt;sup>1</sup> Fuse must be used on **secondary** as conditions of acceptability for UL Class 2/3 operation.