



REVISIONS			
REV	DESCRIPTION	DATE	APPROVED
01 ₂	REVISED	PATLAN 7-28-98	<i>[Signature]</i> 3/31/99
B	PER EC 0U20-0694-00	10/2/01	<i>[Signature]</i> 10/2/01

HOUSING COUPLING NUT	STAINLESS STEEL PER ASTM-A484 AND ASTM-A582, TYPE 303	PASSIVATE PER QQ-P-35
DIELECTRIC	PTFE FLUOROCARBON PER ASTM-D-1457	N/A
CONTACT EXT.	BERYLLIUM COPPER PER ASTM-B-196 OR ASTM-B-197, ALLOY C17300, CONDITION H	GOLD PLATE PER MIL-G-45204
CENTER CONTACT	BRASS PER ASTM-B-16, HALF HARD	GOLD PLATE PER MIL-G-45204
INNER SLEEVE SPLIT WASHER	BRASS PER ASTM-B-16, HALF HARD	NICKEL PLATE
SPRING WASHER	BERYLLIUM COPPER PER ASTM-B-194, ALLOY C17200, CONDITION H	NICKEL PLATE
CAP	VINYL PLASTIC	N/A
GASKET	SILICONE RUBBER PER ZZ-R-765	N/A

ELECTRICAL	MECHANICAL	ENVIRONMENTAL
Nominal Impedance (Ohms) <u>50</u>	Interface Dimensions MIL-STD-348A, Fig. 301-1 BNC	Temperature Rating <u>-65 TO +165°C</u>
Frequency Range (GHz) DC to <u>4.0</u>	Fig. 304-2 OSN	Shock MIL-STD-202, Method 213, Condition I
Volt Rating (VRMS MAX) @ Sea Level <u>500</u>	Recommended Mating Torque <u>N/A</u>	Moisture Resistance MIL-STD-202, Method 106
VSWR <u>1.35 MAX @ 0.5 TO 4 GHz</u>	Mating Characteristics: Insertion (MAX Lbs) <u>2.0</u>	Corrosion - MIL-STD-202, Method 101, Condition B, 5% salt spray
Insertion Loss (dB MAX) <u>0.1 MAX @ 3 GHz</u>	Withdrawal (MIN Oz) <u>2.0</u>	
RF Leakage (dB MIN) <u>-55 @ 2-3 GHz</u>	Force to Engage and Disengage (In-Lbs MAX) <u>6.0 BNC</u>	
Corona, 70,000 Ft (VRMS MIN) <u>375</u>	<u>3.0 OSN</u>	
Dielectric Withstanding Voltage (VRMS MIN) @ Sea Level <u>1,500</u>	Center Contact Captivation Axial (Lbs) <u>6.0</u>	
Contact Resistance (Milliohms MAX) Center Contact <u>2.0</u>	Radial (In-Oz) <u>N/A</u>	
Outer Contact <u>1.5</u>	Cable Retention Axial Force (Lbs) <u>NA</u>	
Cable to Housing <u>N/A</u>	Torque (In-Oz) <u>N/A</u>	
RF High Potential @ Sea Level (VRMS MIN @ 5 MHz) <u>1,000</u>	Weight (Grams) <u>TBD</u>	
LR.(Megohms MIN) <u>5,000</u>		

COMPONENT	MATERIAL	FINISH
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES		
FRAC. ± 1/64	DEC. ± .005	ANGLES ± 1°
DRAWN BY SA DATE 9-16-86		AMP Incorporated 140 Fourth Avenue Waltham, MA 02451-7599
CHECKED BY BGH DATE 9-16-86		
APP'D BY RL DATE 9-17-86		
USE ASSY PROCEDURE		TITLE "N" JACK TO "BNC" PLUG COAXIAL ADAPTER
NO. A.P. <u>N/A</u>		SIZE B CODE IDENT NO. 26805 3082-2321-00 REV 01 ₂
SCALE 3:1		SHEET 1 OF 1

.XXX = in
XX.X = mm (REF)

These drawings and specifications are the property of AMP Interconnect Div. and shall not be reproduced or copied or used in whole or in part as the basis for the manufacture or sale of item(s) without written permission.