



DPDT Ramses N 3GHz Latching Indicators 12Vdc Positive common

Diodes D-sub connector with bracket

PAGE 1/2 ISSUE 10-07-19 SERIE : DPDT PART NUMBER : R577042045

### RF CHARACTERISTICS

Frequency range : 0 - 3 GHz Impedance : 50 Ohms

Frequency (GHz)	DC - 1	1 - 2	2 - 3
VSWR max	1.15	1.20	1.25
Insertion loss max	0.15 dB	0.20 dB	0.25 dB
Isolation min	85 dB	80 dB	75 dB
Average power (*)	700 W	500 W	400 W

### **ELECTRICAL CHARACTERISTICS**

Actuator : LATCHING
Nominal current \*\* : 320 mA

Actuator voltage (Vcc) : 12V (10.2 to 13V) / POSITIVE COMMON

Terminals : 9 pins D-SUB male connector

Indicator rating : 1 W / 30 V / 100 mA

## MECHANICAL CHARACTERISTICS

Connectors : N female per MIL-C 39012

Life : 2.5 million cycles

Switching Time\*\*\* : < 15 ms

Construction : Splashproof

Weight : < 215 g

# **ENVIRONMENTAL CHARACTERISTICS**

Operating temperature range : -40°C to +85°C Storage temperature range : -55°C to +85°C

(\* Average power at 25°C per RF Path)

(\*\* At 25° C ±10%)

(\*\*\* Nominal voltage; 25° C)









DPDT Ramses N 3GHz Latching Indicators 12Vdc Positive common Diodes D-sub connector with bracket

PAGE 2/2 ISSUE 10-07-19 SERIE : DPDT PART NUMBER : R577042045


# DRAWING [0.880] 22.35 | 4 x M4 depth 7 | 7 | 9 | 7 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1 | 9 | 1




# LABEL




RADIALL® R577042045 0 - 3 GHz Un : 12V Lot : \_\_\_\_





General tolerances: ±0,5 mm [0,02 in]

## SCHEMATIC DIAGRAM



Voltage	RF Continuity	Ind.
+C -1	$1 \leftrightarrow 3 / 2 \leftrightarrow 4$	C.1
+C -2	$1 \leftrightarrow 2 / 3 \leftrightarrow 4$	C.2