

## Switchmode/High Frequency Toroidal Inductor

# **FIT50-5**

## **Description:**

The FIT50-5 toroidal inductor is specifically designed to minimize transients. It stores energy and therefore, conditions the output signal by leveling the current waveform providing a more stable current supply. Generally used in high frequency circuits, its standard design provides an economical solution in differential mode applications or as an output inductor.

### Electrical Specifications (@25C):

| Min. Induc | tance (μH)      | Rated | Max      |  |
|------------|-----------------|-------|----------|--|
| No Bias    | No Bias At Bias |       | DCR (mΩ) |  |
| 16.76      | 9.50            | 5.7   | 20.0     |  |

Note: No Bias inductance measured at .25V, 10KHZ.

#### **Dimensions:**

| Α    | В    | С    | D    | Е    | F    | G         |
|------|------|------|------|------|------|-----------|
| .700 | .475 | .750 | .300 | .474 | .125 | .032±.003 |

Units: In inches

Weight: .012 lbs.

#### **Technical Notes:**

- 1. Nominal inductance values are typically 10% higher than minimal rating.
- 2. Biased inductance measured at rated DC amps.
- 3. Operation at rated current yields approximately 40°C temperature rise over 20°C ambient.

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\*Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics website for the most current version. For soldering and washing information please see http://www.triadmagnetics.com/faq.html





