

# BLF6G27-100; BLF6G27LS-100

WiMAX power LDMOS transistor

Rev. 02 — 8 July 2010

Product data sheet

## 1. Product profile

### 1.1 General description

100 W LDMOS power transistor for base station applications at frequencies from 2500 MHz to 2700 MHz.

**Table 1. Typical performance**

Typical RF performance at  $T_{case} = 25\text{ °C}$  in a class-AB production test circuit.

Mode of operation	f (MHz)	V <sub>DS</sub> (V)	P <sub>L(AV)</sub> (W)	G <sub>p</sub> (dB)	η <sub>D</sub> (%)	ACPR <sub>885k</sub> (dBc)	ACPR <sub>1980k</sub> (dBc)	ACPR <sub>5M</sub> (dBc)	ACPR <sub>10M</sub> (dBc)
<b>BLF6G27-100</b>									
1-carrier W-CDMA [1]	2500 to 2700	28	14	16.5	23	-	-	-40	-59
1-carrier N-CDMA [2]	2500 to 2700	28	14	17	23	-50 [3]	-65 [3]	-	-
<b>BLF6G27LS-100</b>									
1-carrier W-CDMA [1]	2500 to 2700	28	14	17	23	-	-	-41	-60
1-carrier N-CDMA [2]	2500 to 2700	28	14	17	23	-50 [3]	-65 [3]	-	-

[1] Signal is a one carrier, TM1 W-CDMA signal with 64 DPCH and 100 % clipping. PAR is 9.65 dB at 0.01 % probability on CCDF.

[2] Single carrier IS-95 with pilot, paging, sync and 6 traffic channels (Walsh codes 8 to 13). PAR = 9.7 dB at 0.01 % probability on the CCDF. Channel bandwidth is 1.2288 MHz.

[3] Measured within 30 kHz bandwidth.

### 1.2 Features and benefits

- Typical 1-carrier W-CDMA performance (single carrier W-CDMA TM1 with 64 DPCH and 100 % clipping; PAR = 9.65 dB at 0.01 % probability on the CCDF; channel bandwidth is 3.84 MHz) at a frequency of 2500 MHz, 2600 MHz and 2700 MHz, a supply voltage of 28 V and an I<sub>Dq</sub> of 900 mA:
  - ◆ Average output power = 14 W
  - ◆ Power gain = 17 dB
  - ◆ Drain efficiency = 23 %
  - ◆ ACPR<sub>5M</sub> = -41 dBc
- Typical 1-carrier N-CDMA performance (single carrier IS-95 with pilot, paging, sync and 6 traffic channels [Walsh codes 8 to 13]. PAR = 9.7 dB at 0.01 % probability on the CCDF. Channel bandwidth is 1.2288 MHz) at a frequency of 2500 MHz, 2600 MHz and 2700 MHz, a supply voltage of 28 V and an I<sub>Dq</sub> of 900 mA:
  - ◆ Average output power = 14 W
  - ◆ Power gain = 17 dB
  - ◆ Drain efficiency = 23 %
  - ◆ ACPR<sub>885k</sub> = -50 dBc (within 30 kHz bandwidth)







- Easy power control
- Integrated ESD protection
- Excellent ruggedness
- High efficiency
- Excellent thermal stability
- Designed for broadband operation (2500 MHz to 2700 MHz)
- Internally matched for ease of use

## 1.3 Applications

- RF power amplifiers for base stations and multicarrier applications in the 2500 MHz to 2700 MHz frequency range

## 2. Pinning information

**Table 2. Pinning**

Pin	Description	Simplified outline	Graphic symbol
<b>BLF6G27-100 (SOT502A)</b>			
1	drain		 sym112
2	gate		
3	source		
<b>BLF6G27LS-100 (SOT502B)</b>			
1	drain		 sym112
2	gate		
3	source		

[1] Connected to flange.

## 3. Ordering information

**Table 3. Ordering information**

Type number	Package		Version
	Name	Description	
BLF6G27-100	-	flanged LDMOST ceramic package; 2 mounting holes; 2 leads	SOT502A
BLF6G27LS-100	-	earless flanged LDMOST ceramic package; 2 leads	SOT502B

## 4. Limiting values

**Table 4. Limiting values**

In accordance with the Absolute Maximum Rating System (IEC 60134).

Symbol	Parameter	Min	Max	Unit
$V_{DS}$	drain-source voltage	-	65	V
$V_{GS}$	gate-source voltage	-0.5	+13	V
$I_D$	drain current	-	29	A
$T_{stg}$	storage temperature	-65	+150	°C
$T_j$	junction temperature	-	200	°C

## 5. Thermal characteristics

**Table 5. Thermal characteristics**

Symbol	Parameter	Conditions	Type	Typ	Unit
$R_{th(j-case)}$	thermal resistance from junction to case	$T_{case} = 80\text{ °C}$ ; $P_L = 100\text{ W}$	BLF6G27-100	0.68	K/W
			BLF6G27LS-100	0.5	K/W

## 6. Characteristics

**Table 6. Characteristics**

$T_j = 25\text{ °C}$  unless otherwise specified.

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$V_{(BR)DSS}$	drain-source breakdown voltage	$V_{GS} = 0\text{ V}$ ; $I_D = 0.5\text{ mA}$	65	-	-	V
$V_{GS(th)}$	gate-source threshold voltage	$V_{DS} = 10\text{ V}$ ; $I_D = 150\text{ mA}$	1.4	2	2.4	V
$I_{DSS}$	drain leakage current	$V_{GS} = 0\text{ V}$ ; $V_{DS} = 28\text{ V}$	-	-	5	$\mu\text{A}$
$I_{DSX}$	drain cut-off current	$V_{GS} = V_{GS(th)} + 3.75\text{ V}$ ; $V_{DS} = 10\text{ V}$	22.3	27	-	A
$I_{GSS}$	gate leakage current	$V_{GS} = 11\text{ V}$ ; $V_{DS} = 0\text{ V}$	-	-	450	nA
$g_{fs}$	forward transconductance	$V_{DS} = 10\text{ V}$ ; $I_D = 5.25\text{ A}$	-	10.5	-	S
$R_{DS(on)}$	drain-source on-state resistance	$V_{GS} = V_{GS(th)} + 3.75\text{ V}$ ; $I_D = 5.25\text{ A}$	-	0.1	0.16	$\Omega$
$C_{rs}$	feedback capacitance	$V_{GS} = 0\text{ V}$ ; $V_{DS} = 28\text{ V}$ ; $f = 1\text{ MHz}$	-	2.4	-	pF

**7. Application information**

**Table 7. Application information**

Mode of operation: 1-carrier W-CDMA; single carrier W-CDMA TM1 with 64 DPCH and 100 % clipping; PAR = 9.65 dB at 0.01 % probability on the CCDF; carrier channel bandwidth is 3.84 MHz;  $f_1 = 2500$  MHz;  $f_2 = 2600$  MHz,  $f_3 = 2700$  MHz; RF performance at  $V_{DS} = 28$  V;  $I_{Dq} = 900$  mA;  $T_{case} = 25$  °C; unless otherwise specified, in a class-AB production circuit.


Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$G_p$	power gain	$P_{L(AV)} = 14$ W				
		BLF6G27-100	14.8	16.5	-	dB
		BLF6G27LS-100	15	17	-	dB
$RL_{in}$	input return loss	$P_{L(AV)} = 14$ W	-	-10	-6	dB
$\eta_D$	drain efficiency	$P_{L(AV)} = 14$ W	20	23	-	%
$ACPR_{5M}$	adjacent channel power ratio (5 MHz)	$P_{L(AV)} = 14$ W	[1]			
		BLF6G27-100	-	-40	-36	dBc
		BLF6G27LS-100	-	-41	-37	dBc
$ACPR_{10M}$	adjacent channel power ratio (10 MHz)	$P_{L(AV)} = 14$ W	[1]			
		BLF6G27-100	-	-59	-56	dBc
		BLF6G27LS-100	-	-60	-57	dBc

[1] ACPR measured in 3.84 MHz channel bandwidth at  $\pm 5$  MHz and  $\pm 10$  MHz.

**7.1 Ruggedness in class-AB operation**

The BLF6G27-100 and BLF6G27LS-100 are capable of withstanding a load mismatch corresponding to VSWR = 10 : 1 through all phases under the following conditions:  $V_{DS} = 28$  V;  $I_{Dq} = 900$  mA;  $P_L = 100$  W (CW);  $f = 2500$  MHz.


7.2 Single carrier W-CDMA performance



$V_{DS} = 28\text{ V}$ ;  $I_{DQ} = 900\text{ mA}$ ; single carrier W-CDMA TM1 with 64 DPCH and 100 % clipping; PAR = 9.65 dB at 0.01 % probability; channel bandwidth = 3.84 MHz.

- (1)  $f = 2500\text{ MHz}$
- (2)  $f = 2600\text{ MHz}$
- (3)  $f = 2700\text{ MHz}$

Fig 1. Power gain and drain efficiency as a function of average output power; typical values




$V_{DS} = 28\text{ V}$ ;  $I_{DQ} = 900\text{ mA}$ ; single carrier W-CDMA TM1 with 64 DPCH and 100 % clipping; PAR = 9.65 dB at 0.01 % probability; channel bandwidth = 3.84 MHz.

- (1)  $f = 2500\text{ MHz}$
- (2)  $f = 2600\text{ MHz}$
- (3)  $f = 2700\text{ MHz}$


Fig 2. ACPR at 5 MHz and at 10 MHz as a function of average output power; typical values

**7.3 Single carrier W-CDMA broadband performance at 14 W average power**



$V_{DS} = 28$  V;  $I_{Dq} = 900$  mA; single carrier W-CDMA TM1 with 64 DPCH and 100 % clipping; PAR = 9.65 dB at 0.01 % probability; channel bandwidth = 3.84 MHz.


**Fig 3. Power gain and drain efficiency as a function of frequency; typical values**



$V_{DS} = 28$  V;  $I_{Dq} = 900$  mA; single carrier W-CDMA TM1 with 64 DPCH and 100 % clipping; PAR = 9.65 dB at 0.01 % probability; channel bandwidth = 3.84 MHz.

**Fig 4. ACPR at 5 MHz and at 10 MHz as a function of frequency; typical values**


7.4 IS-95 performance



$V_{DS} = 28$  V;  $I_{DQ} = 900$  mA; IS-95 with pilot, paging, sync and 6 traffic channels (Walsh codes 8 to 13); PAR = 9.7 dB at 0.01 % probability on the CCDF; channel bandwidth = 1.2288 MHz.

- (1)  $f = 2500$  MHz
- (2)  $f = 2600$  MHz
- (3)  $f = 2700$  MHz

Fig 5. Power gain and drain efficiency as a function of average output power; typical values




$V_{DS} = 28$  V;  $I_{DQ} = 900$  mA; IS-95 with pilot, paging, sync and 6 traffic channels (Walsh codes 8 to 13); PAR = 9.7 dB at 0.01 % probability on the CCDF; channel bandwidth = 1.2288 MHz.

- (1)  $f = 2500$  MHz
- (2)  $f = 2600$  MHz
- (3)  $f = 2700$  MHz


Fig 6. ACPR at 885 kHz and at 1980 kHz as a function of average output power; typical values

## 7.5 IS-95 broadband performance at 14 W average power



$V_{DS} = 28$  V;  $I_{DQ} = 900$  mA; IS-95 with pilot, paging, sync and 6 traffic channels (Walsh codes 8 to 13);  
 PAR = 9.7 dB at 0.01 % probability on the CCDF;  
 channel bandwidth = 1.2288 MHz.

**Fig 7. Power gain and drain efficiency as a function of frequency; typical values**



$V_{DS} = 28$  V;  $I_{DQ} = 900$  mA; IS-95 with pilot, paging, sync and 6 traffic channels (Walsh codes 8 to 13);  
 PAR = 9.7 dB at 0.01 % probability on the CCDF;  
 channel bandwidth = 1.2288 MHz.

**Fig 8. ACPR at 855 kHz and at 1980 kHz as a function of frequency; typical values**



8. Package outline

Flanged LDMOST ceramic package; 2 mounting holes; 2 leads

SOT502A




Fig 9. Package outline SOT502A

Earless flanged LDMOST ceramic package; 2 leads

SOT502B




Fig 10. Package outline SOT502B

## 9. Abbreviations

**Table 8. Abbreviations**

Acronym	Description
CCDF	Complementary Cumulative Distribution Function
CW	Continuous Wave
DPCH	Dedicated Physical CHannel
ESD	ElectroStatic Discharge
FCH	Frame Control Header
FFT	Fast Fourier Transform
IBW	Instantaneous BandWidth
IS-95	Interim Standard 95
LDMOS	Laterally Diffused Metal-Oxide Semiconductor
N-CDMA	Narrowband Code Division Multiple Access
PAR	Peak-to-Average power Ratio
PUSC	Partial Usage of SubChannels
RF	Radio Frequency
TM1	Test Model 1
VSWR	Voltage Standing-Wave Ratio
W-CDMA	Wideband Code Division Multiple Access
WCS	Wireless Communications Service
WiMAX	Worldwide interoperability for Microwave Access

## 10. Revision history

**Table 9. Revision history**

Document ID	Release date	Data sheet status	Change notice	Supersedes
BLF6G27-100_BLF6G27LS-100 v.2	20100708	Product data sheet	-	BLF6G27-100_ BLF6G27LS-100_1
Modifications:				
<ul style="list-style-type: none"> <li>Data sheet status change to Product data sheet.</li> <li><a href="#">Table 1 on page 1</a>: A distinction has been made between BLF6G27-100 and BLF6G27LS-100</li> <li><a href="#">Table 7 on page 4</a>: A distinction has been made between BLF6G27-100 and BLF6G27LS-100</li> </ul>				
BLF6G27-100_BLF6G27LS-100_1	20100503	Preliminary data sheet	-	-

## 11. Legal information

### 11.1 Data sheet status

Document status <sup>[1][2]</sup>	Product status <sup>[3]</sup>	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <http://www.nxp.com>.

### 11.2 Definitions

**Draft** — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

**Short data sheet** — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

**Product specification** — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

### 11.3 Disclaimers

**Limited warranty and liability** — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

**Right to make changes** — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

**Suitability for use** — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or

malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors accepts no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

**Applications** — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

**Limiting values** — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

**Terms and conditions of commercial sale** — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

**No offer to sell or license** — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

**Export control** — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from national authorities.

**Non-automotive qualified products** — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond

NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

## 11.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

## 12. Contact information

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: [salesaddresses@nxp.com](mailto:salesaddresses@nxp.com)

## 13. Contents

---

<b>1</b>	<b>Product profile</b> . . . . .	<b>1</b>
1.1	General description . . . . .	1
1.2	Features and benefits . . . . .	1
1.3	Applications . . . . .	2
<b>2</b>	<b>Pinning information</b> . . . . .	<b>2</b>
<b>3</b>	<b>Ordering information</b> . . . . .	<b>2</b>
<b>4</b>	<b>Limiting values</b> . . . . .	<b>3</b>
<b>5</b>	<b>Thermal characteristics</b> . . . . .	<b>3</b>
<b>6</b>	<b>Characteristics</b> . . . . .	<b>3</b>
<b>7</b>	<b>Application information</b> . . . . .	<b>4</b>
7.1	Ruggedness in class-AB operation . . . . .	4
7.2	Single carrier W-CDMA performance . . . . .	5
7.3	Single carrier W-CDMA broadband performance at 14 W average power . . . . .	6
7.4	IS-95 performance . . . . .	7
7.5	IS-95 broadband performance at 14 W average power . . . . .	8
<b>8</b>	<b>Package outline</b> . . . . .	<b>9</b>
<b>9</b>	<b>Abbreviations</b> . . . . .	<b>11</b>
<b>10</b>	<b>Revision history</b> . . . . .	<b>11</b>
<b>11</b>	<b>Legal information</b> . . . . .	<b>12</b>
11.1	Data sheet status . . . . .	12
11.2	Definitions . . . . .	12
11.3	Disclaimers . . . . .	12
11.4	Trademarks . . . . .	13
<b>12</b>	<b>Contact information</b> . . . . .	<b>13</b>
<b>13</b>	<b>Contents</b> . . . . .	<b>14</b>

---

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

---

© NXP B.V. 2010.

All rights reserved.

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: [salesaddresses@nxp.com](mailto:salesaddresses@nxp.com)

Date of release: 8 July 2010

Document identifier: BLF6G27-100\_BLF6G27LS-100