

**Data sheet | Item number: 879-3000**

Energy meter (MID); for direct connection; 65A; 3x230/400V; 50Hz; Modbus®  
and M-Bus; 2 x S0 interface; 4PU



[www.wago.com/879-3000](http://www.wago.com/879-3000)



Subject to changes. Please also observe the further product documentation!

---

WAGO GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.



Subject to changes. Please also observe the further product documentation!

---

WAGO GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.



## Item description

### Short description:

Optimizing energy consumption requires comprehensive energy measurement. WAGO's portfolio now has new energy meters that make that easier while offering several key advantages. They use push-in connection technology with a lever, making them connect quickly and easily. The devices have a width of just 72 mm for direct measurement. These slim profiles save a tremendous amount of control cabinet space. In addition to the values for active and reactive energy, the energy meters also record the mains frequency, as well as current, voltage and power for all phases. And the user can conveniently scan all of these energy characteristics at a glance on a large, illuminated display.

### Features:

- Time savings at every stage thanks to Push-in CAGE CLAMP® and lever
- Real space savings: 72 mm wide (4PU)
- The communications pro: M-Bus/Modbus® interface and two SO pulse outputs

Subject to changes. Please also observe the further product documentation!

- Full transparency at a glance: display energy quality characteristics on an illuminated full-format display
- Intuitive configuration: touch-sensitive controls and configuration app via *Bluetooth*<sup>®</sup>

## Data

### Technical data

### Configuration

Configuration options

Touch-sensitive controls

Configuration app via *Bluetooth*<sup>®</sup>

### Input

Input signal type	Voltage Current
Network configuration	Two-wire, three-wire and four-wire networks
Reference current $I_{ref}$	5 A
Measured variable	Voltage Current Electrical output Mains frequency
Nominal input voltage $U_{i nom}$	3 x AC 230 ... 400 V
Input voltage range	±20 %
Input current $I_i$	≤ 65 A
Frequency range	45 ... 60 Hz

### Communication

Communication	Modbus <sup>®</sup> M-Bus <i>Bluetooth</i> <sup>®</sup>
Interface	RS-485 (2-wire); 2x S0 interfaces (configurable)
Indicators	LCD with backlight
Rate control input	230 VAC

### Signal processing

Measured variables (calculated)	Active and reactive energy in supply and reference direction
Measurement type (load profile)	No

Subject to changes. Please also observe the further product documentation!

## Measurement error

Accuracy class	Class B (= 1 % error); Active energy per EN 50470-3
Calibration validity period	8 years

## Power supply

Power supply type	Via measurement circuit
Power consumption $P_{\max}$ (phase; active power)	2 W
Power consumption $P_{\max}$ (phase; apparent power)	10 VA

## Safety and protection

Dielectric strength	4 kV; 1 min
Impulse withstand voltage (1.2/50 $\mu$ s)	6 kV
Pollution degree	2
Protection class	II
Protection type	IP51 / IP20; IP51 (front side); IP20 (connection)

## Physical data

Width	72 mm / 2.835 inches
Height	140 mm / 5.512 inches
Depth	63 mm / 2.48 inches
Note (dimensions)	Height without cover: 92 mm

## Mechanical data

Mounting type	DIN-35 rail
Housing design	DIN-rail-mount enclosure

## Material data

Housing material	PC 940A
Weight	280 g

## Environmental requirements

Ambient temperature (operation)	-40 ... +70 °C
Relative humidity	≤ 75% (during storage ≤ 95 %)

Subject to changes. Please also observe the further product documentation!



## Standards and specifications

Conformity marking	CE
Standards/specifications	EN 50470-1/3 MID-compliant

## Commercial data

ETIM 8.0	EC002048
ETIM 7.0	EC002048
Recupel Type	
PU (SPU)	1 pcs
Country of origin	CN
Customs tariff number	90283019000

## Environmental Product Compliance

RoHS Compliance Status	Compliant, No Exemption
------------------------	-------------------------

## Approvals / Certificates

### Declarations of conformity and manufacturer's declarations

Logo	Approval	Additional Approval Text	Certificate name
	<b>EU-Declaration of Conformity</b> WAGO GmbH & Co. KG	-	-
	<b>UK-Declaration of Conformity</b> WAGO GmbH & Co. KG	-	-

## Downloads

### Documentation

#### Manual

Product Manual WAGO Energy Meters (MID) 4PS / 4PU /2PU CT	V 1.7 2023 年3月31 日	pdf 4.1 MB	Download
--	-----------------------	---------------	----------

#### Bid Text

879-3000 X81 - Datei		xml 6.8 kB	Download
879-3000		docx	Download

Subject to changes. Please also observe the further product documentation!



docx - Datei			26.0 kB
--------------	--	--	---------

<a href="#">ausschreiben.de 879-3000</a>			URL	Download
--	--	--	-----	----------

**Instruction Leaflet**

Energy consumption meter	V 1.15 2022 年2月16 日	pdf 956.8 kB	Download
--------------------------	------------------------	-----------------	----------

**Application Notes****Application Note e!COCKPIT**

e!COCKPIT Application Note WagoAppPowerMeasurement	2021-11-08	pdf	Download
This Application Note describes the use of the library WagoAppPowerMeasurement under different boundary conditions.	2021 年12月6 日	953.0 kB	

**Libraries****e!COCKPIT libraries**

e!COCKPIT Library Description WagoAppPowerMeasurement	1.7.4.0 2021 年5月25 日	pdf 1.5 MB	Download
---	-------------------------	---------------	----------

**CAD/CAE-Data****CAD data**

<a href="#">2D/3D Models 879-3000</a>			URL	Download
---------------------------------------	--	--	-----	----------

**CAE data**

<a href="#">ZUKEN Portal 879-3000</a>			URL	Download
---------------------------------------	--	--	-----	----------

<a href="#">EPLAN Data Portal 879-3000</a>			URL	Download
--	--	--	-----	----------

**Environmental Product Compliance****Compliance Search**

<a href="#">Environmental Product Compliance 879-3000</a>			URL	Download
---	--	--	-----	----------

Subject to changes. Please also observe the further product documentation!



Energy meter (MID); for direct connection; 65A; 3x230/400V; 50Hz; Modbus® and M-Bus; 2 x S0 interface; 4PU

---

## Installation Notes

Subject to changes. Please also observe the further product documentation!

---

WAGO GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.