

# SmartSwarm 341

## Asset Integration Gateway



### Features

- Configurable user business logic data processing & display engine
- Comprehensive data outputs via MQTT, email, SMS and a variety of other services and database connections
- Integrates data from WZZARD, WISE, ADAM & third party devices
- Integrates data from internet feeds
- Cellular or Ethernet connection to IIoT system
- Acts as LAN to WAN bridge for third party device connection
- Cellular (EMEA/NATAM support) and wired models available

### Introduction

#### Seamlessly integrate data from diverse systems, devices and sensors into the IIoT

The SmartSwarm 341 IIoT gateway is aimed at owners of remote assets wishing to integrate data from their assets into IIoT applications like dashboarding, analytics or predictive maintenance. Data can be collected from a number of sources, including web feeds, databases and files, as well as from locally connected physical devices and sensors. SmartSwarm 341 includes an interface and manager for B+B's Wizzard wireless sensor platform that provides robust acquisition and transmission of sensor data without installing cables. For bulk I/O requirements where cabling is not an issue, it is also compatible with WISE and ADAM Ethernet connected I/O modules.

#### User Applications

SmartSwarm 341 offers flexible data acquisition, processing and handoff via an inbuilt Node-RED user application environment. Node-RED is a powerful, yet simple to use, application programming environment optimized for processing data streams. Users drag and drop function nodes to acquire, processes and output data, via an internal web server interface provided by the SmartSwarm 341. Crucially, the Node-RED environment is contained, meaning that any user error made in programming cannot crash the gateway, which will remain connected and available for remote management in order to correct errors without site visits. In addition to offering local data processing, the Node-RED environment is also able to create and serve local dashboards, providing a mechanism to serve summary data to engineers, managers or operational staff.

### Specification

#### WZZARD RADIO - 802.15.4E, 2.4 GHZ

▪ Number of Channels	15
▪ Channel Separation	5 MHz
▪ Channel Clear Frequency	2405 + 5* (k-11) MHz
▪ Modulation	IEEE 802.15.4 Direct Sequence Spread Spectrum (DSSS)
▪ Raw Data Rate	250 kbps
▪ Range (25 °C, 50% RH, +2 dBi omni-directional antenna, antenna 2m)	Indoor 100 m Outdoor 300 m Free Space 1200 m
▪ Receiver Sensitivity	Packet Data Error Rate (PER) = 1% -93 dBm
▪ Receiver Sensitivity	Packet Data Error Rate PER = 50% -95 dBm
▪ Output Power (delivered to a 50 Ω load)	High Calibration Setting 8 dBm Low Calibration Setting 0 dBm

#### Ports, LEDs, Antennas

▪ (2) Ethernet Ports	RJ45, 10/100 Mbps
▪ SIM	(2) Mini SIM, 2FF, 1 supported (rear panel)
▪ LED Indicators	PWR, DAT, WAN, ETH, SIM, USR, POE, IN0, IN1, OUT
▪ Wizzard	R-SMA connector
▪ RST	RESET button (rear panel)
▪ *Optional-3x ANT-ANT, DIV	SMA connectors
▪ SD	Available for file storage from Node-RED applications (currently unsupported)
▪ (USB)	

#### Power

▪ *Optional - Power Supply	10 – 60 V <sub>DC</sub> (2-Way Molex connector)
▪ Power Consumption	Idle: 2.5 W Average: 4 W Peak: 11 W Sleep Mode: 10mW

#### Environmental

▪ Temperature Range	Operating: -40 to +75 °C Storage: -40 to +85 °C
▪ Temperature Range LTE450	Operating: -20 to +60 °C Storage: -40 to +85 °C
▪ Humidity	Operating: 0 to 95 % Storage (Non-condensing): 0 to 95 %
▪ Cold Start	-35 °C
▪ Operating Altitude	2000 m / 70 kPa
▪ Ingress Protection Rating	IP30

#### Mechanical

▪ Metal case with metal DIN rail	
▪ Dimensions	55 x 97 x 125 mm (2.17 x 3.82 x 4.9)
▪ Weight	375 g

#### Industry Certifications & Approvals

▪ Radio for general LTE	ETSI EN 301 511 v9.0.2, ETSI EN 301 908-1 v5.2.1, ETSI EN 301 908-2 v5.2.1, ETSI EN 301 908-13 v5.2.1
▪ Emissions/ Immunity	IEC 61000-6-2:2005, ETSI EN 301 489-1 v1.9.2, EN 55022:2010
▪ Safety	EN 60950-1:06 ed.2 (not Hazardous Locations), EN 62311:2008
▪ Vehicle	E8
▪ Environmental	RoHS, RoHS2, REACH, WEEE

### Ordering Information

▪ BB-SG30000520-41	2 Ethernet, Dust (no power supply)
▪ BB-SG30000525-41	2 Ethernet, Dust, International Power Supply
▪ BB-SG30300520-41	2 Ethernet, LTE-EMEA, Dust (no power supply)
▪ BB-SG30300525-41	2 Ethernet, LTE-EMEA, Dust, International Power Supply
▪ BB-SG30500520-41	2 Ethernet, LTE-NATAM, Dust (no power supply)