

988 Soldering Flux

Low-Solids, No-Clean, Liquid Flux

Product Description

Kester 988 Soldering Flux is a low-solids, no-clean flux that is specially designed for excellent solderability and best-in-class through hole fill in lead-free wave soldering process. The residue left behind is evenly distributed and non-tacky so that boards are cosmetically clean as they exit the wave solder machine. The residue remaining after soldering is non-conductive and can be left on the boards without degrading the reliability of the assembly. 988 is classified as Type ROM0 flux under J-STD- 004A specifications.

Performance Characteristics:

- Best-in-class through hole-fill
- Provides excellent solderability on surface mount circuit boards for defect-free soldering even after 2x SMT reflow cycles
- Evenly distributed, uniform and tack-free residues on solder mask
- No surface insulation degradation
- Suitable for leaded and lead-free (SnCu and SnAgCu) alloys
- Eliminates the needs and expense of cleaning
- Classified as ROM0 per J-STD-004

RoHS Compliance

This product meets the requirements of the Restriction of Hazardous Substances (RoHS) Directive, 2015/863 for the stated banned substances.

Physical Properties

Specific Gravity: 0.808

Anton Paar DMA 35 @ 25°C

Percent Solids (theoretical): 6.0

Acid Number (typical): 30.0 mg KOH/g of flux

Tested by potentiometric titration

Thinner: 4662

Reliability Properties

Copper Mirror Corrosion: Moderate

Tested to J-STD-004A, IPC-TM-650, Method 2.3.32

Corrosion Test: Moderate

Tested to J-STD-004A, IPC-TM-650, Method 2.6.15

Silver Chromate: Pass

Tested to J-STD-004A, IPC-TM-650, Method 2.3.33

Chloride and Bromides: None Detected

Tested to J-STD-004A, IPC-TM-650, Method 2.3.35

Fluorides by Spot Test: Pass

Tested to J-STD-004A, IPC-TM-650, Method 2.3.35.1

Electromigration, Bellcore (typical): Pass

Tested to Bellcore GR-78-CORE

	Blank	988 PD	988PU
Day 4	$1.1 \times 10^{11} \Omega$	$6.6 \times 10^8 \Omega$	$2.4 \times 10^9 \Omega$
Day 21	$1.9 \times 10^{11} \Omega$	$1.3 \times 10^{10} \Omega$	$7.0 \times 10^{10} \Omega$

Surface Insulation Resistivity (SIR), (typical): Pass

Tested to J-STD-004A, IPC-TM-650, Method 2.6.3.3

	Blank	988 PD	988 PU
Day 1	$8.4 \times 10^{10} \Omega$	$1.1 \times 10^{10} \Omega$	$9.9 \times 10^9 \Omega$
Day 4	$7.6 \times 10^{10} \Omega$	$1.3 \times 10^{10} \Omega$	$2.6 \times 10^{10} \Omega$
Day 7	$5.8 \times 10^{10} \Omega$	$1.5 \times 10^{10} \Omega$	$2.7 \times 10^{10} \Omega$

Flux Application

988 can be applied via foam or spray fluxing. Flux deposition should be 155 to 310 μg of solids/ cm^2 (600 to 1200 μg of solids/ in^2). An air knife after the flux tank is recommended to remove excess flux from the circuit board and prevent dipping on the preheated surface. For foam, fluxing, the consistency should be maintaining only using Kester 4662 Thinner to compensate for evaporation loss.

Process Considerations

The optimum preheat temperature for most circuit assemblies is 95 to 105 °C (203 to 221 °F) as measured on the top or component side of the printed circuit board. The bottom of the board will not reach 145 °C (293 °F). Dwell time in the solder is typically 2 to 4 seconds for leaded alloys and 4 to 8 seconds for lead-free alloys. The conveyor speed should be adjusted to accomplish proper board contact time with the solder. Then the preheat temperatures are adjusted to achieve the required preheat top board temperatures. In the event you need further direction on the setup of your wave soldering system, please contact Kester Technical Support.

Flux Control

Kester PS-22 Test Kit and procedure are available to insure the level of solids in the flux. The instructions of how to use this kit will come with the purchase of the kit. This could be used as an incoming inspection device or if a container had been left open for any period of time allowing the solvents to evaporate. The flux thinner is Kester's 4662.

Cleaning

988 flux residues are non-conductive, non-corrosive and do not require removal in most applications. If residue removal is required, Kester 5252 Cleaner may be used.

Recycling Services

We provide safe and efficient recycling services to help companies meet their environmental and legislative requirements and at the same time, maximize the value of their waste streams.

Our service collects solder dross, solder scrap, and various forms of solder paste waste. Please contact your local sales representative for recycling capabilities in your area or [link here](#).



Storage, Handling and Shelf Life

988 is flammable. Store away from sources of ignition. Shelf life is 1 year from date of manufacture when handled properly and held at 10 to 25 °C (50 to 77 °F).

Health and Safety

This product, during handling or use, may be hazardous to your health or the environment. Read the Safety Data Sheet and warning label before using this product. Safety Data Sheets are available at this [link](#).

Contact Information

To confirm this document is the most recent version, please contact Assembly@MacDermidAlpha.com

<p>North America 109 Corporate Blvd. South Plainfield, NJ 07080, USA 1.800.253.7837</p>	<p>Europe Unit 2, Genesis Business Park Albert Drive Woking, Surrey, GU21 5RW, UK 44.01483.758400</p>	<p>Asia Pacific 8/F., Paul Y. Centre 51 Hung To Road Kwun Tong, Kowloon, Hong Kong 852.3190.3100</p>
--	--	---

Also read carefully warning and safety information on the Safety Data Sheet. This data sheet contains technical information required for safe and economical operation of this product. READ IT THOROUGHLY PRIOR TO PRODUCT USE. Emergency safety directory assistance: US 1 202 464 2554, Europe + 44 1235 239 670, Asia + 65 3158 1074, Brazil 0800 707 7022 and 0800 172 020, Mexico 01800 002 1400 and (55) 5559 1588

DISCLAIMER: All statements, technical information and recommendations contained herein are based on tests we believe to be reliable, but the accuracy or completeness thereof is not guaranteed. No statement or recommendation shall constitute a representation unless set forth in an agreement signed by officers of seller and manufacturer. NO WARRANTY OF MERCHANTABILITY, WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE OR ANY IMPLIED WARRANTY IS MADE. The following warranty is made in lieu of such warranties and all other warranties, express, implied, or statutory. Products are warranted to be free from defects in material and workmanship at the time sold. The sole obligation of seller and manufacturer under this warranty shall be to replace any noncompliant product at the time sold. Under no circumstances shall manufacturer or seller be liable for any loss, damage or expense, direct, indirect, incidental or consequential, arising out of the inability to use the product. Notwithstanding the foregoing, if products are supplied in response to a customer request that specifies operating parameters beyond those stated above, or if products are used under conditions exceeding said parameters, the customer by acceptance or use thereof assumes all risk of product failure and of all direct, indirect, incidental and consequential damages that may result from use of the products under such conditions, and agrees to exonerate, indemnify, defend and hold harmless MacDermid, Incorporated and its affiliates therefrom. No suggestion for product use nor anything contained herein shall be construed as a recommendation to use any product in a manner that infringes any patent or other intellectual property rights, and seller and manufacturer assume no responsibility or liability for any such infringement.

© 2019 MacDermid, Inc. and its group of companies. All rights reserved. "R" and "TM" are registered trademarks of MacDermid, Inc. and its group of companies in the United States and/or other countries.