



EXH

Two-Way Radio Antenna

FEATURES

- Injection molded ¼ wave base loaded antenna
- High gain
- High durability, high efficiency
- Textured finish with strain-relief base
- Available in various standard connectors
- An original 'Tuf Duck' antenna

PARAMETER	SPECIFICATION
Frequency Range	VHF
Nominal Impedance	50 ohms
VSWR	2:1 max at resonance
Power Rating	Max Power - 50 watts
Temperature Range	-40°C to +85°C
Drop Test	1M
Length ¹	10.50 inches

¹ The length noted is the maximum possible length for this LMR antenna. The actual length of the antenna will vary according to the connector chosen.

FREQUENCIES AND CONNECTOR

PART#	FREQUENCY BAND	CONNECTORS	COLOR CODE
EXH150	145-155 MHz	BN, KR, MX, SF, SFU, SM, SMV & TN	Red
EXH155	150-160 MHz	BN, KR, MD, MX, SF, SFU, SM, SMV & TN	Brown
EXH160	155-165 MHz	BN, KR, MX, SF, SFU, SM, SMV & TN	Black
EXH170	165-175 MHz	BN, KR, MD, MX, SF, SFU, SM, SMV & TN	Orange

The EXH model antenna is available in the above frequencies and connectors. Order by antenna model, frequency and connector. For example: EXH150SF. Specifications subject to change without notice.

TE TECHNICAL SUPPORT CENTER

USA:	+1 (800) 522-6752
Canada:	+1 (905) 475-6222
Mexico:	+52 (0) 55-1106-0800
Latin/S. America:	+54 (0) 11-4733-2200
Germany:	+49 (0) 6251-133-1999
UK:	+44 (0) 800-267666
France:	+33 (0) 1-3420-8686
Netherlands:	+31 (0) 73-6246-999
China:	+86 (0) 400-820-6015

te.com

TE Connectivity, TE Connectivity (logo) and Every Connection Counts are trademarks. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

©2021 TE Connectivity. All Rights Reserved.

11/21 Original