## 60 INCHES LENGTH



Connector A 112234 BNC Jack Straight Bulkhead - Rear Mount Brass Nickel 50 Ohm RG-174 Continuity/Hi-Pot Connector B 000-69475 BNC Plug Straight Brass Nickel

## Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

		Connector A			Cable		Connector B		
D Tr G B C P In M B B IP C C M	Description: Type: Gender: Body Type: Contact Type: Polarity: mpedance: Mounting: Body Material: Body Material: Body Finish: P Rating: Contact Material: Contact Finish: Max. Freq.:	112234 BNC Clamp BHD JK RG188 500 BNC Jack Straight Crimp Standard 50 Ohm Bulkhead - Rear Mount Brass Nickel None Beryllium Copper Silver 4 GHz BNC Jack Straight BHD		Part #: Description: Dielectric: Shielding: Diameter: Impedance: Sheathing: Testing: Length:	RG-174 RG-174 - PE 0.1 PE Braid 0.1 50 Ohm None Continuity Hi-Pot 60 Inches	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting: Clocking:	000-69475 BNC Clamp PLUG F BNC Plug Straight Solder Standard 50 Ohm Cable Brass Nickel None Brass Silver 4 GHz BNC Plug Straight 0°	RG188 50O	
Amphenol CUSTOM CABLE			THIS DRAWING MAY CONTAIN PATENTED OR PROPRIETARY INFORMATION AND MUST NOT BE USED FOR ANY PURPOSE DETRIMENTAL TO CUSTOM CABLE INC. IT MAY NOT BE REPRODUCED OR TRANSCRIBED IN ANY FORM WITHOUT THE WRITTEN CONSENT OF CUSTOM CABLE INC. ACCEPTANCE OF THIS DRAWING ESTABLISHES AND AGREEMENT OF THE FOREGOING.		LE D NG Part No:	BNC-ST-JK/BNC-ST-PL G174 60I		UNLESS SPECIFIED TOLERANCE: 0-18 inches +/- 1/2" over 18" +/- 2% ASSEMBLY: CENTER LABEL IF LENGTH IS LESS THAN 12 INCHES	