

## Switchmode/ High Frequency Rod Core Inductors

ance

## R C - 8

## **Description:**

Triad high current rod core inductors provide cost effective energy storage. By conditioning the output signal, the inductor smoothes out the current waveform to provide a more stable current. These low cost inductors are designed to be compatible with automated P.C.B. installation.


## **Outline Dimensions:**

A. Dimensions: As figure show Unit: In inch B. PIN DIM. : As figure show C. WT Lbs. : 0.03 Oz

| Type No. | +/- 10% Inductance | DC Rated Current | +/- 15% DC Resista |
|----------|--------------------|------------------|--------------------|
|          |                    |                  | Ohms               |
| RC-8     | 250.0 uH           | 1.250A           | 0.210              |

Inductance at a frequency range of 20KHz to 200KHz Rated current 10 amps per pin maximum.

Rated current renders approximately 40C temperature rise.



**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\*Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics website for the most current version. For soldering and washing information please see http://www.triadmagnetics.com/faq.html

| Web: www.TriadMagnetics.com460 Harley Knox Blvd.PublishPhone 951-277-0757460 Harley Knox Blvd.PublishFax 951-277-2757Perris, California 92571Publish | h Date: June 3, 2016 |
|--|----------------------|
|--|----------------------|