



## LIGHTNING ARRESTORS

LAIL350NN / LABH350NN  
LAIL350PP / LABH2400NN

### PROTECT SENSITIVE EQUIPMENT

Surge protectors are an integral part of any antenna installation involving the protection of sensitive equipment from surges caused by lightning. These units have the ability to withstand multiple lightning strikes and are designed for excellent durability and reliability and to resist corrosion.



SPECIFICATIONS	LAIL350NN/LABH350NN LAIL350PP	LABH2400NN
Frequency Range	0-1000 MHz	0-4 GHz
Maximum Power	1000 watts - P.E.P.	70 Watts - P.E.P.
Breakdown Voltage	350 Vac	90 - 130 Vac
Impedance	50 ohms (nom.)	50 ohms (nom.)
Insertion Loss	27-500 MHz < 0.1 dB 1000 MHz < 0.25 dB	1GHz < 0.03 dB 4GHz < 0.29 dB
VSWR	0-150 MHz < 1.1:1 150-1000 MHz < 1.2:1	1GHz < -25 dB 4GHz < -20 dB
Protection	5000 amps	1 shock = 20kA/10 shocks = 10kA
IP Rating	Not Rated	IP65

## ORDERING GUIDE

PART NUMBER	CONNECTOR 1	CONNECTOR 2
LABH350NN	Bulkhead N-Female	N-Female
LAIL350NN	N-Female	N-Female
LAIL350PP	SO239	SO239
LABH2400NN	Bulkhead N-Female	N-Female

### TE TECHNICAL SUPPORT CENTER

	+1 (800) 522-6752
USA:	+1 (905) 475-6222
Canada:	+52 (0) 55-1106-0800
Mexico:	+54 (0) 11-4733-2200
Latin/S. America:	+49 (0) 6251-133-1999
Germany:	+44 (0) 800-267666
UK:	+33 (0) 1-3420-8686
France:	+31 (0) 73-6246-999
Netherlands:	+86 (0) 400-820-6015

China:  
**te.com**

TE, and TE connectivity (logo) are trademarks owned or licensed by the TE Connectivity Ltd. family of companies. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

TE Connectivity warrants to the original end user customer of its products that its products are free from defects in material and workmanship. Subject to conditions and limitations TE Connectivity will, at its option, either repair or replace any part of its products that prove defective because of improper workmanship or materials. This limited warranty is in force for the useful lifetime of the original end product into which the TE Connectivity product is installed. Useful lifetime of the original end product may vary but is not to exceed one (1) year from the original date of the end product purchase.

©2023 TE Connectivity. All Rights Reserved.

02/23 Original