

EEM-MA370-24DC - Measuring instrument



1127059

<https://www.phoenixcontact.com/pc/products/1127059>

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Multi-functional energy measuring device with 24 V DC supply and integrated Modbus/TCP interface for measuring electrical parameters in low-voltage installations up to 690 V

Commercial data

Item number	1127059
Packing unit	1 pc
Minimum order quantity	1 pc
Product key	CK4C21
GTIN	4063151055240
Weight per piece (including packing)	412.6 g
Weight per piece (excluding packing)	400 g
Customs tariff number	90303100
Country of origin	DE

Technical data

Product properties

Product type	Energy measuring device
Product family	EMpro

Insulation characteristics

Overvoltage category	III (300 V)
Pollution degree	2

Electrical properties

Electrical isolation	IEC 61010-1 (Overvoltage category III at 300 V AC Overvoltage category II at 600 V AC)
	IEC 61010-1 (Measurement category III at 300 V AC Measurement category II at 600 V AC)
Test voltage	4 kV AC (50 Hz, 1 min.)
Maximum power dissipation for nominal condition	10 VA
Mains type	3-phase (3 or 4-conductor), 2-phase (2-conductor), and single-phase (1-conductor)

Supply

Supply voltage	24 V DC \pm 25 %
Supply voltage range	18 V DC ... 30 V DC
Power consumption	< 4 W

Input data

General

Measuring principle	True r.m.s. value measurement
Measured value	AC sine (50/60 Hz)
Acquisition of harmonics	up to 63rd harmonic
Description of the input	Digital input in accordance with IEC/EN 61131-2 (type 3)
Number	1
Voltage input signal	24 V DC 0 V DC ... 30 V DC
Current input signal	2 mA ... 15 mA
Protection	250 mA (fast-blow)

Measurement: Voltage

Input name	Voltage measuring input V1, V2, V3
Input voltage range direct	35 V AC ... 690 V AC (Phase/Phase) 20 V AC ... 400 V AC (Phase/neutral conductor)
Input voltage range via external transformers	60 V AC ... 2000000 V AC (primary) 60 V AC ... 400 V AC (secondary)
Surge voltage capacity	760 V AC (Phase/Phase)
Precision	0.2 %

EEM-MA370-24DC - Measuring instrument



1127059

<https://www.phoenixcontact.com/pc/products/1127059>

Power consumption	< 2 VA
-------------------	--------

Measurement: Current

Input name	Current measurement I1, I2, I3
Input current	1 A (secondary)
	5 A (secondary)
Current measuring range	1 A ... 20000 A (primary)
Overload capacity	6 A (I_{max})
Response threshold from measuring range nominal value	10 mA (1 A)
	50 mA (5 A)
Precision	0.2 %
Current overload	50 A for 1 s
Power consumption	< 0.5 VA

Measurement: Power

Precision	0.5 %
Active energy (IEC 62053-22)	Class 0.5 S
Reactive power (IEC 62053-23)	Class 2
ANSI C12.20	Class 0.5 S

Output data

Output description	Digital output in accordance with IEC/EN 61131-2 (type 3)
Number	1
Current output signal	≤ 100 mA
Voltage output signal	24 V DC
Protection	250 mA (fast-blow)

Connection data

Current / voltage / supply

Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3
Conductor cross section rigid	0.2 mm ² ... 6 mm ²
Conductor cross section flexible	0.2 mm ² ... 4 mm ²
Conductor cross section AWG	24 ... 10
Tightening torque	0.5 Nm ... 0.6 Nm

Digital I/O / communication

Connection method	Screw connection
Stripping length	7 mm
Screw thread	M3
Conductor cross section rigid	0.14 mm ² ... 2.5 mm ²
Conductor cross section flexible	0.14 mm ² ... 1.5 mm ²
Conductor cross section AWG	26 ... 14
Tightening torque	0.5 Nm ... 0.6 Nm

Interfaces

Data: Network interface

Communication protocol	Modbus/TCP
	REST
Connection method	RJ45

Dimensions

Width	90 mm
Height	80 mm
Depth	64 mm

Environmental and real-life conditions

Ambient conditions

Degree of protection (Display)	IP40 (Display)
Degree of protection (Housing)	IP20 (Housing)
Ambient temperature (operation)	-10 °C ... 55 °C
Ambient temperature (storage/transport)	-40 °C ... 70 °C
Altitude	≤ 2000 m
Max. permissible relative humidity (operation)	≤ 95 % (non-condensing)

Approvals

CE

Certificate	CE-compliant
-------------	--------------

UKCA

Certificate	UKCA-compliant
-------------	----------------

UL, USA/Canada

Identification	UL/C-UL Listed UL 61010-1
----------------	---------------------------

UL data

Operating mode	Indoor use
----------------	------------

UL data

Operating mode	Indoor use
----------------	------------

Mounting

Mounting type	DIN rail mounting
Mounting position	Horizontal DIN rail

EEM-MA370-24DC - Measuring instrument



1127059

<https://www.phoenixcontact.com/pc/products/1127059>

Approvals

To download certificates, visit the product detail page: <https://www.phoenixcontact.com/pc/products/1127059>



UL Listed

Approval ID: FILE E 357804



cUL Listed

Approval ID: FILE E 357804

cULus Listed

EEM-MA370-24DC - Measuring instrument



1127059

<https://www.phoenixcontact.com/pc/products/1127059>

Classifications

ECLASS

ECLASS-11.0	27142330
ECLASS-13.0	27142330
ECLASS-12.0	27142330

ETIM

ETIM 8.0	EC002301
----------	----------

UNSPSC

UNSPSC 21.0	41113600
-------------	----------

EEM-MA370-24DC - Measuring instrument



1127059

<https://www.phoenixcontact.com/pc/products/1127059>

Environmental product compliance

REACH SVHC

Lead 7439-92-1

1127059

<https://www.phoenixcontact.com/pc/products/1127059>

Accessories

PACT MCR-V1-21-44 - Current transformer

2277268

<https://www.phoenixcontact.com/pc/products/2277268>



Bus-bar current transformer, primary current can be selected between 50...500 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

PACT MCR-V2- 3015- 60 - Current transformer

2277271

<https://www.phoenixcontact.com/pc/products/2277271>



Window-type current transformer, primary current can be selected between 50...750 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

EEM-MA370-24DC - Measuring instrument

1127059

<https://www.phoenixcontact.com/pc/products/1127059>



PACT MCR-V2-3015-60-PT - Current transformer

2907413

<https://www.phoenixcontact.com/pc/products/2907413>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (50 ... 750) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

PACT MCR-V2- 4012- 70 - Current transformer

2277284

<https://www.phoenixcontact.com/pc/products/2277284>



Window-type current transformer, primary current can be selected between 75... 1000 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

EEM-MA370-24DC - Measuring instrument

1127059

<https://www.phoenixcontact.com/pc/products/1127059>

PACT MCR-V2-4012-70-PT - Current transformer

2907414

<https://www.phoenixcontact.com/pc/products/2907414>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (100 ... 1000) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

PACT MCR-V2- 5012- 85 - Current transformer

2277297

<https://www.phoenixcontact.com/pc/products/2277297>



Window-type current transformer, primary current can be selected between 100..1500 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

EEM-MA370-24DC - Measuring instrument

1127059

<https://www.phoenixcontact.com/pc/products/1127059>

PACT MCR-V2-5012-85-PT - Current transformer

2907416

<https://www.phoenixcontact.com/pc/products/2907416>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (100 ... 1500) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

PACT MCR-V2- 6015- 85 - Current transformer

2277336

<https://www.phoenixcontact.com/pc/products/2277336>



Window-type current transformer, primary current can be selected between 200 . . . 1,250 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

EEM-MA370-24DC - Measuring instrument

1127059

<https://www.phoenixcontact.com/pc/products/1127059>



PACT MCR-V2-6015-85-PT - Current transformer

2907417

<https://www.phoenixcontact.com/pc/products/2907417>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (200 ... 1600) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

PACT MCR-V2-10020-129 - Current transformer

2277378

<https://www.phoenixcontact.com/pc/products/2277378>



Window-type current transformer, primary current can be selected between 800 and 4,000 A AC, secondary current can be selected 1 A AC or 5 A AC, accuracy class can be selected 0.5 or 1, rated power can be selected

EEM-MA370-24DC - Measuring instrument

1127059

<https://www.phoenixcontact.com/pc/products/1127059>



PACT MCR-V3-60 - Current transformer

2277417

<https://www.phoenixcontact.com/pc/products/2277417>



Winding current transformer, primary current can be selected between 1...40 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

Phoenix Contact 2023 © - all rights reserved

<https://www.phoenixcontact.com>

PHOENIX CONTACT GmbH & Co. KG

Flachsmarktstraße 8

D-32825 Blomberg

+49 (0) 5235-3 00

info@phoenixcontact.com