



# 1575.42 MHz GNSS ACTIVE ANTENNA

Part Number: 2108912-1

# FEATURES & BENEFITS

- L1 band for GNSS
- Active Patch Antenna
- The following data is based on 12 x 12mm ground size
- Different cable lengths and connector options available
- No matching circuits required

# **RF SPECIFICATIONS**

Frequency Range (MHz)	1575.42
VSWR	< 2.0:1
System Gain at Zenith @ 5V	Typ. 11.1 dBic
Axial Ratio at Zenith	Typ.5.1 dB
Average Gain (Cable loss included)	6.3 dBic
Noise Figure	Typ. 1.4 dB @ 5V
Group Delay @ Zenith Variation Across Single Constellation(ns)	13.0
Phase Center Variation PCV (mm) including Active Circuitry	NA
LNA (Voltage & Current)	DC Voltage Range 1.8~3.3V & 4.0mA @3.0V
Feed Point Impedance	50 ohms
Polarization	RHCP


Standard Antenna Solutions

# MECHANICAL SPECIFICATIONS

Size	12.0 mm x 12.0 mm x 5.2 mm	
Weight	< 2.5 g	
Mounting	Adhesive Tape	
Mating Connector	MHF-type receptacle (TE PN 2337019-1)	
Cable	Coaxial Cable: 1.13mm Dia. (Length : 55±2 mm)	
Operating Temperature	-30 to +85°C	
Storage Temperature	-40 to +85°C	
Hazardous Materials	A certificate of conformance is available from the product page on TE website.	


# OUT OF BAND ATTENUATION

Frequency (MHz)	1475(F₀-100)	1675(F₀+100)	
L1 Atten. (dB)	26.83	26.39	
L1 F0 = 1575.42 MHz			




### **RF DATA**

(shown as 2108912-1 : Ground size : 12 x 12 mm, DC 3V & Current 4.0mA.)




Peak Gain



Antenna gain varies with cable length


#### **RADIATION PATTERN**


(shown as 2108912-1 : Ground size : 12 x 12 mm, DC 3V & Current 4.0mA.)



Antenna gain varies with cable length

DIMENSIONS






Dimension: mm Diagrams is not to scale

# MATING COMPONENTS

2108912-1	55	2.165	MHF-TYPE PLUG	RECEPTACLE (TE PN: 2337019-1)	$\overline{\mathbf{O}}$
PART	MM	INCH	CONNECTOR TYPE	PART NUMBER	IMAGE
NUMBER	CABLE LE	ENGTH(A)	(ON CABLE)	MATING COMPONE	NTS

Standard Antenna Solutions

### PACKAGING



#### TE TECHNICAL SUPPORT CENTER

USA:	+1 (800) 522-6752
Canada:	+1 (905) 475-6222
Mexico:	+52 (0) 55-1106-0800
Latin/S. America:	+54 (0) 11-4733-2200
Germany:	+49 (0) 6251-133-1999
UK:	+44 (0) 800-267666
France:	+33 (0) 1-3420-8686
Netherlands:	+31 (0) 73-6246-999
China:	+86 (0) 400-820-6015

For phone numbers in other countries, go to te.com/support-center

#### te.com

TE Connectivity, TE Connectivity (logo) are trademarks. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

© 2020 TE Connectivity Ltd. family of companies All Rights Reserved.

05/2021

