


**R/A FEMALE MODULE 6 SOLDER TYPE INSERTS**

**R694.252.107**




**2.5MM FOR PCB**

Series : MCC2


6 Coax Position AB/1A ,1B ,1C



Connectors' packaging



All dimensions are in mm.



COMPONENTS	MATERIALS	PLATING (µm)
BODY	BRASS	NICKEL 2
CENTER CONTACT	BERYLLIUM COPPER	NPGR
OUTER CONTACT	BRASS	NPGR
INSULATOR	PEEK , ULTEM	
GASKET	-	
OTHERS PARTS	LIQUID CRISTAL POLYMER	
.	.	.
.	.	.

Issue : 0727 D

In the effort to improve our products, we reserve the right to make changes judged to be necessary.



**R/A FEMALE MODULE 6 SOLDER TYPE INSERTS**  
**2.5MM FOR PCB**

**R694.252.107**

Series : MCC2

**PACKAGING**

**SPECIFICATION**

Standard	Unit	Other
<b>50</b>	<b>'W' option</b>	<b>Contact us</b>

**ELECTRICAL CHARACTERISTICS**

Impedance	<b>50</b>	$\Omega$
Frequency	<b>0-6</b>	GHz
VSWR	<b>1.15*</b> + <b>0,0000</b>	x F(GHz) Maxi
Insertion loss	<b>0.2</b>	$\sqrt{F}(\text{GHz})$ dB Maxi
RF leakage	- ( <b>AD</b> )	- F(GHz)) dB Maxi
Voltage rating	<b>500</b>	Veff Maxi
Dielectric withstanding voltage	<b>750</b>	Veff mini
Insulation resistance	<b>5000</b>	M $\Omega$ mini

**ENVIRONMENTAL**

Operating temperature	<b>-25/+125</b>	$^{\circ}\text{C}$
Hermetic seal	<b>NA</b>	Atm.cm3/s
Panel leakage	<b>NA</b>	

**OTHER CHARACTERISTICS**

Assembly instruction

Others :

\*VSWR optimized between DC to 3GHz

**MECHANICAL CHARACTERISTICS**

Center contact retention		
Axial force – Mating end	<b>6</b>	N mini
Axial force – Opposite end	<b>6</b>	N mini
Torque	<b>NA</b>	N.cm mini
Recommended torque		
Mating	<b>NA</b>	N.cm
Panel nut	<b>NA</b>	N.cm
Mating life	<b>500</b>	Cycles mini
Weight	<b>7,1000</b>	g

Issue : 0727 D


In the effort to improve our products, we reserve the right to make changes judged to be necessary.



**R/A FEMALE MODULE 6 SOLDER TYPE INSERTS**  
**2.5MM FOR PCB**

**R694.252.107**

Series : MCC2



Issue : 0727 D

In the effort to improve our products, we reserve the right to make changes judged to be necessary.




**R/A FEMALE MODULE 6 SOLDER TYPE INSERTS**  
**2.5MM FOR PCB**


**R694.252.107**

Series : MCC2


- Place the coax connector(s) on the PCB



- Place correctly the PCB between the punch and the nest of the press.
- In case of multiple housing configuration , use a punch and a nest large enough to cover all the housings.
- Press on the plastic housing(s) with the punch until the complete insertion of the fixing stud into the PCB.



- Solder the legs on board



Radiall do not recommend to use more than 3 modules on the same motherboard and can't be held liable of any connection defect when more than 3 modules are implemented on the board.

Issue : 0727 D

In the effort to improve our products, we reserve the right to make changes judged to be necessary.

