


## Item # F-1000U (End of Life), Single Secondary Chassis Mount Power Transformers

Triad offers a full choice of power supply transformers for direct use or in transformer, rectifier, or filter circuits. Other available secondary voltages include control, filament and low level signaling in standard values. The transformers are single primary with single and multiple secondaries in standard size and weight configurations.



### Specifications

<b>Secondary Voltage</b>	24.0 V
<b>Secondary Current</b>	21.000 A
<b>Transformer Contact Type</b>	Center Tap
<b>Primary Voltage</b>	115 V 230 V
<b>Primary Frequency</b>	50 Hz 60 Hz
<b>Secondary RMS Test Voltage</b>	1,500 V
<b>Case Type</b>	U

<b>Connections</b>	Leads
<b>Height (H)</b>	5 1/4 in
<b>Width (W)</b>	4 3/8 in
<b>Depth (D)</b>	3 1/2 in
<b>Mounting Width</b>	3 1/2 in
<b>Mounting Depth</b>	23/4 in
<b>Mounting Hole Size</b>	13/64 x 3/8 in
<b>Weight</b>	14.00 lb