



# Data Sheet

## RISH MIT 30

Analog Digital Multimeter  
with Insulation resistance



Measure



Control



Record



Analyze

## Application :

**RISH MIT 30** is Analog Digital Multimeter with insulation resistance measurement , which measures VAC, VDC, VAC+DC, Frequency, mA DC, mA AC+DC, Resistance, continuity, Diode, Farad, AC current measurement with clip-on sensor and insulation resistance measurement.

## Product Features:

### Insulation resistance measurement up to 3GΩ.

Insulation resistance measurement up to 3GΩ with Test voltages selection: 50 V, 100V, 250V, 500V and 1000V.

### Route mean square value with distorted wave form.

Measuring principal employed permits the measurement of root mean square value (TRMS) OF AC quantities and mixed quantities (AC and DC) regardless of wave form.

### AC Current measurement with clip-on sensor

Current measurement up to 300A with clip-on sensor having ratio 1mv/10mA.

### Min/Max Function

By pressing min/max button instrument will start recording minimum and maximum readings.

### Temperature measurement

Temperatures from -200 to 800°C using pt100 and pt 1000 sensors.

### Auto Power Off

In order to save the power of the Batteries, the meter will automatically shut OFF if it detects no activity for 10 minutes.

### Continuity test

This permits testing for short circuit and open circuit. In addition to the display, a facility of sound signal is available.

### AUTO and MANUAL ranging modes.

In AUTO ranging mode the instrument automatically selects the range with best resolution depending on the applied input. In MANUAL ranging mode range is user selectable using **MAN** key.

### Indication of negative values on the analog scale.

When measuring DC quantities, also negative values are shown on the analog scale so that variations of the measured value can be observed at the Zero point.

### Protection from dust and water:

Instrument: Ip50 For terminals : IP20 as per IEC60529

### Applicable International Safety standards

1000 V CAT II/600V CAT III as per International Safety standard IEC 61010-1- 2001 and IEC 61557.

### Signaling in the case of a blown fuse.

The display shows "FUSE" in case of blown fuse.

### Automatic blocking socket(ABS)

The automatic terminal blocking system prevents incorrect connection of test lead and incorrect selection of measurement quantity, which provide safety to the user.

### Interface and software RISH com 100.

The multimeters are fitted with a serial RS-232 C interface via which the measured values can be transmitted to a PC. These values, electrically isolated, are transmitted to the attachable interface adaptor with infrared light through the case.

### Analog Scale

Analog scale that updates at the rate 20 times/sec to observe fluctuations in input.

### Continuous On Mode

In this mode, AUTO POWER OFF is disabled.

### DATA Hold Function

By pressing DATA HOLD button, reading on the display can be latched for Hands free operation.

### NULL ZERO Correction for Resistance

For Low ohm measurement, the lead resistance can be compensated by pressing the shift key (Yellow Key)

### NULL ZERO Correction for Capacitance

Null zero connection for capacitance. For nF range, stray capacitance can be compensated by shift key (Yellow Key)

### Diode Measurement


For testing diode and transistors, diode measurement function is available.

### Display with Backlit.

For clear visibility in dark conditions, RISH MIT 30 is featured with backlit.

## Specifications:

| Measuring function | Measuring range        | Resolution     | Input impedance | Intrinsic error of digital display<br>± (...% of rdg + ...digit) at reference condition | Over load capacity <sup>1)</sup>             |                   |
|--------------------|------------------------|----------------|-----------------|-----------------------------------------------------------------------------------------|----------------------------------------------|-------------------|
|                    |                        |                |                 |                                                                                         | Over load value                              | Overload duration |
| V dc               | 30.00 mV               | 10 µV          | >10 GΩ // <40pF | 0.5 + 3 <sup>2)</sup>                                                                   | 1000 V<br>DC<br>AC<br>eff / rms<br>Sine wave | Continuously      |
|                    | 300.0 mV               | 100 µV         | >10 GΩ // <40pF | 0.5 + 3                                                                                 |                                              |                   |
|                    | 3.000 V                | 1 mV           | 11 MΩ // <40pF  | 0.25 + 1                                                                                |                                              |                   |
|                    | 30.00 V                | 10 mV          | 10 MΩ // <40pF  | 0.25 + 1                                                                                |                                              |                   |
|                    | 300.0 V                | 100 mV         | 10 MΩ // <40pF  | 0.25 + 1                                                                                |                                              |                   |
| V ~                | 1000 V                 | 1 V            | 10 MΩ // <40pF  | 0.35 + 1                                                                                |                                              |                   |
|                    | 3.000 V                | 1 mV           | 11 MΩ // <40pF  | 1.0 + 3 (>10 Digits)                                                                    |                                              |                   |
|                    | 30.00 V                | 10 mV          | 10 MΩ // <40pF  |                                                                                         |                                              |                   |
|                    | 300.0 V                | 100 mV         | 10 MΩ // <40pF  |                                                                                         |                                              |                   |
| 1000 V             | 1V                     | 10 MΩ // <40pF |                 |                                                                                         |                                              |                   |
| V AC+DC            | 3.000 V                | 1 mV           | 11 MΩ // <40pF  | 1.0 + 3 (>10 Digits)                                                                    |                                              |                   |
|                    | 30.00 V                | 10 mV          | 10 MΩ // <40pF  |                                                                                         |                                              |                   |
|                    | 300.0 V                | 100 mV         | 10 MΩ // <40pF  |                                                                                         |                                              |                   |
|                    | 1000 V                 | 1V             | 10 MΩ // <40pF  |                                                                                         |                                              |                   |
| A AC with clamp 6) | 30/300 A               | 10/100mA       | –               | 0.5 +5                                                                                  | –                                            | --                |
| A DC               | <b>Voltage Drop</b>    |                |                 |                                                                                         | 0.36 A                                       | Continuously      |
|                    | 300.0 µA               | 100 nA         | 15 mV           | 0.5+5 (>10 Digit)                                                                       |                                              |                   |
|                    | 3.000 mA               | 1 µA           | 150 mV          | 0.5+2                                                                                   |                                              |                   |
|                    | 30.00 mA               | 10 µA          | 650 mV          | 0.5+5 (>10 Digit)                                                                       |                                              |                   |
| A AC+DC            | 300.0 mA               | 100 µA         | 1V              | 0.5+5                                                                                   | 0.36 A                                       | Continuously      |
|                    | 3.000 mA               | 1 µA           | 150 mV          | 1.5+4 (>10 Digit)                                                                       |                                              |                   |
|                    | 300.0 mA               | 100 µA         | 1 V             | 1.5+4 (>10 Digit)                                                                       |                                              |                   |
| Ω                  | <b>No load voltage</b> |                |                 |                                                                                         | 1000 V<br>DC<br>AC<br>eff / rms<br>Sine wave | 10 sec            |
|                    | 30.00 Ω                | 10 mΩ          | Max. 3.2 V      | 0.5 + 3 <sup>2)</sup>                                                                   |                                              |                   |
|                    | 300.0 Ω                | 100 mΩ         | Max. 3.2 V      | 0.5 + 3                                                                                 |                                              |                   |
|                    | 3.000 KΩ               | 1Ω             | Max. 1.25 V     | 0.4 + 1                                                                                 |                                              |                   |
|                    | 30.00 KΩ               | 10 Ω           | Max. 1.25 V     | 0.4 + 1                                                                                 |                                              |                   |
|                    | 300.0 KΩ               | 100 Ω          | Max. 1.25 V     | 0.4 + 1                                                                                 |                                              |                   |
|                    | 3.000 MΩ               | 1 KΩ           | Max. 1.25 V     | 0.6 + 1                                                                                 |                                              |                   |
| →                  | 2.000 V                | 1 mV           | Max. 3.2 V      | 2.0 + 1                                                                                 |                                              |                   |

| Measuring function                                                                           | Measuring range | Resolution | Discharge resistance | U0 max. | Intrinsic error of digital display<br>± (...% of rdg + ...digit) at reference condition | Over load capacity <sup>1)</sup>        |                   |
|----------------------------------------------------------------------------------------------|-----------------|------------|----------------------|---------|-----------------------------------------------------------------------------------------|-----------------------------------------|-------------------|
|                                                                                              |                 |            |                      |         |                                                                                         | Over load value                         | Overload duration |
| Farad<br> | 30.00 nF        | 10 pF      | 250 KΩ               | 2.5 V   | 1.0 + 3 <sup>2)</sup>                                                                   | 1000 V<br>DC<br>AC<br>eff / rms<br>Sine | 10 sec            |
|                                                                                              | 300.0 nF        | 100 pF     | 250 KΩ               | 2.5 V   | 1.0 + 3                                                                                 |                                         |                   |
|                                                                                              | 3.000 µF        | 1 nF       | 25 KΩ                | 2.5 V   | 1.0 + 3                                                                                 |                                         |                   |
|                                                                                              | 30.00 µF        | 10 nF      | 25 KΩ                | 2.5 V   | 3.0 + 3                                                                                 |                                         |                   |

| Measuring function     | Measuring range | Resolution             | Discharge resistance   | U0 max.               | Intrinsic error of digital display<br>± (...% of rdg + ...digit) at reference condition | Over load capacity <sup>1)</sup>                            |                                         |
|------------------------|-----------------|------------------------|------------------------|-----------------------|-----------------------------------------------------------------------------------------|-------------------------------------------------------------|-----------------------------------------|
|                        |                 |                        |                        |                       |                                                                                         | Over load value                                             | Overload duration                       |
| Hz                     |                 |                        | <b>f min V dc</b>      | <b>f min V ~</b>      | 0.5 + 1 <sup>3)</sup>                                                                   | ≤ 3 kHz<br>1000 v<br>≤ 30 kHz;<br>300 V<br>≤100 kHz<br>30 V | Continuously                            |
|                        | 300.0 Hz        | 0.1 Hz                 | 1 Hz                   | 45 Hz                 |                                                                                         |                                                             |                                         |
|                        | 3.000 KHz       | 1 Hz                   | 1 Hz                   | 45 Hz                 |                                                                                         |                                                             |                                         |
|                        | 30.00 KHz       | 10 Hz                  | 10 Hz                  | 45 Hz                 |                                                                                         |                                                             |                                         |
| %                      | 2.0...98.0%     |                        | 2 Hz                   | --                    | 2 Hz... 1kHz ± 5 Digit <sup>4)</sup><br>1 kHz ... 10 kHz; ± 5 Digit / kHz <sup>4)</sup> |                                                             |                                         |
|                        | °C              | Pt<br>100              | -200.0...<br>+200.0 °C | 0.1 °C                | --                                                                                      | 2 Kelvin + 5 Digit <sup>5)</sup>                            | 1000 V<br>DC<br>AC<br>eff / rms<br>Sine |
| +200.0...<br>+850.0 °C |                 |                        | 0.1 °C                 | 1.0 + 5 <sup>5)</sup> |                                                                                         |                                                             |                                         |
| Pt<br>1000             |                 | -100.0...<br>+200.0 °C | 0.1 °C                 | --                    | 2 Kelvin + 2 Digit <sup>5)</sup>                                                        |                                                             |                                         |
|                        |                 | +200.0...<br>+850.0 °C | 0.1 °C                 |                       | 1.0 + 2 <sup>5)</sup>                                                                   |                                                             |                                         |

## Reference conditions for Accuracy:

|                               |                 |
|-------------------------------|-----------------|
| Reference temperature         | 23°C ± 2K       |
| Relative Humidity             | 45%...55% RH    |
| Waveform of measured quantity | Sinusoidal      |
| Input frequency               | 50 or 60 Hz ±2% |
| Battery Voltage               | 8 V ± 0.1 V     |

## Response time (After manual range selection):

| Measured Quantity/<br>Measured Response time | Response Time        |                       | Transient response for step function of<br>the measured quantity |
|----------------------------------------------|----------------------|-----------------------|------------------------------------------------------------------|
|                                              | Of Analog indication | Of digital indication |                                                                  |
| VDC, VAC, AAC+DC, AAC                        | 0.7 s                | 1.5 s                 | From 0 to 80 % of upper range limit.                             |
| 30Ω...3 MΩ                                   | 1.5 s                | 2 s                   |                                                                  |
| 30 MΩ                                        | 4 s                  | 5 s                   | From ∞ to 50 % of upper range limit.                             |
|                                              | 0.7s                 | 1.5s                  |                                                                  |
| nF, μF, °C,                                  |                      | Max. 1... 3 s         |                                                                  |
| 300 Hz, 3KHz                                 |                      | Max 2 s               | From 0 to 80 % of upper range limit.                             |
| 30 KHz, 300 KHz                              |                      | Max 0.7 s             |                                                                  |
| % (1 Hz)                                     |                      | Max 9 s               |                                                                  |
| % (≥10 Hz)                                   |                      | Max 2.5 s             |                                                                  |

## Environmental

|                       |                      |
|-----------------------|----------------------|
| Operating temperature | -20 to +50°C         |
| Storage temperature   | -25 to +70°C         |
| Relative humidity     | <75% non condensing. |
| Terminal Protection   | IP20 for terminals   |
| Altitude              | Up to 2000 m         |

## Battery

|                 |                                                                                                                                                                                                             |
|-----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Battery Voltage | 6 x 1.5 V Cells                                                                                                                                                                                             |
| Battery type    | Alkaline manganese Dioxide cell as per IEC LR 03 , ANSI 24A (Size AAA)                                                                                                                                      |
| Battery Life    | Minimum 600 hours on Vdc, Adc ,240 hours on Vac, Aac,<br>For MΩISO @1000 V, 800 Measurements possible with nominal current<br>MΩISO @500,250V, 100V, 50 V, 2400 Measurements possible with nominal current. |

## Interface

|                   |                                                 |
|-------------------|-------------------------------------------------|
| Type              | RS232C, serial, as per DIN 19241.               |
| Data transmission | Optically with infrared light through the case. |
| Baud rate         | 8192 bits/s.                                    |

## Influence Quantities and Variations:

| Influence Quantity | Measuring Range  | Resolution | Intrinsic error of digital display<br>± (...% of rdg + ...digit) at<br>reference condition |
|--------------------|------------------|------------|--------------------------------------------------------------------------------------------|
| V1MΩ <sup>7)</sup> | 0...1000 V AC+DC | 1V         | 1+10 D                                                                                     |
| MΩIT@1000V 8)      | 0...1000 V AC+DC | 1V         | 1+10 D                                                                                     |
| MΩIT Un=50 V       | 0.100...1.600 MΩ | 1KΩ        | --                                                                                         |
|                    | 01.40...16.00 MΩ | 10 KΩ      | 5 + 15 D                                                                                   |
| MΩIT Un=100 V      | 014.0...155.0 MΩ | 100 KΩ     | --                                                                                         |
|                    | 0.100...3.100 MΩ | 1KΩ        | --                                                                                         |
|                    | 02.80...31.00 MΩ | 10 KΩ      | 5 + 15 D                                                                                   |
| MΩIT Un=250 V      | 028.0...310.0 MΩ | 100 KΩ     | --                                                                                         |
|                    | 0.100...0.800 MΩ | 1KΩ        | --                                                                                         |
|                    | 00.70...08.00 MΩ | 10 KΩ      | 3 + 10 D                                                                                   |
|                    | 007.0...080.0 MΩ | 100 KΩ     | --                                                                                         |
| MΩIT Un=500 V      | 0070...0775 MΩ   | 1MΩ        | --                                                                                         |
|                    | 0.100...1.600 MΩ | 1KΩ        | --                                                                                         |
|                    | 01.40...16.00 MΩ | 10 KΩ      | 3 + 10 D                                                                                   |
|                    | 014.0...160.0 MΩ | 100 KΩ     | --                                                                                         |
| MΩIT Un=1000 V     | 0140...1600 MΩ   | 1MΩ        | --                                                                                         |
|                    | 0.100...3.100 MΩ | 1KΩ        | --                                                                                         |
|                    | 02.80...31.00 MΩ | 10 KΩ      | 3 + 10 D                                                                                   |
|                    | 028.0...310.0 MΩ | 100 KΩ     | --                                                                                         |
|                    | 0280...3100 MΩ   | 1MΩ        | --                                                                                         |

- 1) At 0° .... + 40 °C
- 2) With zero adjustment, without zero adjustment + 50 digits
- 3) Range
  - 3 V ac/dc: Ue = 1.5 V eff/rms ... 100 V eff/rms
  - 30 V ac/dc: Ue = 15 V eff/rms ... 300 V eff/rms
  - 300 V ac/dc: Ue = 150 V eff/rms ... 1000 V eff/rms
- 4) On the range 3 V dc, square – wave signal positive on one side 5 ... 15 V,  
f = const., not 163.84 Hz or integral multiple.
- 5) Without sensor.
- 6) Measurement with clip-on current sensor with ratio 1mv/10mA.
- 7) Discharge the DUT through 1MΩ resistance, before insulation resistance measurement. LCD displays value of voltage present on DUT.
- 8) In this switch position live circuit detection (V AD+DC) is done before insulation measurement. If voltage present is greater than 50V (AC+DC), insulation resistance measurement function is disabled and LCD displays value of voltage present on DUT.

| Influence Quantity                               | Range of Influence                                       | Measured Quantity / measuring Range | Variation <sup>1)</sup><br>± (...% of rdg. + ....digits) |            |
|--------------------------------------------------|----------------------------------------------------------|-------------------------------------|----------------------------------------------------------|------------|
| Temperature                                      | 0 °C<br>+21 °C<br>and<br>+25 °C...+40°C<br>MΩIT 0.25 + 2 | 30/300 mV dc                        | 1.0 + 3                                                  |            |
|                                                  |                                                          | 3...300 V dc                        | 0.15 + 1                                                 |            |
|                                                  |                                                          | 1000 V dc                           | 0.2 + 1                                                  |            |
|                                                  |                                                          | V ~                                 | 0.4 + 1                                                  |            |
|                                                  |                                                          | 300µA ... 300mA DC                  | 0.5+1                                                    |            |
|                                                  |                                                          | A AC+DC                             | 0.75+3                                                   |            |
|                                                  |                                                          | 30 Ω 2)                             | 0.15 + 2                                                 |            |
|                                                  |                                                          |                                     | 300 Ω 0.25 + 2                                           |            |
|                                                  |                                                          |                                     | 3 KΩ – 3 MΩ                                              | 0.15 + 1   |
|                                                  |                                                          |                                     | 30 MΩ                                                    | 1.0 + 1    |
|                                                  |                                                          |                                     | 30 nF <sup>2)</sup> – 3 µF                               | 0.5 + 2    |
|                                                  |                                                          |                                     | 30 µF                                                    | 2.0 + 2    |
|                                                  |                                                          |                                     | Hz                                                       | 0.5 + 1    |
|                                                  |                                                          |                                     | %                                                        | ± 5 digits |
| Frequency of the measured quantity               | 15 Hz...< 30 Hz                                          | 3...1000 V ~                        | 1.0 + 3                                                  |            |
|                                                  | 30 Hz...< 45 Hz                                          |                                     | 0.5 + 3                                                  |            |
|                                                  | > 65 Hz... 400 Hz                                        |                                     | 2.0 + 3                                                  |            |
|                                                  | >400 Hz...1 KHz                                          |                                     | 3.0 + 3                                                  |            |
|                                                  | 20Hz ...< 45 Hz                                          |                                     | 3.0 + 7                                                  |            |
|                                                  | >66 Hz... 1 kHz                                          |                                     | 2.0 + 3                                                  |            |
| Wave form of the measured quantity <sup>3)</sup> | Crest factor CF                                          | V ~ 4), A~ 4)                       | ± 1 % of rdg                                             |            |
|                                                  |                                                          |                                     | ± 3 % of rdg                                             |            |
| Battery Voltage                                  | ⎓ <sup>5)</sup> ...< 7.9 V<br>> 8.1 V ...10.0 V          | V DC                                | 2 Digit                                                  |            |
|                                                  |                                                          | V~, ADC                             | 4 Digit                                                  |            |
|                                                  |                                                          | A AC+DC                             | 6 Digit                                                  |            |
|                                                  |                                                          | 30Ω / 300 Ω/°C                      | 4 Digit                                                  |            |
|                                                  |                                                          | 3 kΩ – 30MΩ, MΩIT                   | 3 Digit                                                  |            |
|                                                  |                                                          | nF, µF,                             | 1 Digit                                                  |            |
|                                                  |                                                          | Hz                                  | 1 Digit                                                  |            |
| %                                                | 1 Digit                                                  |                                     |                                                          |            |
| Relative humidity                                | 75%                                                      | V~,V DC<br>AAC+DC,A DC              | 3 Days                                                   |            |
|                                                  | 3 Days                                                   | Ω                                   | 1 x intrinsic error                                      |            |
|                                                  | Meter off                                                | Hz<br>°C                            |                                                          |            |
| DATA                                             | -                                                        | %                                   | ± 1 digits                                               |            |
| MIN/MAX                                          | -                                                        | V ac/dc , A ac/dc, clamp            | ± 2 digits                                               |            |

- 1) With temperature: Error data apply per 10 K change in temperature.  
With frequency: Error data apply to a display from 300 digits onwards.
- 2) With zero adjustment.
- 3) With unknown waveform (crest factor CF > 2), measure with manual range selection
- 4) With the exception of sinusoidal waveform.
- 5) After the “⎓” symbol is displayed.

| Influence Quantity               | Range of Influence                                                                                               | measuring Range              | Attenuation         |
|----------------------------------|------------------------------------------------------------------------------------------------------------------|------------------------------|---------------------|
| Common Mode interference voltage | Noise quantity max. 1000 V                                                                                       | V dc<br>3V~ , 30V~<br>300 V~ | > 120 dB<br>> 70 dB |
|                                  |                                                                                                                  | 1000 V~                      | > 60 dB             |
| Normal Mode Interference Voltage | Noise quantity max. 1000 V ~<br><br>Value of the measuring range at a time<br>Max. 1000V~ ,50Hz, 60Hz sinusoidal | V dc                         | 50dB                |
|                                  | Noise quantity max. 1000 V-                                                                                      | V~                           | >110dB              |

### Applicable Standards:

For Use as a Insulation Measuring Instrument.

IEC 61557: Devices for testing, measuring and monitoring protective safety measures in system with voltages of up to 1000 V A.C. and 1500 V D.C.

IEC 61557- 1: For general requirements

IEC 61557- 2: For Insulation resistance measuring instruments

IEC 61326: Class B

IEC 61000-4-2 8 KV atmosphere discharge, 4 KV contact discharge

IEC 61000-4-3 : 3 V/m

EMC

Immunity

### Safety

IEC 61010-1-2001

IP for water & dust

IEC60529

Pollution degree:

2

Installation category:

III

High Voltage Test

3.5 kV (IEC 61010-1-2001)



RISHABH

All specifications are subject to change without notice



Measure



Control



Record



Analyze

## RISHABH INSTRUMENTS LIMITED

Domestic (India): +91 253 2202028/99 | [marketing@rishabh.co.in](mailto:marketing@rishabh.co.in)

International: +91 253 2202004/06/08/99 | [global@rishabh.co.in](mailto:global@rishabh.co.in)

[www.rishabh.co.in](http://www.rishabh.co.in)