## 0.75 METER LENGTH



Connector A 112234 BNC Jack Straight Bulkhead - Rear Mount Brass Nickel 50 Ohm RG-174 Continuity/Hi-Pot Connector B 132119 SMA Jack Straight Bulkhead - Rear Mount Brass Gold + Heatshrink

## Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

	Connector A			Cable			Connector B		
	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting:	112234 BNC Clamp BHD JK RG188 500 BNC Jack Straight Crimp Standard 50 Ohm Bulkhead - Rear Mount Brass Nickel None Beryllium Copper Silver 4 GHz BNC Jack Straight BHD		Part #: Description: Dielectric: Shielding: Diameter: Impedance: Sheathing: Testing: Length:	RG-174 RG-174 - PE 0.1 PE Braid 0.1 50 Ohm None Continuity Hi-Pot 0.75 Meter	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting: Clocking:	132119 SMA BHD JK RG17 SMA Jack Straight Solder Standard 50 Ohm Bulkhead - Rear Mo Brass Gold None Beryllium Copper Gold 12.4 GHz	SMA BHD JK RG174 RG188 RG316 500 SMA Jack Straight Solder Standard 50 Ohm Bulkhead - Rear Mount Brass Gold None Beryllium Copper Gold 12.4 GHz SMA Jack Straight BHD	
Amphenol CUSTOM CABLE			THIS DRAWING MAY CONTAIN PATENTED OR PROPRIETARY INFORMATION AND MUST NOT BE USED FOR ANY PURPOSE DETRIMENTAL TO CUSTOM CABLE N. IT MAY NOT BE REPRODUCED OR TRANSCRIBED N ANY FORM WITHOUT THE WRITTEN CONSENT OF JUSTOM CABLE INC. ACCEPTANCE OF THIS DRAWING ISTABLISHES AND AGREEMENT OF THE FOREGOING.		BLE ED F NG Part No:	BNC-ST-JK/SMA-ST-JK G174 0.75M			