

SmartPro 230V 750VA 500W Line-Interactive Sine Wave UPS, Tower, Network Card Options, USB, DB9 Serial

MODEL NUMBER: SMX750SLT





Highlights

- 750VA line interactive tower UPS; Sine wave output
- 220/230/240V nominal output during brownouts and overvoltages
- Add optional WEBCARDLX with latest version of PADM20 for enhanced remote management
- Front panel status LEDs with load level and battery capacity display
- C14 input; 6 C13 outlets; Includes 2 C13 to C14 cables

Package Includes

- SMX750SLT UPS System
- USB and serial cabling
- User manual with warranty information

Description

Tripp Lite's SMX750SLT intelligent, line-interactive sine wave UPS system protects servers, networking accessories and telecommunications equipment from blackouts, voltage fluctuations and transient surges. Large internal batteries offer 15 minutes half load runtime and 5 minutes full load runtime. 750VA/500 watt power handling capability and full-time sine wave output offers guaranteed compatibility with networking, telecom and other sensitive electronic applications. Includes 6 protected C13 output receptacles total. Network management interfaces support communications via USB, RS-232 and slot for network management card options. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Network communications ports enable detailed monitoring of equipment load levels, self-test data and utility power conditions. PowerAlert UPS monitoring software is available via free download. Single line Tel/DSL and network Ethernet line surge suppression. Built-in audible alarm and 9 LEDs offer status notification for line power, battery power, battery charge level, load level, plus AVR boost and trim operational status information. Network grade AC surge suppression protects equipment from damage and performance problems resulting from transient surges. Attractive, all-black tower housing.

Features

- SMX750SLT line-interactive UPS offers battery derived sine wave AC output during power outages, voltage regulation during brownouts and overvoltages, plus network-grade AC surge suppression
- 750VA/500 watt power handling capability with full-time sine wave output offers guaranteed compatibility with networking, telecom and other sensitive electronic devices
- Large internal batteries offer runtimes of 15 minutes at half load (325VA/250 watts) and 5 minutes at full load (750VA/500 watts)
- Intelligent battery management system extends battery life
- Automatic Voltage Regulation (AVR) circuits maintain user-selectable 220, 230 or 240V nominal output over an input voltage range of 151 to 290
- Includes 6 C13 output receptacles
- IEC320-C14 input connection accepts a variety of detachable cordsets
- Compatible with Tripp Lite UPS management card options WEBCARDLX, RELAYIOCARD, SNMPWEBCARD
- Optional WEBCARDLX (sold separately) with the latest version of PowerAlert Device Manager firmware (PADM20) provides enhanced remote management capabilities



- PADM20 and PowerAlert Element Manager (PAEM) form a powerful tool for expanding maintenance functions in large installations, including firmware update checks and backup and restoration of device configurations
- USB & Serial ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from tripplite.eaton.com/products/power-alert
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Supports Tripp Lite's WatchDog software application (requires optional WATCHDOGSW)
- 9 LEDs offer continuous status information of UPS operating parameters and site power quality
- Hot-swappable batteries allow on-site battery replacement without powering off connected equipment
- Single line Tel/DSL and network Ethernet line surge suppression

Specifications

OVERVIEW		
UPC Code	037332124388	
UPS Type	Line-Interactive	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	3.6A (220V), 3.5A (230V), 3.4A (240V)	
Nominal Input Voltage(s) Supported	220V AC; 230V AC; 240V AC	
UPS Input Connection Type	C14 inlet	
UPS Input Connection Description	IEC320-C14 input connection accepts a variety of detachable cordsets to match country or site-specific wall receptacles	
ОИТРИТ		
Output Capacity (VA)	750	
Output Capacity (kVA)	0.75	
Output Capacity (Watts)	500	
Output Capacity (kW)	0.5	
Power Factor	0.7	
Nominal Voltage Details	230V default (voltage selection via back panel switches)	
Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	Automatic frequency selection	
Output Voltage Regulation (Line Mode)	-11%, +6%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Included Output Power Cables	Includes 2 C13 to C14 output power cables	
Output AC Waveform (AC Mode)	Sine wave	



Output Ac Waveform (Battery Modage (s) 220V; 230V; 240V 250V; 250V				
Supported (6) C13 Output Receptacles (6) C13 Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 5 min. (500W) Runtime Half Load (min.) 15 min. (500W) Runtime Half Load (min.) 15 min. (500W) Runtime Half Load (min.) 15 min. (500W) Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Archage Rate (included Batteries) Battery Access Battery Access Battery access door Internal UPS Replacement Battery Archage Rate (included Batteries) Battery Replacement Description Controllable Battery Access Battery Access Battery Access Battery Access Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% follorance Undervoltage Correction Voltage reduction of 12% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% follorance User INTERFACE, ALERTS & CONTROLS Switches Correction Power-flat alarm acan be silenced using alarm-cance/self-test operation; rear panel protected switches support nominal voltage selection Audible Alarm Audible alarm indicates power failure and overload conditions UPS AC Suppression Joule Rating SOLED indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level Instantaneous Instantaneous Instantaneous Instantaneous Instantaneous Instantaneous		Pure Sine wave		
Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 5 min. (500W) Runtime Full Load (min.) 15 min. (250W) Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Battery Cartridge Control of System Voltage (min.) 24 Battery Access Battery access door Battery Access Battery access door All DPS Replacement Battery Cartridge Forestellar (Included Battery Cartridge Forestellar (Internal DPS Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage accurate of 12% applies when input is 175-196 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints affect of 167% applies when input is 175-196 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints affect of 167% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V);	Nominal Output Voltage(s) Supported	220V; 230V; 240V		
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 5 min. (500W) Runtime Hull Load (min.) 15 min. (250W) Expandable Runtime No DC System Voltage (VDC) 24 Battary Access Battery Access door Internal UPS Replacement Battery Access Battery Access door Internal UPS Replacement Battery Access Battery Access	Output Receptacles	(6) C13		
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 5 min. (500W) Runtime Full Load (min.) 15 min. (250W) Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Battery Recharge Rate (Included Battery Access Battery access door Internal UPS Replacement Battery 8 mbsp.ca class="modulut.ink" hytel="//kirppilia.eaton.com/UPS-Replacement-24VDC-Battery-Cartridge-for-select-darridge Battery Replacement Description Hot-swappable. user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints -5% tolerance Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage boost of 30% applies wh	Individually Controllable Load Banks	No		
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 5 min. (500W) Runtime Full Load (min.) 15 min. (250W) Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Battery Recharge Rate (Included Battery Access Battery access door Internal UPS Replacement Battery 8 mbsp.ca class="modulut.ink" hytel="//kirppilia.eaton.com/UPS-Replacement-24VDC-Battery-Cartridge-for-select-darridge Battery Replacement Description Hot-swappable. user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints -5% tolerance Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints -5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage boost of 30% applies wh	BATTERY			
Runtime Full Load (min.) 5 min. (500W) Runtime Half Load (min.) 15 min. (550W) Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Battery access door Internal LPS Replacement Battery Arbap-va class="modusel-link" hydrol-"/kilpplite.eaton.com/UPS-Replacement-24VDC-Battery-Cartridge-for-select-Trap-Life-SLT-UPS-RBC24-SLT-">RBC24-SLT-Vas-Battery-Cartridge-for-select-Trap-Life-SLT-UPS-RBC24-SLT-Vas-Batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 299V Overvoltage Correction Voltage refuction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% tolerance Undervoltage Correction Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% tolerance Severe Undervoltage Correction Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Audible Alarm Audible alarm indicates power failure and overload conditions 1 LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION LPS AC Suppression Joule Rating 504 LPS AC Suppression Joule Rating 504		Valve Regulated Lead Acid (VRLA)		
Runtime Half Load (min.) 15 min. (250W) Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Batteries) Battery Access Battery Access Battery access door Internal UPS Replacement Battery Access Hots-sale and the selection of the	7 71	` '		
DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) Battery Access Battery access door Battery Access Battery access door Battery Access Battery access door Internal UPS Replacement Battery Thipp-Lite-St.T-UPSRBC24-St.T-x8BC24-St.T-x8Arbsp; Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage Correction Voltage boost of 15% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% folerance Severe Undervoltage Correction Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% folerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Audible Alarm Audible Alarm Audible alarm indicates power failure and overload conditions SUSPER INTERFACE 1 Suppression Joule Rating 504 UPS AC Suppression Joule Rating Instantaneous	` '			
Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Arribps:-ca class="productLink" href="//tripplite.eaton.com/UPS-Replacement-24VDC-Battery-Cartridge-for-select-cartridge-for-se	Expandable Runtime	No		
Battery Access Battery access does not solve the product Link* here="//tripplite.eaton.com/UPS-Replacement-24VDC-Battery-Cartridge-for-select-cartridge for-select-cartridge for-	DC System Voltage (VDC)	24		
Internal UPS Replacement Battery Cartridge Anbsp;-a class="productLink" href="//tripplite.eaton.com/UPS-Replacement-24VDC-Battery-Cartridge-for-select-Tripp-Lite-SLT-UPS-RBC24-SLT'>-RBC24-SLT-/a>-Anbsp; Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Vervoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% folerance Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% folerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V		Less than 4 hours to 90% (typical, full load discharge)		
Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% tolerance Undervoltage Correction Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support norninal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level UPS AC Suppression Joule Rating 504 UPS AC Suppression Response Instantaneous	Battery Access	Battery access door		
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% tolerance Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level UPS AC Suppression Joule Rating 504 UPS AC Suppression Response Time Instantaneous	Internal UPS Replacement Battery Cartridge	RBC24-SLT		
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V Overvoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% tolerance Undervoltage Correction Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 504 UPS AC Suppression Response Instantaneous	Battery Replacement Description	Hot-swappable, user replaceable batteries		
Overvoltage Correction Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% tolerance Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% tolerance Severe Undervoltage Correction Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating Instantaneous	VOLTAGE REGULATION			
Undervoltage Correction Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% tolerance Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 10 LED Instantaneous 11 LED Instantaneous	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 290V		
Severe Undervoltage Correction Voltage boost of 30% applies when input is 151-174 (220V), 158-181 (230V), 166-190 (240V); Voltage setpoints ±5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 504 UPS AC Suppression Response Instantaneous	Overvoltage Correction	Voltage reduction of 12% applies when input is 232-266 (220V), 244-278 (230V), 254-290 (240V); Voltage setpoints ±5% tolerance		
#5% tolerance USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 504 UPS AC Suppression Response Time Instantaneous	Undervoltage Correction	Voltage boost of 15% applies when input is 175-198 (220V), 182-206 (230V), 190-216 (240V); Voltage setpoints ±5% tolerance		
Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; rear panel protected switches support nominal voltage selection Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 504 UPS AC Suppression Response Instantaneous	Severe Undervoltage Correction			
Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 504 UPS AC Suppression Response Instantaneous	USER INTERFACE, ALERTS & CON	USER INTERFACE, ALERTS & CONTROLS		
Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	Switches			
LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch		
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	Audible Alarm	Audible alarm indicates power failure and overload conditions		
UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous	LED Indicators			
UPS AC Suppression Response Time Instantaneous	SURGE / NOISE SUPPRESSION			
Time "Instantaneous"	UPS AC Suppression Joule Rating	504		
UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet		Instantaneous		
	UPS Dataline Suppression	1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet		



EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Primary Form Factor	Tower	
Cooling Method	Fan	
Installation Form Factors Supported with Included Accessories	Tower	
Primary UPS Depth (mm)	337	
Primary UPS Height (mm)	260	
Primary UPS Width (mm)	171	
Shipping Dimensions (hwd / in.)	14.00 x 9.75 x 18.50	
Shipping Dimensions (hwd / cm)	35.56 x 24.76 x 46.99	
Shipping Weight (lbs.)	38.60	
Shipping Weight (kg)	17.51	
UPS Housing Material	Steel	
UPS Power Module Dimensions (hwd, cm)	26.04 x 17.14 x 33.66	
UPS Power Module Dimensions (hwd, in.)	10.25 x 6.75 x 13.25	
UPS Power Module Weight (kg)	15.47	
UPS Power Module Weight (lbs.)	34.1	
Unit Dimensions (hwd / in.)	10.250 x 6.750 x 13.250	
Unit Weight (lbs.)	34.1000	
Unit Weight (kg)	15.47	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Storage Temperature Range	5° to 122°F (-15° to 50°C)	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	73	
AC Mode Efficiency Rating (100% Load)	96%	
Operating Elevation (ft.)	Up to 10,000 ft	
Audible Noise	Audible Noise < 50 dBA at Front Side 1 Meter	
Operating Elevation (m)	Up to 3,000m	
COMMUNICATIONS		



Network Management Cards	SNMPWEBCARD; WEBCARDLX ; RELAYIOCARD
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert
Communications Cable	USB and DB9 cabling included
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
Network Management Card Description	Network management card optional
Communications Interface	DB9 Serial; Slot for SNMP/Web interface; USB (HID enabled)
LINE / BATTERY TRANSFER	
Transfer Time	4-8 milliseconds
Low Voltage Transfer to Battery Power (Setpoint)	151 (220V), 158 (230V), 166 (240V); Voltage setpoints ±5% tolerance
High Voltage Transfer to Battery Power (Setpoint)	266V (220V), 278V (230V) or 290V (240V); Voltage setpoints ±5% tolerance
FEATURES & SPECIFICATIONS	
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported
High Availability UPS Features	Auto Probe Monitoring (requires WEBCARDLX); Automatic Voltage Regulation (AVR); Hot swappable batteries; Remote management; Sine wave output; Surge/noise protection
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS
STANDARDS & COMPLIANCE	
Product Certifications	GOST (Russia); EN 62040-1; EN 62040-2
Product Compliance	RoHS; SASO (Saudi Arabia); CE (Europe)
WARRANTY & SUPPORT	
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	2-year limited warranty
Product Warranty Period (Puerto Rico)	2-year limited warranty



© 2023 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.