

# CST206-3A

### **Description:**

Designed for switching power supply applications, Triad current sense transformers are used to detect the current passing through a conductor. These transformers are very reliable and operate over the frequency range of 20 kHz-200 kHz.

## **Electrical Specifications (@25C)**

ET VµSEC REF 20kHz	Turns Count	Min. Ind. mH	DCR Max. Ω	Pri. Amps	
6000	300	130.0	12.40	70.0 RMS	

#### Safety:

These current sense transformers are constructed of UL rated 130°C materials.


# **Dimensions:**

Α	В	С	D	Е	F	G	н
Min	Max	Ref	Ref	Ref	Max	Max	Dia. Pins
.360	1.225	.700	.127	.500	.400	1.075	.045

Units: In inches

#### **Technical Notes:**

- 1. Derate ET product by 32% for 50 kHz, 52% for 100 kHz and 50% for unidirectional operation.
- 2. Rated primary current renders approximately 40°C temp. rise.
- 3. Maximum recommended terminating resistance of 1 ohm per turn.
- 4. Primary is inserted through hole in casting.




**RoHS Compliance:** As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

\*Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics website for the most current version. For soldering and washing information please see http://www.triadmagnetics.com/faq.html

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571



Publish Date: April 18, 2019