

POWER TRANSFORMER **CHASSIS MOUNT : OUICK-CONNECT WORLD SERIES TM**

VPS16-8100

Electrical Specifications (@25C)

- 1. Maximum Power: 130.0VA
- 2. Primary Series: 230VAC, 50/60Hz; Parallel: 115VAC, 50/60Hz
- 3. Secondary: Series: 16.0V CT@ 8.1A; Parallel: 8.0V @ 16.2A
- 4. Voltage Regulation: 25% TYP @ full load to no load
- 5. Temperature Rise: 30C TYP (45C MAX allowed)
- 6. Insulation Resistance: 100MΩ

Construction:

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

Safety:

These units are designed with 4000VAC isolation between the primary and secondary, and also, between each winding and the core. Since the dual bobbin construction effectively reduces capacitance, electrostatic shielding is not required. World Series Transformers are designed and manufactured to meet the following agency approvals:

Agency File:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose. CSA: File LR 221330. C22.2 NO. 66, General Purpose. TUV: File R72182067, EN 61558-1:2005+A1, EN61558-2-6:2009. Double Insulated. Non-inherently Short-Circuit-Proof.



A. Dimensions:

A. Dimensions:						Jnit: In inches		
н	W	D	А	В	С	т	MW	ML
3-3/8	2-13/16	2-11/16	-	1-5/8	3/8	1/4	2-1/4	2-1/2
B. Moun	ting Hole Siz	ze: 13/64")	X3/8"					

C. WT Lbs. : 4.1

D. Terminal Size: 0.250" x 0.030"

Connections¹:

Input: Series - 6 and 1, Jumper 5 to 2 Parallel - 6 and 1, Jumper 6 to 2 and 5 to 1 Output: Series - 12 and 7, Jumper 11 to 8

Parallel - 12 and 7, Jumper 12 to 8 and 11 to 7


RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.


* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571









Publish Date: August 26, 2021

¹ Primary and secondary windings are designed to be connected in series or parallel. Windings are not intended to be used independently.