ON Semiconductor

Is Now



To learn more about onsemi™, please visit our website at www.onsemi.com

onsemi and ONSEMI. and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/ or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use onsemi products for any such unintended or unauthorized application,

Power MOSFET -60 V, 13 mΩ, -80 A, P-Channel

Automotive Power MOSFET designed for compact and efficient designs and including high thermal performance.

 $AEC\mbox{-}Q101$ qualified MOSFET and PPAP capable suitable for automotive applications.



- Low On-Resistance
- High Current Capability
- 100% Avalanche Tested
- AEC-Q101 qualified and PPAP capable
- ATPAK package is pin-compatible with DPAK (TO-252)
- Pb-Free, Halogen Free and RoHS compliance

Typical Applications

- Reverse Battery Protection
- Load Switch
- Automotive Front Lighting
- Automotive Body Controllers

SPECIFICATIONS

ABSOLUTE MAXIMUM RATING at Ta = 25°C (Note 1)

V _{DSS} V _{GSS}	-60 ±20 -80	V V A
	_	-
lD	-80	Α
		-
IDP	-320	Α
PD	84	W
Tj, Tstg	-55 to +175	ô
Eas	197	mJ
lΑV	-42	Α
P T	PD j, Tstg AS	PD 84 Tj, Tstg -55 to +175 AS 197

Note 1: Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

- $2:V_{\mbox{\footnotesize{DD}}}$ = -36 V, L = 100 $\mu\mbox{H},$ IAV = -42 A (Fig.1)
- 3 : L ≤ 100 μ H, Single pulse

THERMAL RESISTANCE RATINGS

Parameter	Symbol	Value	Unit		
Junction to Case Steady State (Tc = 25°C)	R ₀ JC	1.78	°C/W		
Junction to Ambient (Note 4)	R_{θ} JA	79.1	°C/W		

Note 4: Surface mounted on FR4 board using a 130 mm², 1 oz. Cu pad.




ON Semiconductor®

www.onsemi.com

VDSS	R _{DS} (on) Max	ID Max
-60 V	13 mΩ @ –10 V	00.4
	18 mΩ @ –4.5 V	–80 A

ELECTRICAL CONNECTION P-Channel





MARKING



ORDERING INFORMATION

See detailed ordering and shipping information on page 6 of this data sheet.

ELECTRICAL CHARACTERISTICS at Ta = 25°C (Note 5)

Daramatas	Currente e l	Conditions	Value			I Imit
Parameter	Symbol	Conditions	min	typ	max	Unit
Drain to Source Breakdown Voltage	V(BR)DSS	$I_D = -1 \text{ mA}, V_{GS} = 0 \text{ V}$	-60			V
Zero-Gate Voltage Drain Current	IDSS	$V_{DS} = -60 \text{ V}, V_{GS} = 0 \text{ V}$			-10	μΑ
Gate to Source Leakage Current	IGSS	$V_{GS} = \pm 16 \text{ V}, V_{DS} = 0 \text{ V}$			±10	μΑ
Gate Threshold Voltage	VGS(th)	$V_{DS} = -10 \text{ V}, I_{D} = -1 \text{ mA}$	-1.2		-2.6	٧
Forward Transconductance	gFS .	$V_{DS} = -10 \text{ V}, I_{D} = -35 \text{ A}$		75		S
Static Drain to Source On-State	R _{DS} (on)1	I _D = -35 A, V _{GS} = -10 V		10	13	$m\Omega$
Resistance	R _{DS} (on)2	I _D = -35 A, V _{GS} = -4.5 V		13	18	mΩ
Input Capacitance	Ciss			5,400		pF
Output Capacitance	Coss	V _{DS} = -20 V, f = 1 MHz		500		pF
Reverse Transfer Capacitance	Crss			370		pF
Turn-ON Delay Time	t _d (on)			35		ns
Rise Time	tr	Soo Fig 2		430		ns
Turn-OFF Delay Time	t _d (off)	See Fig.2		420		ns
Fall Time	tf			500		ns
Total Gate Charge	Qg			115		nC
Gate to Source Charge	Qgs	$V_{DS} = -36 \text{ V}, V_{GS} = -10 \text{ V}, I_{D} = -70 \text{ A}$		20		nC
Gate to Drain "Miller" Charge	Qgd			25		nC
Forward Diode Voltage	V _{SD}	I _S = -70 A, V _{GS} = 0 V		-1.0	-1.5	V

Note 5 :Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

Fig.1 Unclamped Inductive Switching Test Circuit







Fig.2 Switching Time Test Circuit







0.01

Pulse Time, PT - s

1.0

0.1

0.001

0.0001


0.01

PACKAGE DIMENSIONS

unit: mm

DPAK (Single Gauge) / ATPAK

CASE 369AM ISSUE O



ORDERING INFORMATION

Device	Marking	Package	Shipping (Qty / Packing)
NVATS5A302PLZT4G	ATP302	DPAK(Single Gauge) / ATPAK (Pb-Free / Halogen Free)	3,000 / Tape & Reel

[†] For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D. http://www.onsemi.com/pub_link/Collateral/BRD8011-D.PDF

Note on usage: Since the NVATS5A302PLZ is a MOSFET product, please avoid using this device in the vicinity of highly charged objects.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdt/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officer