

TPS92410EVM-002 Offline LED Driver Evaluation Module

User's Guide



Literature Number: SLVUA46

May 2014

1	Introduction	4
2	Warnings and Cautions	4
3	Description	5
	3.1 Typical Applications.....	5
	3.2 Connector Descriptions	5
4	Electrical Performance Specifications	6
5	TPS92410EVM-002 Schematic	7
6	Performance Data and Typical Characteristic Curves	8
	6.1 Power Factor.....	8
	6.2 Line Regulation	8
	6.3 Output Current.....	9
	6.4 Drain Overvoltage (DOV) Event (160-V Stack Shorted then Released)	9
	6.5 Input Voltage and Input Current	10
	6.6 Linear Regulator Drain Voltage and Input Current	10
	6.7 Triac Dimming Waveforms	11
	6.8 EMI Performance	14
7	TPS92410EVM-002 PCB Layout	15
8	Bill of Materials	16

List of Figures

1	TPS92410EVM-002 Schematic	7
2	Power Factor Versus Input Voltage	8
3	Input (Linear Regulator) Current Versus Input Voltage	8
4	160-V Stack (Top), 80-V Stack (Middle), and 40-V Stack (Bottom).....	9
5	Drain Voltage (Top), DOV Pin Voltage (Middle), and Input Current (Bottom)	9
6	Input Voltage (Top) and Input Current (Bottom)	10
7	Drain Voltage (Top) and Input Current (Bottom)	10
8	Forward Phase Triac Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Full.....	11
9	Forward Phase Triac Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Half	11
10	Forward Phase Triac Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Low	12
11	Reverse Phase Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Full	12
12	Reverse Phase Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Half.....	13
13	Reverse Phase Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Low.....	13
14	Conducted EMI Performance	14
15	Top Layer and Top Overlay (Top View)	15
16	Bottom Layer and Bottom Overlay (Bottom View)	15

List of Tables

1	TPS92410EVM-002 Electrical Performance Specifications	6
2	TPS92410EVM-002 Bill of Materials.....	16

Switch Controlled Direct Drive Linear Controller for Offline LED Drivers

1 Introduction

The TPS92410EVM-002 evaluation module (EVM) helps designers evaluate the operation and performance of the TPS92410 direct drive linear controller designed for use with the TPS92411 in offline LED-drive applications. The TPS92410 is designed to control the drive of high-brightness light emitting diodes (LEDs) and features a wide input voltage range (9.5 V to 400 V), thermal foldback, analog dimming capability, and linear FET overvoltage protection.

2 Warnings and Cautions


Observe the following precautions when using the TPS92410EVM-002.

WARNING




High Voltage

CAUTION



DO NOT STARE DIRECTLY INTO THE LED LIGHT SOURCE.
Intense light sources have a high secondary blinding effect. A temporary reduction in visual acuity and afterimages can occur, leading to irritation, annoyance, visual impairment, and even accidents – depending on the situation. Always consider the use of light filtering and darkening protective eyewear and be fully aware of surrounding laboratory type set-ups when viewing intense light sources to minimize or eliminate such risks in order to avoid accidents related to temporary blindness.

WARNING



Do not stare at the operating LED – (Risk Group 1 (RG1)). See IEC32471-1 ed1.0:2009-08 for risk group definitions.

3 Description

The TPS92410EVM-002 provides a high-brightness LED driver based on the TPS92410 in conjunction with the TPS92411 direct drive switch. It is designed to operate with an input voltage in the range of 190 VAC to 260 VAC with a 230 VAC nominal input voltage. This input voltage range is typical for offline applications. The EVM is set up for a default input current of 50 mA for 11.5 W total power and 3 LED voltage stacks of 40 V, 80 V, and 160 V. The TPS92410 helps provide high efficacy, good power factor, low THD, and flicker-free triac and phase dimming, due to its dimmer detect function that switches the input current mode to a DC level.

3.1 Typical Applications

This converter design describes an application of the TPS92410 as an LED driver controller with the specifications listed in [Section 4](#). For applications with a different input voltage range or different output voltage range, refer to the TPS92410 datasheet ([SLUSBW9](#)) and the TPS92411 datasheet ([SLUSBQ6](#)).

3.2 Connector Descriptions

This section describes the connectors and test points on the EVM and how to properly connect, setup, and use the TPS92410EVM-002.

3.2.1 J1

The screw down connector J1 is for the input voltage supply to the LED driver. The leads to the input supply should be twisted and kept as short as possible to minimize voltage drop, inductance, and EMI transmission. The input is not polarized. Line and neutral may be connected to either terminal.

3.2.2 VPx, VSx, ISx

The test points VP1, VS1, IS1, VP2, VS2, IS2, VP3, VS3, and IS3 are for testing the different LED stack voltages and currents. For example, connect a voltmeter from VP1 to IS1 across the 1- Ω resistor, R2, to measure the current in the top (160 V) LED string (1 mV = 1 mA). Connect a voltmeter from VP1 to VS1 to measure the top stack voltage. The middle and lower stack currents and voltages can be measured in the same way using the test points labeled with 2 and 3, respectively.

3.2.3 ADIM

The test point ADIM connects directly to the ADIM pin of the TPS92410. The voltage range is 0 V to 3 V. Applying a voltage between 1.5 V and 3 V allows the internal reference to take over, resulting in a 1.5-V reference at the CS pin. Applying a voltage below 1.5 V results in the applied voltage being the reference at the CS pin down to 50 mV. Below 50 mV, the linear regulator is disabled and the GDL pin is pulled to ground.

4 Electrical Performance Specifications

Table 1 contains the electrical performance specifications for the EVM.

Table 1. TPS92410EVM-002 Electrical Performance Specifications

Parameter	Test Conditions	MIN	TYP	MAX	Units
Input Characteristics					
Voltage range		190	230	260	VAC
Maximum input current			50		mA
Output Characteristics					
Output voltage, V_{OUT}	Upper LED stack		160		V
	Middle LED stack		80		
	Lower LED stack		40		
Flicker Index			0.03		
Output current ripple percent			12		%
Output current ripple	Each stack		12		mApp
Overvoltage protection level	Each individual TPS92411P		100		V
Linear FET overvoltage protection level			51		V
Systems Characteristics					
Efficiency	Input voltage = 230 VAC, No triac dimmer		80		%
Power factor	Input voltage = 230 VAC, No triac dimmer		0.97		
THD	Input voltage = 230 VAC, No triac dimmer		10.5		%

5 TPS92410EVM-002 Schematic

Figure 1 illustrates the TPS92410EVM-002 schematic.




Figure 1. TPS92410EVM-002 Schematic

6 Performance Data and Typical Characteristic Curves

Figure 2 through Figure 13 present typical performance curves for the TPS92410EVM-002.

6.1 Power Factor




Figure 2. Power Factor Versus Input Voltage

6.2 Line Regulation




Figure 3. Input (Linear Regulator) Current Versus Input Voltage

6.3 Output Current




Figure 4. 160-V Stack (Top), 80-V Stack (Middle), and 40-V Stack (Bottom)

6.4 Drain Overvoltage (DOV) Event (160-V Stack Shorted then Released)




Figure 5. Drain Voltage (Top), DOV Pin Voltage (Middle), and Input Current (Bottom)

6.5 Input Voltage and Input Current



Figure 6. Input Voltage (Top) and Input Current (Bottom)

6.6 Linear Regulator Drain Voltage and Input Current




Figure 7. Drain Voltage (Top) and Input Current (Bottom)

6.7 Triac Dimming Waveforms




Figure 8. Forward Phase Triac Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Full




Figure 9. Forward Phase Triac Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Half




Figure 10. Forward Phase Triac Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Low




Figure 11. Reverse Phase Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Full




Figure 12. Reverse Phase Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Half




Figure 13. Reverse Phase Dimming: Rectified Input Voltage (Top) and Input Current (Bottom) – Low

6.8 EMI Performance

Figure 14 shows the conducted EMI performance of the EVM under the following conditions:

- $P_{IN} = 11.5\text{ W}$
- $V_{IN} = 230\text{ VAC}$
- QP = quasi-peak limit line
- A = average limit line
- Blue trace = peak scan
- Black trace = average scan




Figure 14. Conducted EMI Performance

7 TPS92410EVM-002 PCB Layout

Figure 15 and Figure 16 show the design of the TPS92410EVM-002 printed circuit board.




Figure 15. Top Layer and Top Overlay (Top View)




Figure 16. Bottom Layer and Bottom Overlay (Bottom View)

8 Bill of Materials

Table 2 contains the TPS92410EVM-002 components list according to the schematic shown in Figure 1.

Table 2. TPS92410EVM-002 Bill of Materials

Reference Designator	QTY	Value	Description	Size	Part Number	MFR
C1	1	680pF	CAP, CERM, 680pF, 200V, +/-10%, X7R	0805	CC0805KRX7RABB681	Yageo America
C2	1	0.022μF	Cap, Film, 0.022μF, 400VDC	Radial	B32529C6223J	EPCOS Inc
C3	1	0.15μF	CAP, Film, 0.15μF, 520V, +/-10%	13x11x5mm	B32671P5154K	EPCOS Inc
C4	1	22μF	CAP, Alum, 22μF, 200V, +/-20%	10x20mm	UPW2D220MPD	Nichicon
C5	1	0.1μF	CAP, CERM, 0.1μF, 100V, +/-10%, X7R	0805	CL21B104KCFSE	Samsung
C6	1	47μF	CAP, Alum, 47μF, 100V, +/-20%, 0.43 ohm	10x12.5mm	UHE2A470MPD	Nichicon
C7, C12	2	0.1μF	CAP, CERM, 0.1μF, 16V, +/-5%, X7R	0603	C0603C104J4RACTU	Kemet
C8	1	10μF	CAP, CERM, 10μF, 25V, +/-10%, X7R	1206	GRM31CR71E106KA12L	MuRata
C9, C14	2	1μF	CAP, CERM, 1μF, 16V, +/-10%, X7R	0603	C1608X7R1C105K	TDK
C10, C13	2	4.7μF	CAP, CERM, 4.7μF, 16V, +/-10%, X5R	0603	GRM188R61C475KAAJ	MuRata
C11	1	1000pF	CAP, CERM, 1000pF, 50V, +/-10%, X7R	0603	GRM188R71H102KA01D	MuRata
C15	1	100μF	CAP, Alum, 100μF, 50V, +/-20%	8.0x10.5 mm	UHE1H101MPD	Nichicon
D1, D22, D30	3	200V	Diode, Switching, 200V, 0.2A	SOT-23	BAS21-7-F	Diodes Inc.
D2, D3, D4, D5, D7, D8, D9, D10, D11, D12, D14, D15, D16, D17, D18, D19, D20, D21, D23, D24, D25, D26, D27, D28, D29, D31, D32, D34	28	Cool White	LED, Cool White, SMD	3x.75x5.2 mm	SAW8KG0B-Y1Z4-CA	Seoul Semiconductor
D6	1		Diode, Switching-Bridge, 600V, 0.8A	MiniDIP	HD06-T	Diodes Inc.
D13	1	12V	Diode, Zener, 12V, 300mW	SOT-23	AZ23C12-7-F	Diodes Inc.
D33	1	100V	Diode, Ultrafast, 100V, 0.15A	SOD-123	1N4148W-7-F	Diodes Inc.
J1	1	2x1	Conn Term Block, 2POS, 5.08mm	2POS Terminal Block	1715721	Phoenix Contact
Q1	1	200V	MOSFET, N-CH, 200V, 0.6A	TSOP-6	IRF5801TRPBF	International Rectifier
Q2	1	600V	MOSFET, N-CH, 600V, 2A	DPAK	AOD2N60	AOS
Q3	1	0.25V	Transistor, NPN, 140V, 0.6A	SOT-23	MMBT5550LT1G	ON Semiconductor
R1	1	1.00k	RES, 1.00k ohm, 1%, 0.125W	0805	CRCW08051K00FKEA	Vishay-Dale
R2, R9, R18	3	1.00	RES, 1.00 ohm, 1%, 0.125W	0805	RMCF0805FT1R00	Stackpole Electronics Inc
R3, R4	2	820	RES, 820 ohm, 5%, 1W	2512	CRCW2512820RJNEG	Vishay Dale
R5	1	1.00Meg	RES, 1.00Meg ohm, 1%, 0.25W	1206	CRCW12061M00FKEA	Vishay-Dale
R6	1	10.0k	RES, 10.0k ohm, 1%, 0.125W	0805	CRCW080510K0FKEA	Vishay-Dale
R7	1	2.80Meg	RES, 2.80Meg ohm, 1%, 0.25W	1206	CRCW12062M80FKEA	Vishay-Dale
R8, R12, R27	3	1.50Meg	RES, 1.50Meg ohm, 1%, 0.25W	1206	RC1206FR-071M5L	Yageo America
R10	1	2.67Meg	RES, 2.67Meg ohm, 1%, 0.125W	0805	CRCW08052M67FKEA	Vishay-Dale
R11, R13	2	2.00Meg	RES, 2.00Meg ohm, 1%, 0.25W	1206	CRCW12062M00FKEA	Vishay-Dale

Table 2. TPS92410EVM-002 Bill of Materials (continued)

Reference Designator	QTY	Value	Description	Size	Part Number	MFR
R14, R15	2	2.00Meg	RES, 2.00Meg ohm, 1%, 0.125W	0805	CRCW08052M00FKEA	Vishay-Dale
R16, R21	2	30.1k	RES, 30.1k ohm, 1%, 0.1W	0603	CRCW060330K1FKEA	Vishay-Dale
R17	1	200k	RES, 200k ohm, 1%, 0.1W	0603	CRCW0603200KFKEA	Vishay-Dale
R19	1	54.9k	RES, 54.9k ohm, 1%, 0.1W	0603	CRCW060354K9FKEA	Vishay-Dale
R20	1	100	RES, 100 ohm, 1%, 0.1W	0603	CRCW0603100RFKEA	Vishay-Dale
R23	1	121k	RES, 121k ohm, 1%, 0.1W	0603	CRCW0603121KFKEA	Vishay-Dale
R24	1	2.37Meg	RES, 2.37Meg ohm, 1%, 0.125W	0805	CRCW08052M37FKEA	Vishay-Dale
R25	1	30.1	RES, 30.1 ohm, 1%, 0.25W	1206	CRCW120630R1FKEA	Vishay-Dale
RF1	1	68	RES, 68 ohm, 10%, 2W, Fusible	Axial resistor	EMC2-68RKI	TT Electronics/IRC
RT1	1	470k	Thermistor NTC, 470k ohm, 5%	0603	NCP18WM474J03RB	MuRata
RV1	1	430V	Metal Oxide Varistor	9.00 mm Diameter	MOV-07D431K	Bourns
U1, U2, U4	3		Switch Controlled Direct Drive Switch for Offline LED Drivers	SOT23-5	TPS92411PDBV	Texas Instruments
U3	1		Switch Controlled Direct Drive Linear Controller for Offline LED Drivers	SOIC-13	TPS92410D	Texas Instruments
R22	0		DNP			
R26	0		DNP			
R28	0		DNP			

ADDITIONAL TERMS AND CONDITIONS, WARNINGS, RESTRICTIONS, AND DISCLAIMERS FOR EVALUATION MODULES

Texas Instruments Incorporated (TI) markets, sells, and loans all evaluation boards, kits, and/or modules (EVMs) pursuant to, and user expressly acknowledges, represents, and agrees, and takes sole responsibility and risk with respect to, the following:

1. User agrees and acknowledges that EVMs are intended to be handled and used for feasibility evaluation only in laboratory and/or development environments. Notwithstanding the foregoing, in certain instances, TI makes certain EVMs available to users that do not handle and use EVMs solely for feasibility evaluation only in laboratory and/or development environments, but may use EVMs in a hobbyist environment. All EVMs made available to hobbyist users are FCC certified, as applicable. Hobbyist users acknowledge, agree, and shall comply with all applicable terms, conditions, warnings, and restrictions in this document and are subject to the disclaimer and indemnity provisions included in this document.
2. Unless otherwise indicated, EVMs are not finished products and not intended for consumer use. EVMs are intended solely for use by technically qualified electronics experts who are familiar with the dangers and application risks associated with handling electrical mechanical components, systems, and subsystems.
3. User agrees that EVMs shall not be used as, or incorporated into, all or any part of a finished product.
4. User agrees and acknowledges that certain EVMs may not be designed or manufactured by TI.
5. User must read the user's guide and all other documentation accompanying EVMs, including without limitation any warning or restriction notices, prior to handling and/or using EVMs. Such notices contain important safety information related to, for example, temperatures and voltages. For additional information on TI's environmental and/or safety programs, please visit www.ti.com/esh or contact TI.
6. User assumes all responsibility, obligation, and any corresponding liability for proper and safe handling and use of EVMs.
7. Should any EVM not meet the specifications indicated in the user's guide or other documentation accompanying such EVM, the EVM may be returned to TI within 30 days from the date of delivery for a full refund. THE FOREGOING LIMITED WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY TI TO USER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. TI SHALL NOT BE LIABLE TO USER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES RELATED TO THE HANDLING OR USE OF ANY EVM.
8. No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which EVMs might be or are used. TI currently deals with a variety of customers, and therefore TI's arrangement with the user is not exclusive. TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services with respect to the handling or use of EVMs.
9. User assumes sole responsibility to determine whether EVMs may be subject to any applicable federal, state, or local laws and regulatory requirements (including but not limited to U.S. Food and Drug Administration regulations, if applicable) related to its handling and use of EVMs and, if applicable, compliance in all respects with such laws and regulations.
10. User has sole responsibility to ensure the safety of any activities to be conducted by it and its employees, affiliates, contractors or designees, with respect to handling and using EVMs. Further, user is responsible to ensure that any interfaces (electronic and/or mechanical) between EVMs and any human body are designed with suitable isolation and means to safely limit accessible leakage currents to minimize the risk of electrical shock hazard.
11. User shall employ reasonable safeguards to ensure that user's use of EVMs will not result in any property damage, injury or death, even if EVMs should fail to perform as described or expected.
12. User shall be solely responsible for proper disposal and recycling of EVMs consistent with all applicable federal, state, and local requirements.

Certain Instructions. User shall operate EVMs within TI's recommended specifications and environmental considerations per the user's guide, accompanying documentation, and any other applicable requirements. Exceeding the specified ratings (including but not limited to input and output voltage, current, power, and environmental ranges) for EVMs may cause property damage, personal injury or death. If there are questions concerning these ratings, user should contact a TI field representative prior to connecting interface electronics including input power and intended loads. Any loads applied outside of the specified output range may result in unintended and/or inaccurate operation and/or possible permanent damage to the EVM and/or interface electronics. Please consult the applicable EVM user's guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative. During normal operation, some circuit components may have case temperatures greater than 60°C as long as the input and output are maintained at a normal ambient operating temperature. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors which can be identified using EVMs' schematics located in the applicable EVM user's guide. When placing measurement probes near EVMs during normal operation, please be aware that EVMs may become very warm. As with all electronic evaluation tools, only qualified personnel knowledgeable in electronic measurement and diagnostics normally found in development environments should use EVMs.

Agreement to Defend, Indemnify and Hold Harmless. User agrees to defend, indemnify, and hold TI, its directors, officers, employees, agents, representatives, affiliates, licensors and their representatives harmless from and against any and all claims, damages, losses, expenses, costs and liabilities (collectively, "Claims") arising out of, or in connection with, any handling and/or use of EVMs. User's indemnity shall apply whether Claims arise under law of tort or contract or any other legal theory, and even if EVMs fail to perform as described or expected.

Safety-Critical or Life-Critical Applications. If user intends to use EVMs in evaluations of safety critical applications (such as life support), and a failure of a TI product considered for purchase by user for use in user's product would reasonably be expected to cause severe personal injury or death such as devices which are classified as FDA Class III or similar classification, then user must specifically notify TI of such intent and enter into a separate Assurance and Indemnity Agreement.

RADIO FREQUENCY REGULATORY COMPLIANCE INFORMATION FOR EVALUATION MODULES

Texas Instruments Incorporated (TI) evaluation boards, kits, and/or modules (EVMs) and/or accompanying hardware that is marketed, sold, or loaned to users may or may not be subject to radio frequency regulations in specific countries.

General Statement for EVMs Not Including a Radio

For EVMs not including a radio and not subject to the U.S. Federal Communications Commission (FCC) or Industry Canada (IC) regulations, TI intends EVMs to be used only for engineering development, demonstration, or evaluation purposes. EVMs are not finished products typically fit for general consumer use. EVMs may nonetheless generate, use, or radiate radio frequency energy, but have not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC or the ICES-003 rules. Operation of such EVMs may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

General Statement for EVMs including a radio

User Power/Frequency Use Obligations: For EVMs including a radio, the radio included in such EVMs is intended for development and/or professional use only in legally allocated frequency and power limits. Any use of radio frequencies and/or power availability in such EVMs and their development application(s) must comply with local laws governing radio spectrum allocation and power limits for such EVMs. It is the user's sole responsibility to only operate this radio in legally acceptable frequency space and within legally mandated power limitations. Any exceptions to this are strictly prohibited and unauthorized by TI unless user has obtained appropriate experimental and/or development licenses from local regulatory authorities, which is the sole responsibility of the user, including its acceptable authorization.

U.S. Federal Communications Commission Compliance

For EVMs Annotated as FCC – FEDERAL COMMUNICATIONS COMMISSION Part 15 Compliant

Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications could void the user's authority to operate the equipment.

FCC Interference Statement for Class A EVM devices

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at its own expense.

FCC Interference Statement for Class B EVM devices

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Industry Canada Compliance (English)

For EVMs Annotated as IC – INDUSTRY CANADA Compliant:

This Class A or B digital apparatus complies with Canadian ICES-003.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Concerning EVMs Including Radio Transmitters

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Concerning EVMs Including Detachable Antennas

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

This radio transmitter has been approved by Industry Canada to operate with the antenna types listed in the user guide with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

Canada Industry Canada Compliance (French)

Cet appareil numérique de la classe A ou B est conforme à la norme NMB-003 du Canada

Les changements ou les modifications pas expressément approuvés par la partie responsable de la conformité ont pu vider l'autorité de l'utilisateur pour actionner l'équipement.

Concernant les EVMs avec appareils radio

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Concernant les EVMs avec antennes détachables

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

Le présent émetteur radio a été approuvé par Industrie Canada pour fonctionner avec les types d'antenne énumérés dans le manuel d'usage et ayant un gain admissible maximal et l'impédance requise pour chaque type d'antenne. Les types d'antenne non inclus dans cette liste, ou dont le gain est supérieur au gain maximal indiqué, sont strictement interdits pour l'exploitation de l'émetteur.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2014, Texas Instruments Incorporated

Important Notice for Users of EVMs Considered “Radio Frequency Products” in Japan

EVMs entering Japan are NOT certified by TI as conforming to Technical Regulations of Radio Law of Japan.

If user uses EVMs in Japan, user is required by Radio Law of Japan to follow the instructions below with respect to EVMs:

1. Use EVMs in a shielded room or any other test facility as defined in the notification #173 issued by Ministry of Internal Affairs and Communications on March 28, 2006, based on Sub-section 1.1 of Article 6 of the Ministry's Rule for Enforcement of Radio Law of Japan,
2. Use EVMs only after user obtains the license of Test Radio Station as provided in Radio Law of Japan with respect to EVMs, or
3. Use of EVMs only after user obtains the Technical Regulations Conformity Certification as provided in Radio Law of Japan with respect to EVMs. Also, do not transfer EVMs, unless user gives the same notice above to the transferee. Please note that if user does not follow the instructions above, user will be subject to penalties of Radio Law of Japan.

<http://www.tij.co.jp>

【無線電波を送信する製品の開発キットをお使いになる際の注意事項】本開発キットは技術基準適合証明を受けておりません。本製品のご使用に際しては、電波法遵守のため、以下のいずれかの措置を取っていただく必要がありますのでご注意ください。

1. 電波法施行規則第6条第1項第1号に基づく平成18年3月28日総務省告示第173号で定められた電波暗室等の試験設備でご使用いただく。
2. 実験局の免許を取得後ご使用いただく。
3. 技術基準適合証明を取得後ご使用いただく。。

なお、本製品は、上記の「ご使用にあたっての注意」を譲渡先、移転先に通知しない限り、譲渡、移転できないものとします

上記を遵守頂けない場合は、電波法の罰則が適用される可能性があることをご留意ください。

日本テキサス・インスツルメンツ株式会社

東京都新宿区西新宿6丁目24番1号

西新宿三井ビル

<http://www.tij.co.jp>

Texas Instruments Japan Limited

(address) 24-1, Nishi-Shinjuku 6 chome, Shinjuku-ku, Tokyo, Japan

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com