



EVQ7200A-L-00A

42V, 3A, 410kHz, Synchronous LED Driver Buck Mode Evaluation Board, AEC-Q100 Qualified

DESCRIPTION

The EVQ7200A-L-00A is an evaluation board designed to demonstrate the capabilities of the MPQ7200A, a constant-current LED driver with integrated power MOSFETs. It offers a compact solution to achieve 3A of continuous output current (I_{OUT}), with excellent load and line regulation across a wide input supply range.

Constant frequency hysteretic control mode provides fast transient response without loop compensation. The switching frequency (f_{sw}) is

410kHz in buck mode for optimized efficiency and electromagnetic interference (EMI) performance.

The MPQ7200A is available in a QFN-19 (3mmx4mm) package with wettable flanks, and is available in AEC-Q100 Grade 1.


The EVQ7200A-L-00A is a fully assembled and tested buck mode LED driver evaluation board. It generates an LED current up to 3A from a 6V to 42V input range.

PERFORMANCE SUMMARY

Specifications are at $T_A = 25^\circ\text{C}$, unless otherwise noted.

Parameters	Conditions	Value
Input voltage (V_{IN}) range		6V to 42V
Maximum output current (I_{OUT})	$V_{IN} = 6\text{V to }42\text{V}$	3A
Typical efficiency	$V_{IN} = 13.5\text{V}$, 2 LEDs, $I_{LED} = 3\text{A}$	93.32%
Peak efficiency	$V_{IN} = 8\text{V}$, 2 LEDs, $I_{LED} = 0.75\text{A}$	96.22%
Switching frequency (f_{sw})		410kHz

EVALUATION BOARD



LxWxH (8.3cmx8.3cmx1.3cm)

Board Number	MPS IC Number
EVQ7200A-L-00A	MPQ7200AGLE-AEC1

QUICK START GUIDE

1. Preset the power supply between 6V and 42V, then turn off the power supply (see Figure 1).




Figure 1: Measurement Equipment Set-Up

2. If longer cables (>0.5m total) are being used between the source and the evaluation board, install a damping capacitor at the input terminals. This is especially critical when V_{EMI} exceeds 24V.
3. Connect the power supply terminals to:
 - a. Positive (+): VEMI
 - b. Negative (-): GND
4. Connect the load terminals to:
 - a. Positive (+): VLED+
 - b. Negative (-): VLED-
5. After making the connections, turn on the power supply.
6. To use the enable (EN) function, apply a digital input to the EN/DIM pin. Drive EN above 2.5V to turn the regulator on; drive EN below 1V to turn it off.
7. When two-step dimming is inactive ($R_{DUTY} = 4.87k\Omega$), an external 100Hz to 2kHz pulse-width modulation (PWM) waveform can be applied to the EN/DIM pin.
8. To initiate the two-step dimming function, use the EN/DIM pin. Table 1 on page 3 shows the proposed resistor (R3) in E96 series for different dimming duty cycles. When EN/DIM is high, the dimming duty cycle is 100%; when EN/DIM is low, the dimming duty cycle percentage varies.

QUICK START GUIDE *(continued)*
Table 1: Two-Step Dimming Duty vs. R3

Two-Step Dimming Duty	R3 (Ω)
15%	61900
14%	41200
13%	27400
12%	18200
11%	12100
10%	7870
Two-step dimming off	4870
9%	3090
8%	2050
7%	1370
6%	887
5%	576

9. The external resistor (R5) connected to the ISET pin sets the LED current (I_{LED}). R5 can be calculated using Equation (1):

$$R5 = \frac{16}{I_{LED} (A)} (k\Omega) \quad (1)$$

EVALUATION BOARD SCHEMATIC




Figure 2: Evaluation Board Schematic

EVQ7200A-L-00A BILL OF MATERIALS


Qty	Ref	Value	Description	Package	Manufacturer	Manufacturer PN
1	L1	4.7μH	Inductor, 44.1mΩ DCR, 4.6A	SMD	Coilcraft	XEL4030-472MEB
1	L2	10μH	Inductor, 40.9mΩ DCR, 4.9A	SMD	Coilcraft	XEL5050-103MEB
4	C1A, C1B, CIN5, CIN6	10μF	Ceramic capacitor, 50V, X7R	1210	Murata	GRM32ER71H106KA8
2	C1C, C1D	0.1μF	Ceramic capacitor, 50V, X7R	0603	Murata	GRM188R71H104KA93D
2	C2A, C2B	2.2μF	Ceramic capacitor, 25V, X7R	1206	Murata	GRM31MR71E225KA93L
2	C2C, C2D	1nF	Ceramic capacitor, 50V, C0G	0603	Murata	GRM1885C1H02JAC
1	C1	10μF	Ceramic capacitor, 16V, X5R	0603	Murata	GRM188R61C106KAA
1	C2	0.1μF	Ceramic capacitor, 16V, X7R	0603	Murata	GRM188R71C104KA01D
1	CIN7	47μF	Electrolytic capacitor, 63V	SMD	Panasonic	EEHZC1J470P
4	CIN1, CIN2, CIN3, CIN4	22nF	Ceramic capacitor, 50V, X7R	0603	TDK	C1608X7R1H223K
10	R1, R2	100kΩ	Film resistor, 5%	0603	Yageo	RC0603JR-07100KL
11	R3	4.87kΩ	Film resistor, 1%	0603	Yageo	RC0603FR-074K87L
12	R4	10kΩ	Film resistor, 1%	0603	Yageo	RC0603FR-0710KL
13	R5	5.36kΩ	Film resistor, 1%	0603	Yageo	RC0603FR-075K36L
14	R6	23.2kΩ	Film resistor, 1%	0603	Yageo	RC0603FR-0723K2L
15	R7	20Ω	Film resistor, 1%	0603	Yageo	RC0603FR-0720RL
5	VEMI, GND, VLED+, VLED-	2mm	Golden pin	DIP	Custom	
4	EN, DIM, GND, FAULT	1mm	Golden pin	DIP	Custom	
1	U1	MPQ7200A	Buck-boost regulator, AEC-Q100	QFN-19 (3mmx4mm)	MPS	MPQ7200AGLE-AEC1

EVB TEST RESULTS

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{SW} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


CISPR25 Class 5 Peak Conducted Emissions

150kHz to 108MHz




CISPR25 Class 5 Average Conducted Emissions

150kHz to 108MHz




CISPR25 Class 5 Peak Radiated Emissions

150kHz to 30MHz




CISPR25 Class 5 Average Radiated Emissions

150kHz to 30MHz




CISPR25 Class 5 Peak Radiated Emissions

Horizontal, 30MHz to 200MHz



CISPR25 Class 5 Average Radiated Emissions

Horizontal, 30MHz to 200MHz




EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{SW} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


CISPR25 Class 5 Peak Radiated Emissions

Vertical, 30MHz to 200MHz




CISPR25 Class 5 Average Radiated Emissions

Vertical, 30MHz to 200MHz




CISPR25 Class 5 Peak Radiated Emissions

Horizontal, 200MHz to 1GHz




CISPR25 Class 5 Average Radiated Emissions

Horizontal, 200MHz to 1GHz




CISPR25 Class 5 Peak Radiated Emissions

Vertical, 200MHz to 1GHz









CISPR25 Class 5 Average Radiated Emissions

Vertical, 200MHz to 1GHz



EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{SW} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted. ⁽¹⁾





Note:

1) The inductor details regarding the efficiency curves follow: $L = 15\mu H$ (XAL5050-153MEB), $L = 22\mu H$ (XAL5050-223MEB).

EVB TEST RESULTS *(continued)*

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{SW} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.




EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, $I_{LED} = 3A$, 2 LEDs in series ($V_{LED} = 6V$), $f_{sw} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


Steady State

$I_{LED} = 3A$




Start-Up through VIN

$I_{LED} = 3A$




Shutdown through VIN

$I_{LED} = 3A$




Start-Up through EN

$I_{LED} = 3A$




Shutdown through EN

$I_{LED} = 3A$



PWM Dimming Steady State

Dimming frequency = 100Hz




EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{sw} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


PWM Dimming Steady State

Dimming frequency = 2kHz




PWM Dimming

Start-up through V_{IN}




PWM Dimming

Shutdown through V_{IN}




Two-Step Dimming

Steady state




Two-Step Dimming

Start-up through V_{IN}



Two-Step Dimming

Shutdown through V_{IN}




EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{SW} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


No Dimming

LED open start-up




No Dimming

LED open entry




PWM Dimming

LED open start-up




PWM Dimming

LED open entry




Two-Step Dimming

LED open start-up



Two-Step Dimming

LED open start-up




EVB TEST RESULTS *(continued)*

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{sw} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


No Dimming

LED+ short to LED- start-up




No Dimming

LED+ short to LED- entry




PWM Dimming

LED+ short to LED- start-up




PWM Dimming

LED+ short to LED- entry




Two-Step Dimming

LED+ short to LED- start-up



Two-Step Dimming


LED+ short to LED- entry




EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{SW} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


I_{REF} Short before Start-Up




I_{REF} Open before Start-Up




I_{REF} Short after Start-Up




I_{REF} Open after Start-Up



**I_{REF} Short after Start-Up
PWM dimming**




**I_{REF} Open after Start-Up
PWM dimming**




EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{sw} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


I_{SET} Short before Start-Up




I_{SET} Open before Start-Up




I_{SET} Short after Start-Up




I_{SET} Open after Start-Up



I_{SET} Short after Start-Up PWM dimming




I_{SET} Open after Start-Up PWM dimming




EVB TEST RESULTS (continued)

Performance curves and waveforms are tested on the evaluation board, $V_{IN} = 13.5V$, 2 LEDs in series ($V_{LED} = 6V$), $f_{SW} = 410kHz$, $L = 10\mu H$, $T_A = 25^\circ C$, unless otherwise noted.


I_{DUTY} Short before Start-Up




I_{DUTY} Open before Start-Up




FAULT Short during VIN Start Up



FAULT Short after VIN Start-Up



False Mode Detection during VIN Start-Up



PCB LAYOUT




Figure 3: Top Silk and Top Layer




Figure 4: Mid-Layer 1




Figure 5: Mid-Layer 2




Figure 6: Bottom Layer and Bottom Silk

REVISION HISTORY

Revision #	Revision Date	Description	Pages Updated
1.0	2/7/2022	Initial Release	-

Notice: The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third-party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.