




---

## SparkFun Arduimoto - Motor Driver Shield

DEV-09815 ROHS ✓ 

★★★★☆ 4



© images are CC BY-NC-SA 3.0

**Description:** This is a motor shield for Arduino that will control two DC motors. Based on the L298 H-bridge, the SparkFun Arduimoto can drive up to 2 amps per channel. The board takes its power from the same Vin line as the Arduino board, includes blue and yellow LEDs to indicate active direction, and all driver lines are diode protected from back EMF. The new version of this shield allows for either 3.3 or 5v logic, a separate and more robust VIN connection, and the PWM input has moved to pin 3.

Control for motor attached to OUT1/2 is connected to digital line 12 (direction A) and digital line 3 (PWM A). Control for motor attached to OUT3/4 is connected to digital line 13 (direction B) and digital line 11 (PWM B).

Compatible screw terminals and connectors are listed below. They are not included in this SKU. You will need to add them to your cart separately.

**Note:** The VIN connection is tied directly to the VIN on the Arduino, so make sure to not apply power to both