

# NTC Type JI

Thermometrics Double Insulated Chip Thermistor with Insulated Wires



### Features

- Waterproof to IP68
- Withstands freeze/thaw cycling
- Available using any device in the Thermometrics standard NK and DC95 ranges
- Range of wire lengths 11.81 in to 196.85 in (300 mm to 5000 mm) (dimension WL on page 2)
- Suitable for refrigeration applications, including evaporators

## Amphenol Advanced Sensors

# Type JI Specifications

#### Description


Chip thermistor housed in a tip, which is molded onto flexible circular cable. Tip and outer cable insulation material is thermoplastic elastomer. Tinned copper conductors have individual polyolefin insulation.

### Options

- Other resistance temperature characteristics
- Other wire lengths

#### Data

- Temperature range: -40°F to 221°F (-40°C to 105°C)
- Insulation resistance: >100 M $\Omega$  at 500 VDC
- Wire conductors: 7 X 0.23 mm diameter (0.30 mm<sup>2</sup>)
- Resistance temperature characteristics: Refer to NK and DC95 data sheets



NTC Type JI dimensions

#### **Ordering Information**

Code	Туре		
JI	Double Insulated With Insulated Wires		
1	Code	Туре	
	103C1R2	NK103C1R2	See NK or DC95 Data sheets
	F103W	DC95F103V	V
		Code	Wire Length WL in mm
		L301	300 ± 10
		L501	500 ± 10
		L751	750 ± 20
		L102	1000 ± 20
		L152	1500 ± 25
		L202	2000 ± 25
		L252	2500 ± 50
		L302	3000 ± 50
		L352	3500 ± 50
		L402	4000 ± 50
		L452	4500 ± 50
		L502	5000 ± 50
V	V	▼	
JI -			Typical model number

Resistance characteristic and wire length are specified by the product code: e.g. JI103C1R2 or JIF103W

Other wire lengths are available for quantities > 5000 pieces as above with a wire tolerance at > 3.28 ft (1 m) of +100 /- 0 mm (+3.9 in /- 0 in)

## **Amphenol** Advanced Sensors

#### www.amphenol-sensors.com

© 2014 Amphenol Corporation. All Rights Reserved. Specifications are subject to change without notice. Other company names and product names used in this document are the registered trademarks or trademarks of their respective owners.