


MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918
Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com

Analog MUX 4 Click



PID: MIKROE-4795

Analog MUX 4 Click is a compact add-on board that switches one of many analog inputs to one digital output. This board features the $\underline{\mathsf{TMUX1308}}$, a general-purpose 8:1 single-ended CMOS multiplexer (MUX) from $\underline{\mathsf{Texas}}$ Instruments. The TMUX1308 has an internal injection current control which eliminates the need for external diode and resistor networks to protect the switch and keep the input signals within the supply voltage. It also supports bidirectional analog and digital signals ranging from 0 to 5V, alongside several protection features allowing a reliable operation and protecting the device from potential damage. This Click board is suitable for various applications, from industrial to instrumentation, consumer, communications, and more.

Analog MUX 4 Click is supported by a $\frac{\text{mikroSDK}}{\text{compliant library}}$, which includes functions that simplify software development. This $\frac{\text{Click board}}{\text{comes}}$ comes as a fully tested product, ready to be used on a system equipped with the $\frac{\text{mikroBUS}}{\text{mikroBUS}}$ socket.

Mikroe produces entire development toolchains for all major microcontroller architectures.

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.





health and safety management system.



MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918
Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com

Specifications

Туре	Measurements,Port expander
Applications	Can be used for various applications, from industrial to instrumentation, consumer, communications, and more
On-board modules	TMUX1308 - general-purpose 8:1 single-ended CMOS analog multiplexer from Texas Instruments
Key Features	Injection current control, back-powering protection, bidirectional signal path, Break-Before-Make switching, VCC range signal handling, TTL/CMOS-logic compatible, pincontrollable, and more
Interface	Analog,GPIO
ClickID	No
Compatibility	mikroBUS
Click board size	L (57.15 x 25.4 mm)
Input Voltage	3.3V or 5V

www.mikroe.com

Resources

<u>mikroBUS™</u>

mikroSDK

Click board™ Catalog

Click boards™

Downloads

Analog MUX 4 click example on Libstock

TMUX1308 datasheet

Analog MUX 4 click schematic

Analog MUX 4 click 2D and 3D files

Mikroe produces entire development toolchains for all major microcontroller architectures.

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.





health and safety management system.