Technical Data Sheet



DPDT Ramses Low PIM SMA 18GHz Failsafe Indicators 28Vdc TTL

Diodes Pins Terminals with bracket

PAGE 1/2 ISSUE 11-04-17 SERIE : DPDT PART NUMBER : R577423100LP

RF CHARACTERISTICS

Frequency range : 0 - 18 GHz Impedance : 50 Ohms

Frequency (GHz)	DC - 3	3 - 8	8 - 12.4	12.4 - 18
VSWR max	1.20	1.30	1.40	1.50
Insertion loss max	0.20 dB	0.30 dB	0.40 dB	0.50 dB
Isolation min	80 dB	70 dB	65 dB	60 dB
Average power (*)	240 W	150 W	120 W	100 W

	Passive intermodulation		
Tone 1	1810 MHz, approximately 43 dBm		
Tone 2	1850 MHz, approximately 43 dBm		
3 rd order PIM	- 160 dBc at 1770 MHz		

Depending on application, carrier powers and frequencies, PIM measurements can vary. PIM testing is not measured during product acceptance test.

ELECTRICAL CHARACTERISTICS

Actuator : FAILSAFE
Nominal current ** : 140 mA

Actuator voltage (Vcc) : 28V (24 to 30V)

Terminals : solder pins (250°C max. / 30 sec.)

Indicator rating : 1 W / 30 V / 100 mA

TTL inputs (E) - High level : 2.2 to 5.5 V / $800\mu A$ at 5.5 V

- Low level : 0 to 0.8 V / 20μA at 0.8 V

MECHANICAL CHARACTERISTICS

Connectors***** : SMA female per MIL-C 39012

Life : 2 million cycles
Switching Time*** : < 15 ms

Construction : Splashproof Weight : < 100 g

ENVIRONMENTAL CHARACTERISTICS

Operating temperature range : -25°C to +70°C
Storage temperature range : -55°C to +85°C

(* Average power at 25°C per RF Path)

(** At 25° C ±10%)

(*** Nominal voltage; 25° C)

(***** Recommended mating torque: 80-120 N.cm)









DPDT Ramses Low PIM SMA 18GHz Failsafe Indicators 28Vdc TTL

Diodes Pins Terminals with bracket

PAGE 2/2 ISSUE 11-04-17 SERIE : DPDT PART NUMBER : R577423100LP


0.909] 23.10 [0.638] [0.638] 4 x M3 depth 3.50 0.700 0.905





General tolerances: ±0,5 mm [0,02 in]

SCHEMATIC DIAGRAM





LABEL

E 6N v.c. f & c RADIALL® R577423100LP 0 - 18 GHz Un : 28V Lot : ____

TTL input	RF Continuity	Ind.
E = 1	$1 \leftrightarrow 3 / 2 \leftrightarrow 4$	C.1
E = 0	$1 \leftrightarrow 2 \ / \ 3 \leftrightarrow 4$	C.2