Features

- High Performance, Low Power AVR® 8-Bit Microcontroller
- **Advanced RISC Architecture**
 - 130 Powerful Instructions Most Single Clock Cycle Execution
 - 32 x 8 General Purpose Working Registers
 - Fully Static Operation
 - Up to 20 MIPS Throughput at 20 MHz
 - On-Chip 2-cycle Multiplier
- High Endurance Non-volatile Memory segments
 - 32K Bytes of In-System Self-programmable Flash program memory
 1K Bytes EEPROM

 - 2K Bytes Internal SRAM
 - Write/Erase cyles: 10,000 Flash/100,000 EEPROM
 - Data retention: 20 years at 85°C/100 years at 25°C⁽¹⁾
 - Optional Boot Code Section with Independent Lock Bits In-System Programming by On-chip Boot Program True Read-While-Write Operation
 - Programming Lock for Software Security
- JTAG (IEEE std. 1149.1 compliant) Interface
 - Boundary-scan Capabilities According to the JTAG Standard
 - Extensive On-chip Debug Support
 - Programming of Flash, EEPROM, Fuses, and Lock Bits through the JTAG Interface
- Peripheral Features
 - Two 8-bit Timer/Counters with Separate Prescaler and Compare Mode
 - One 16-bit Timer/Counter with Separate Prescaler, Compare Mode, and Capture
 - Real Time Counter with Separate Oscillator
 - Four PWM Channels
 - 8-channel, 10-bit ADC
 - Programmable Serial USART
 - Master/Slave SPI Serial Interface
 - Universal Serial Interface with Start Condition Detector
 - Programmable Watchdog Timer with Separate On-chip Oscillator
 - On-chip Analog Comparator
 - Interrupt and Wake-up on Pin Change
- Special Microcontroller Features
 - Power-on Reset and Programmable Brown-out Detection
 - Internal Calibrated Oscillator
 - External and Internal Interrupt Sources
 - Five Sleep Modes: Idle, ADC Noise Reduction, Power-save, Power-down, and Standby
- I/O and Packages
 - 54/69 Programmable I/O Lines
 - 64-lead TQFP, 64-pad QFN/MLF, and 100-lead TQFP
- Speed Grade:
 - ATmega325PV/ATmega3250PV:
 - 0 4 MHz @ 1.8 5.5V, 0 10 MHz @ 2.7 5.5V
 - ATmega325P/3250P:
 - 0 10 MHz @ 2.7 5.5V, 0 20 MHz @ 4.5 5.5V
- Temperature range:
 - -40°C to 85°C Industrial
- Ultra-Low Power Consumption
 - Active Mode:
 - 420 µA at 1 MHz, 1.8V
 - Power-down Mode:
 - 40 nA at 1.8V
 - Power-save Mode:
 - 750 nA at 1.8V



8-bit A Microcontroller with 32K Bytes In-System **Programmable Flash**

ATmega325P/V ATmega3250P/V

Preliminary





1. Pin Configurations

Figure 1-1. Pinout ATmega3250P

TQFP





Figure 1-2. Pinout ATmega325P



Note: The large center pad underneath the QFN/MLF packages is made of metal and internally connected to GND. It should be soldered or glued to the board to ensure good mechanical stability. If the center pad is left unconnected, the package might loosen from the board.

1.1 Disclaimer

Typical values contained in this datasheet are based on simulations and characterization of other AVR microcontrollers manufactured on the same process technology. Min and Max values will be available after the device is characterized.

2. Overview


The ATmega325P/3250P is a low-power CMOS 8-bit microcontroller based on the AVR enhanced RISC architecture. By executing powerful instructions in a single clock cycle, the ATmega325P/3250P achieves throughputs approaching 1 MIPS per MHz allowing the system designer to optimize power consumption versus processing speed.





2.1 Block Diagram

Figure 2-1. Block Diagram



The AVR core combines a rich instruction set with 32 general purpose working registers. All the 32 registers are directly connected to the Arithmetic Logic Unit (ALU), allowing two independent registers to be accessed in one single instruction executed in one clock cycle. The resulting architecture is more code efficient while achieving throughputs up to ten times faster than conventional CISC microcontrollers.

The ATmega325P/3250P provides the following features: 32K bytes of In-System Programmable Flash with Read-While-Write capabilities, 1K bytes EEPROM, 2K byte SRAM, 54/69 general purpose I/O lines, 32 general purpose working registers, a JTAG interface for Boundary-scan, On-chip Debugging support and programming, three flexible Timer/Counters with compare modes, internal and external interrupts, a serial programmable USART, Universal Serial Interface with Start Condition Detector, an 8-channel, 10-bit ADC, a programmable Watchdog Timer with internal Oscillator, an SPI serial port, and five software selectable power saving modes. The Idle mode stops the CPU while allowing the SRAM, Timer/Counters, SPI port, and interrupt system to continue functioning. The Power-down mode saves the register contents but freezes the Oscillator, disabling all other chip functions until the next interrupt or hardware reset. In Power-save mode, the asynchronous timer, allowing the user to maintain a timer base while the rest of the device is sleeping. The ADC Noise Reduction mode stops the CPU and all I/O modules except asynchronous timer and ADC, to minimize switching noise during ADC conversions. In Standby mode, the crystal/resonator Oscillator is running while the rest of the device is sleeping. This allows very fast start-up combined with low-power consumption.

The device is manufactured using Atmel's high density non-volatile memory technology. The On-chip In-System re-Programmable (ISP) Flash allows the program memory to be reprogrammed In-System through an SPI serial interface, by a conventional non-volatile memory programmer, or by an On-chip Boot program running on the AVR core. The Boot program can use any interface to download the application program in the Application Flash memory. Software in the Boot Flash section will continue to run while the Application Flash section is updated, providing true Read-While-Write operation. By combining an 8-bit RISC CPU with In-System Self-Programmable Flash on a monolithic chip, the Atmel ATmega325P/3250P is a powerful microcontroller that provides a highly flexible and cost effective solution to many embedded control applications.

The ATmega325P/3250P AVR is supported with a full suite of program and system development tools including: C Compilers, Macro Assemblers, Program Debugger/Simulators, In-Circuit Emulators, and Evaluation kits.

2.2 Comparison between ATmega325P and ATmega3250P

The ATmega325P and ATmega3250P differs only in memory sizes, pin count and pinout. Table 2-1 on page 5 summarizes the different configurations for the four devices.

Table 2-1. Configuration Summary

Device	Flash	EEPROM	RAM	General Purpose I/O Pins
ATmega325P	32K bytes	1K bytes	2K bytes	54
ATmega3250P	32K bytes	1K bytes	2K bytes	69





2.3 Pin Descriptions

The following section describes the I/O-pin special functions.

2.3.1 V_{CC}

Digital supply voltage.

2.3.2 GND

Ground.

2.3.3 Port A (PA7..PA0)

Port A is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port A output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port A pins that are externally pulled low will source current if the pull-up resistors are activated. The Port A pins are tri-stated when a reset condition becomes active, even if the clock is not running.

2.3.4 Port B (PB7..PB0)

Port B is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port B output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port B pins that are externally pulled low will source current if the pull-up resistors are activated. The Port B pins are tri-stated when a reset condition becomes active, even if the clock is not running.

Port B has better driving capabilities than the other ports.

Port B also serves the functions of various special features of the ATmega325P/3250P as listed on page 71.

2.3.5 Port C (PC7..PC0)

Port C is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port C output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port C pins that are externally pulled low will source current if the pull-up resistors are activated. The Port C pins are tri-stated when a reset condition becomes active, even if the clock is not running.

2.3.6 Port D (PD7..PD0)

Port D is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port D output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port D pins that are externally pulled low will source current if the pull-up resistors are activated. The Port D pins are tri-stated when a reset condition becomes active, even if the clock is not running.

Port D also serves the functions of various special features of the ATmega325P/3250P as listed on page 74.

2.3.7 Port E (PE7..PE0)

Port E is an 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port E output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port E pins that are externally pulled low will source current if the pull-up

resistors are activated. The Port E pins are tri-stated when a reset condition becomes active, even if the clock is not running.

Port E also serves the functions of various special features of the ATmega325P/3250P as listed on page 75.

2.3.8 Port F (PF7..PF0)

Port F serves as the analog inputs to the A/D Converter.

Port F also serves as an 8-bit bi-directional I/O port, if the A/D Converter is not used. Port pins can provide internal pull-up resistors (selected for each bit). The Port F output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port F pins that are externally pulled low will source current if the pull-up resistors are activated. The Port F pins are tri-stated when a reset condition becomes active, even if the clock is not running. If the JTAG interface is enabled, the pull-up resistors on pins PF7(TDI), PF5(TMS), and PF4(TCK) will be activated even if a reset occurs.

Port F also serves the functions of the JTAG interface.

2.3.9 Port G (PG5..PG0)

Port G is a 6-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port G output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port G pins that are externally pulled low will source current if the pull-up resistors are activated. The Port G pins are tri-stated when a reset condition becomes active, even if the clock is not running.

Port G also serves the functions of various special features of the ATmega325P/3250P as listed on page 75.

2.3.10 Port H (PH7..PH0)

Port H is a 8-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port H output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port H pins that are externally pulled low will source current if the pull-up resistors are activated. The Port H pins are tri-stated when a reset condition becomes active, even if the clock is not running.

Port H also serves the functions of various special features of the ATmega3250P as listed on page 75.

2.3.11 Port J (PJ6..PJ0)

Port J is a 7-bit bi-directional I/O port with internal pull-up resistors (selected for each bit). The Port J output buffers have symmetrical drive characteristics with both high sink and source capability. As inputs, Port J pins that are externally pulled low will source current if the pull-up resistors are activated. The Port J pins are tri-stated when a reset condition becomes active, even if the clock is not running.

Port J also serves the functions of various special features of the ATmega3250P as listed on page 75.





2.3.12 **RESET**

Reset input. A low level on this pin for longer than the minimum pulse length will generate a reset, even if the clock is not running. The minimum pulse length is given in "System and Reset Characterizations" on page 308. Shorter pulses are not guaranteed to generate a reset.

2.3.13 XTAL1

Input to the inverting Oscillator amplifier and input to the internal clock operating circuit.

2.3.14 XTAL2

Output from the inverting Oscillator amplifier.

2.3.15 AVCC

AVCC is the supply voltage pin for Port F and the A/D Converter. It should be externally connected to V_{CC} , even if the ADC is not used. If the ADC is used, it should be connected to V_{CC} through a low-pass filter.

2.3.16 AREF

This is the analog reference pin for the A/D Converter.

3. Resources

A comprehensive set of development tools, application notes and datasheets are available for download on http://www.atmel.com/avr.





4. Data Retention

Reliability Qualification results show that the projected data retention failure rate is much less than 1 PPM over 20 years at 85°C or 100 years at 25°C.

5. About Code Examples

This documentation contains simple code examples that briefly show how to use various parts of the device. These code examples assume that the part specific header file is included before compilation. Be aware that not all C compiler vendors include bit definitions in the header files and interrupt handling in C is compiler dependent. Please confirm with the C compiler documentation for more details.

For I/O Registers located in extended I/O map, "IN", "OUT", "SBIS", "SBIC", "CBI", and "SBI" instructions must be replaced with instructions that allow access to extended I/O. Typically "LDS" and "STS" combined with "SBRS", "SBRC", "SBR", and "CBR".

28. Register Summary

Note: Registers with bold type only available in ATmega3250P.

Address	Name	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Page
(0xFF)	Reserved	-	-	-	-	-	-	-	-	
(0xFE)	Reserved	-	-	-	-	-	-	-	-	
(0xFD)	Reserved	-	-	-	-	-	-	-	-	
(0xFC)	Reserved	-	-	-	-	-	-	-	-	
(0xFB)	Reserved	-	-	-	-	-	-	-	-	
(0xFA)	Reserved	-	-	-	-	-	-	-	-	
(0xF9)	Reserved	-	-	-	-	-	-	-	-	
(0xF8)	Reserved	-	-	-	-	-	-	-	-	
(0xF7)	Reserved	-	-	-	-	-	-	-	-	
(0xF6)	Reserved	-	-	-	-	-	-	-	-	
(0xF5)	Reserved	-	-	-	-	-	-	-	-	
(0xF4)	Reserved	-	•	-	-	-	-	-	-	
(0xF3)	Reserved	-	•	-	-	-	-	-	-	
(0xF2)	Reserved	-	-	-	-	-	-	-	-	
(0xF1)	Reserved	-	-	-	-	-	-	-	-	
(0xF0)	Reserved	-	-	-	-	-	-	-	-	
(0xEF)	Reserved	-	-	-	-	-	-	-	-	
(0xEE)	Reserved	-	-	-	-	-	-	-	-	
(0xED)	Reserved	-	-	-	-	-	-	-	-	
(0xEC)	Reserved Reserved	-	-	-	-	-	-	-	-	
(0xEB)	Reserved	-	-		-			-	-	
(0xEA)	Reserved	-	-	-	-	-	-	-	-	
(0xE9)	Reserved	-	-	-	-	-	-	-	-	
(0xE8)	Reserved	-	-	-	-	-	-	-	-	
(0xE7) (0xE6)	Reserved	-	_	_	-	-	-	-	-	
· · · · · ·	Reserved	-	-	-	-	-	-	-	-	
(0xE5) (0xE4)	Reserved	-	-	-	-	-	-	-	-	
(0xE3)	Reserved	-	-	-	-	-	-	-	-	
(0xE2)	Reserved	-	-	-	-	-	-	-	-	
(0xE1)	Reserved	-	-	-	-	-	-	-	-	
(0xE0)	Reserved	-	-	-	-	-	-	-	-	
(0xDF)	Reserved	-	-	-	-	-	-	-	-	
(0xDE)	Reserved	-	-	-	-	-	-	-	-	
(0xDD)	PORTJ	-	PORTJ6	PORTJ5	PORTJ4	PORTJ3	PORTJ2	PORTJ1	PORTJ0	88
(0xDC)	DDRJ	-	DDJ6	DDJ5	DDJ4	DDJ3	DDJ2	DDJ1	DDJ0	88
(0xDB)	PINJ	-	PINJ6	PINJ5	PINJ4	PINJ3	PINJ2	PINJ1	PINJ0	88
(0xDA)	PORTH	PORTH7	PORTH6	PORTH5	PORTH4	PORTH3	PORTH2	PORTH1	PORTH0	87
(0xD9)	DDRH	DDH7	DDH6	DDH5	DDH4	DDH3	DDH2	DDH1	DDH0	88
(0xD8)	PINH	PINH7	PINH6	PINH5	PINH4	PINH3	PINH2	PINH1	PINH0	88
(0xD7)	Reserved	-	-	-	-	-	-	-	-	
(0xD6)	Reserved	-	1	-	-	-	-	-	-	
(0xD5)	Reserved	-	-	-	-	-	-	-	-	
(0xD4)	Reserved	-	-	-	-	-	-	-	-	
(0xD3)	Reserved	-	•	-	-	-	-	-	-	
(0xD2)	Reserved	-	•	-	-	-	-	-	-	
(0xD1)	Reserved	-	-	-	-	-	-	-	-	
(0xD0)	Reserved	-	-	-	-	-	-	-	-	
(0xCF)	Reserved	-	-	-	-	-	-	-	-	
(0xCE)	Reserved	-	-	-	-	-	-	-	-	
(0xCD)	Reserved	-	-	-	-	-	-	-	-	
(0xCC)	Reserved	-	-	-	-	-	-	-	-	
(0xCB)	Reserved	-	-	-	-	-	-	-	-	
(0xCA)	Reserved	-	-	-	-	-	-	-	-	
(0xC9)	Reserved	-	-	-	-	-	-	-	-	
(0xC8)	Reserved	-	-	-	-	-	-	-	-	
(0xC7)	Reserved	-	-	-	-	- ata Register	-	-	-	100
(0xC6)	UDR0 UBRR0H				USARIUD	aia negister	USART0 Baud R	ata Pagistar Lieb		182 186
(0xC5)	UBRRUH						OSARTO Baud R	ate negister high		190





Address	Name	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Page
(0xC4)	UBRR0L		L		USART0 Baud F	Rate Register Low				186
(0xC3)	Reserved	-	-	-	-	-	-	-	-	
(0xC2)	UCSR0C	-	UMSEL0	UPM01	UPM00	USBS0	UCSZ01	UCSZ00	UCPOL0	184
(0xC1)	UCSR0B	RXCIE0	TXCIE0	UDRIE0	RXEN0	TXEN0	UCSZ02	RXB80	TXB80	183
(0xC0)	UCSR0A	RXC0	TXC0	UDRE0	FE0	DOR0	UPE0	U2X0	MPCM0	182
(0xBF)	Reserved	-	-	-	-	-	-	-	-	
(0xBE)	Reserved	-	-	-	-	-	-	-	-	
(0xBD)	Reserved	-	-	-	-	-	-	-	-	
(0xBC)	Reserved	-	-	-	-	-	-	-	-	
(0xBB)	Reserved	-	-	-	-	-	-	-	-	
(0xBA)	USIDR					a Register				199
(0xBA)	USISR	USISIF	USIOIF	USIPF	USIDC	USICNT3	USICNT2	USICNT1	USICNT0	199
(0xB9) (0xB8)	USICR	USISIE	USIOIE	USIWM1	USIWM0	USICS1	USICS0	USICLK	USITC	200
	Reserved	-	-	-	-	-	-	-	-	200
(0xB7)	ASSR	-	-	-	EXCLK	AS2	TCN2UB	OCR2UB	TCR2UB	151
(0xB6)					-					131
(0xB5)	Reserved	-	-	-		-	-	-	-	
(0xB4)	Reserved	-	-	- Time	-		-	-	-	454
(0xB3)	OCR2A			Tim		ut Compare Regist	er A			151
(0xB2)	TCNT2		1			Counter2				151
(0xB1)	Reserved	-	-	-	-	-	-	-	-	
(0xB0)	TCCR2A	FOC2A	WGM20	COM2A1	COM2A0	WGM21	CS22	CS21	CS20	149
(0xAF)	Reserved	-	-	-	-	-	-	-	-	
(0xAE)	Reserved	-	-	-	-	-	-	-	-	
(0xAD)	Reserved	-	-	-	-	-	-	-	-	
(0xAC)	Reserved	-	-	-	-	-	-	-	-	
(0xAB)	Reserved	-	-	-	-	-	-	-	-	
(0xAA)	Reserved	-	-	-	-	-	-	-	-	
(0xA9)	Reserved	-	-	-	-	-	-	-	-	
(0xA8)	Reserved	-	-	-	-	-	-	-	-	
(0xA7)	Reserved	-	-	-	-	-	-	-	-	
(0xA6)	Reserved	-	-	-	-	-	-	-	-	
(0xA5)	Reserved	-	-	-	-	-	-	-	-	
(0xA4)	Reserved	-	-	-	-	-	-	-	-	
(0xA3)	Reserved	-	-	-	-	-	-	-	-	
(0xA2)	Reserved	-	-	-	-	-	-	-	-	
(0xA1)	Reserved	-	-	-	-	-	-	-	-	
(0xA1)	Reserved	-	-	-	-	-	-	-	-	
• •	Reserved	_	_	_	_	-	-	-	-	
(0x9F)	Reserved	-	-	-	-	-	-	-	-	
(0x9E)	Reserved	-	-	-	_	-	-	_	-	
(0x9D)										
(0x9C)	Reserved	-	-	-	-	-	-	-	-	
(0x9B)	Reserved	-	-	-	-	-	-	-	-	
(0x9A)	Reserved	-	-	-	-	-	-	-	-	
(0x99)	Reserved	-	-	-	-	-	-	-	-	
(0x98)	Reserved	-	-	-	-	-	-	-	-	
(0x97)	Reserved	-	-	-	-	-	-	-	-	
(0x96)	Reserved	-	-	-	-	-	-	-	-	
(0x95)	Reserved	-	-	-	-	-	-	-	-	
(0x94)	Reserved	-	-	-	-	-	-	-	-	
(0x93)	Reserved	-	-	-	-	-	-	-	-	
(0x92)	Reserved	-	-	-	-	-	-	-	-	
(0x91)	Reserved	-	-	-	-	-	-	-	-	
(0x90)	Reserved	-	-	-	-	-	-	-	-	
(0x8F)	Reserved	-	-	-	-	-	-	-	-	
(0x8E)	Reserved	-	-	-	-	-	-	-	-	
(0x8D)	Reserved	-	-	-	-	-	-	-	-	
(0x8C)	Reserved	-	-	-	-	-	-	-	-	
(0x8B)	OCR1BH			Timer	/Counter1 Output	Compare Register				132
(0x8A)	OCR1BL					Compare Register				132
(0x8A) (0x89)	OCR1AH					Compare Register				132
, ,	OCR1AL					Compare Register				132
(0x88)	ICR1H					Capture Register I				132
(0x87)	ICR1L						-			
(0x86)	I ICHU	1		I in	ner/Counter1 Input	Capture Register	LOW			133

ATmega325P/3250P

Address	Name	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Page
(0x85)	TCNT1H			ı.	Timer/Cou	unter1 High		l.	Į.	132
(0x84)	TCNT1L				Timer/Co	unter1 Low				132
(0x83)	Reserved	-	-	-	-	-	-	-	-	
(0x82)	TCCR1C	FOC1A	FOC1B	-	-	-	-	-	-	131
(0x81)	TCCR1B	ICNC1	ICES1	-	WGM13	WGM12	CS12	CS11	CS10	130
(0x80)	TCCR1A	COM1A1	COM1A0	COM1B1	COM1B0	-	-	WGM11	WGM10	128
(0x7F)	DIDR1	-	-	-	-	-	-	AIN1D	AIN0D	205
(0x7E)	DIDR0	ADC7D	ADC6D	ADC5D	ADC4D	ADC3D	ADC2D	ADC1D	ADC0D	222
(0x7D)	Reserved	-	-	-	-	-	-	-	-	
(0x7C)	ADMUX	REFS1	REFS0	ADLAR	MUX4	MUX3	MUX2	MUX1	MUX0	218
(0x7B)	ADCSRB	-	ACME	-	-	-	ADTS2	ADTS1	ADTS0	204/222
(0x7A)	ADCSRA	ADEN	ADSC	ADATE	ADIF	ADIE	ADPS2	ADPS1	ADPS0	220
(0x79)	ADCH				ADC Data F	Register High		I.		221
(0x78)	ADCL				ADC Data I	Register Low				221
(0x77)	Reserved	-	-	-	-	-	-	-	-	
(0x76)	Reserved	-	-	-	-	-	-	-	-	
(0x75)	Reserved	-	-	-	-	-	-	-	-	
(0x74)	Reserved	-	-	-	-	-	-	-	-	
(0x73)	PCMSK3	-	PCINT30	PCINT29	PCINT28	PCINT27	PCINT26	PCINT25	PCINT24	62
(0x72)	Reserved	-	-	-	-	-	-	-	-	
(0x71)	Reserved	-	-	-	-	-	-	-	-	
(0x70)	TIMSK2	-	-	-	-	-	-	OCIE2A	TOIE2	152
(0x6F)	TIMSK1	-	-	ICIE1	-	-	OCIE1B	OCIE1A	TOIE1	133
(0x6E)	TIMSK0	-	-	-	-	-	-	OCIE0A	TOIE0	104
(0x6D)	PCMSK2	PCINT23	PCINT22	PCINT21	PCINT20	PCINT19	PCINT18	PCINT17	PCINT16	62
(0x6C)	PCMSK1	PCINT15	PCINT14	PCINT13	PCINT12	PCINT11	PCINT10	PCINT9	PCINT8	62
(0x6B)	PCMSK0	PCINT7	PCINT6	PCINT5	PCINT4	PCINT3	PCINT2	PCINT1	PCINT0	62
(0x6A)	Reserved	-	-	-	-	-	-	-	-	
(0x69)	EICRA	-	-	-	-	-	-	ISC01	ISC00	59
(0x68)	Reserved	-	-	-	-	-	-	-	-	
(0x67)	Reserved	-	-	-	-	-	-	-	-	
(0x66)	OSCCAL				l Dscillator Calibratio	n Register [CAL7	01			36
(0x65)	Reserved	-	-	-	-	-	-	-	-	
(0x64)	PRR	-	-	-	-	PRTIM1	PRSPI	PSUSART0	PRADC	44
(0x63)	Reserved	-	-	-	-	-	-	-	-	
(0x62)	Reserved	-	-	-	-	-	-	-	-	
(0x61)	CLKPR	CLKPCE	-	-	-	CLKPS3	CLKPS2	CLKPS1	CLKPS0	36
(0x60)	WDTCR	-	-	-	WDCE	WDE	WDP2	WDP1	WDP0	51
0x3F (0x5F)	SREG	I	Т	Н	S	V	N	Z	С	13
0x3E (0x5E)	SPH				Stack Po	inter High				15
0x3D (0x5D)	SPL				Stack Po	ointer Low				15
0x3C (0x5C)	Reserved	-	-	-	-	-	-	-	-	
0x3B (0x5B)	Reserved	-	-	-	-	-	-	-	-	
0x3A (0x5A)	Reserved	-	-	-	-	-	-	-	-	
0x39 (0x59)	Reserved	-	-	-	-	-	-	-	-	
0x38 (0x58)	Reserved	-	-	-	-	-	-	-	-	
0x37 (0x57)	SPMCSR	SPMIE	RWWSB	-	RWWSRE	BLBSET	PGWRT	PGERS	SPMEN	269
0x36 (0x56)	Reserved									
0x35 (0x55)	MCUCR	JTD	BODS	BODSE	PUD	-	-	IVSEL	IVCE	56/85/255
0x34 (0x54)	MCUSR	-	-	-	JTRF	WDRF	BORF	EXTRF	PORF	50
0x33 (0x53)	SMCR	-	-	-	-	SM2	SM1	SM0	SE	43
0x32 (0x52)	Reserved	-	-	-	-	-	-	-	-	
0x31 (0x51)	OCDR	IDRD/OCDR7	OCDR6	OCDR5	OCDR4	OCDR3	OCDR2	OCDR1	OCDR0	228
0x30 (0x50)	ACSR	ACD	ACBG	ACO	ACI	ACIE	ACIC	ACIS1	ACIS0	204
0x2F (0x4F)	Reserved	-	-	-	-	-	-	-	-	
0x2F (0x4F)	SPDR					a Register				162
0x2L (0x4L) 0x2D (0x4D)	SPSR	SPIF	WCOL	-	-	-	-	-	SPI2X	162
0x2D (0x4D) 0x2C (0x4C)	SPCR	SPIE	SPE	DORD	MSTR	CPOL	CPHA	SPR1	SPR0	160
0x2C (0x4C) 0x2B (0x4B)	GPIOR2		<u>-</u>	1		ose I/O Register	1			27
0x2B (0x4B) 0x2A (0x4A)	GPIOR1					ose I/O Register				27
0x2A (0x4A) 0x29 (0x49)	Reserved	-	-	-	-	-	-	-	-	
, ,	Reserved	-		-	-	-	-	-	-	
0x28 (0x48)	OCR0A					Output Compare A				104
0x27 (0x47)	301107					Jaspas Joinpare A				104





Address	Name	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Page
0x26 (0x46)	TCNT0				Timer/0	Counter0			"	104
0x25 (0x45)	Reserved	-	-	-	-	-	-	-	-	
0x24 (0x44)	TCCR0A	FOC0A	WGM00	COM0A1	COM0A0	WGM01	CS02	CS01	CS00	102
0x23 (0x43)	GTCCR	TSM	•	-	-	-	-	PSR2	PSR10	105/153
0x22 (0x42)	EEARH	-	-	-	-	-	EEPRO	OM Address Regis	ter High	23
0x21 (0x41)	EEARL				EEPROM Addre	ess Register Low				23
0x20 (0x40)	EEDR				EEPROM D	Data Register				23
0x1F (0x3F)	EECR	-	-	-	-	EERIE	EEMWE	EEWE	EERE	24
0x1E (0x3E)	GPIOR0			ı	General Purpo	se I/O Register	l .	I	Ш	28
0x1D (0x3D)	EIMSK	PCIE3	PCIE2	PCIE1	PCIE0	-	-	-	INT0	60
0x1C (0x3C)	EIFR	PCIF3	PCIF2	PCIF1	PCIF0	-	-	-	INTF0	61
0x1B (0x3B)	Reserved	-	-	-	-	-	-	-	-	
0x1A (0x3A)	Reserved	-	-	-	-	-	-	-	-	
0x19 (0x39)	Reserved	-	-	-	-	-	-	-	-	
0x18 (0x38)	Reserved	-	•	-	-	-	-	-	-	
0x17 (0x37)	TIFR2	-	-	-	-	-	-	OCF2A	TOV2	153
0x16 (0x36)	TIFR1	-	-	ICF1	-	-	OCF1B	OCF1A	TOV1	133
0x15 (0x35)	TIFR0	-	-	-	-	-	-	OCF0A	TOV0	105
0x14 (0x34)	PORTG	-	-	-	PORTG4	PORTG3	PORTG2	PORTG1	PORTG0	87
0x13 (0x33)	DDRG	-	-	-	DDG4	DDG3	DDG2	DDG1	DDG0	87
0x12 (0x32)	PING	-	•	PING5	PING4	PING3	PING2	PING1	PING0	87
0x11 (0x31)	PORTF	PORTF7	PORTF6	PORTF5	PORTF4	PORTF3	PORTF2	PORTF1	PORTF0	87
0x10 (0x30)	DDRF	DDF7	DDF6	DDF5	DDF4	DDF3	DDF2	DDF1	DDF0	87
0x0F (0x2F)	PINF	PINF7	PINF6	PINF5	PINF4	PINF3	PINF2	PINF1	PINF0	87
0x0E (0x2E)	PORTE	PORTE7	PORTE6	PORTE5	PORTE4	PORTE3	PORTE2	PORTE1	PORTE0	86
0x0D (0x2D)	DDRE	DDE7	DDE6	DDE5	DDE4	DDE3	DDE2	DDE1	DDE0	86
0x0C (0x2C)	PINE	PINE7	PINE6	PINE5	PINE4	PINE3	PINE2	PINE1	PINE0	87
0x0B (0x2B)	PORTD	PORTD7	PORTD6	PORTD5	PORTD4	PORTD3	PORTD2	PORTD1	PORTD0	86
0x0A (0x2A)	DDRD	DDD7	DDD6	DDD5	DDD4	DDD3	DDD2	DDD1	DDD0	86
0x09 (0x29)	PIND	PIND7	PIND6	PIND5	PIND4	PIND3	PIND2	PIND1	PIND0	86
0x08 (0x28)	PORTC	PORTC7	PORTC6	PORTC5	PORTC4	PORTC3	PORTC2	PORTC1	PORTC0	86
0x07 (0x27)	DDRC	DDC7	DDC6	DDC5	DDC4	DDC3	DDC2	DDC1	DDC0	86
0x06 (0x26)	PINC	PINC7	PINC6	PINC5	PINC4	PINC3	PINC2	PINC1	PINC0	86
0x05 (0x25)	PORTB	PORTB7	PORTB6	PORTB5	PORTB4	PORTB3	PORTB2	PORTB1	PORTB0	85
0x04 (0x24)	DDRB	DDB7	DDB6	DDB5	DDB4	DDB3	DDB2	DDB1	DDB0	85
0x03 (0x23)	PINB	PINB7	PINB6	PINB5	PINB4	PINB3	PINB2	PINB1	PINB0	85
0x02 (0x22)	PORTA	PORTA7	PORTA6	PORTA5	PORTA4	PORTA3	PORTA2	PORTA1	PORTA0	85
0x01 (0x21)	DDRA	DDA7	DDA6	DDA5	DDA4	DDA3	DDA2	DDA1	DDA0	85
0x00 (0x20)	PINA	PINA7	PINA6	PINA5	PINA4	PINA3	PINA2	PINA1	PINA0	85

- Notes: 1. For compatibility with future devices, reserved bits should be written to zero if accessed. Reserved I/O memory addresses should never be written.
 - 2. I/O Registers within the address range 0x00 0x1F are directly bit-accessible using the SBI and CBI instructions. In these registers, the value of single bits can be checked by using the SBIS and SBIC instructions.
 - 3. Some of the Status Flags are cleared by writing a logical one to them. Note that, unlike most other AVRs, the CBI and SBI instructions will only operate on the specified bit, and can therefore be used on registers containing such Status Flags. The CBI and SBI instructions work with registers 0x00 to 0x1F only.
 - 4. When using the I/O specific commands IN and OUT, the I/O addresses 0x00 0x3F must be used. When addressing I/O Registers as data space using LD and ST instructions, 0x20 must be added to these addresses. The ATmega325P/3250P is a complex microcontroller with more peripheral units than can be supported within the 64 location reserved in Opcode for the IN and OUT instructions. For the Extended I/O space from 0x60 - 0xFF in SRAM, only the ST/STS/STD and LD/LDS/LDD instructions can be used.

29. Instruction Set Summary

Mnemonics	Operands	Description	Operation	Flags	#Clocks
ARITHMETIC AND L	OGIC INSTRUCTIONS	•	·	<u> </u>	
ADD	Rd, Rr	Add two Registers	Rd ← Rd + Rr	Z,C,N,V,H	1
ADC	Rd, Rr	Add with Carry two Registers	$Rd \leftarrow Rd + Rr + C$	Z,C,N,V,H	1
ADIW	Rdl,K	Add Immediate to Word	Rdh:Rdl ← Rdh:Rdl + K	Z,C,N,V,S	2
SUB	Rd, Rr	Subtract two Registers	Rd ← Rd - Rr	Z,C,N,V,H	1
SUBI	Rd, K	Subtract Constant from Register	Rd ← Rd - K	Z,C,N,V,H	1
SBC	Rd, Rr	Subtract with Carry two Registers	Rd ← Rd - Rr - C	Z,C,N,V,H	1
SBCI	Rd, K	Subtract with Carry Constant from Reg.	Rd ← Rd - K - C	Z,C,N,V,H	1
SBIW	Rdl,K	Subtract Immediate from Word	Rdh:Rdl ← Rdh:Rdl - K	Z,C,N,V,S	2
AND	Rd, Rr	Logical AND Registers	Rd ← Rd • Rr	Z,N,V	1
ANDI	Rd, K	Logical AND Register and Constant	$Rd \leftarrow Rd \bullet K$	Z,N,V	1
OR	Rd, Rr	Logical OR Registers	Rd ← Rd v Rr	Z,N,V	1
ORI	Rd, K	Logical OR Register and Constant	$Rd \leftarrow Rd \vee K$	Z,N,V	1
EOR	Rd, Rr	Exclusive OR Registers	$Rd \leftarrow Rd \oplus Rr$	Z,N,V	1
COM	Rd	One's Complement	Rd ← 0xFF – Rd	Z,C,N,V	1
NEG	Rd	Two's Complement	Rd ← 0x00 – Rd	Z,C,N,V,H	1
SBR	Rd,K	Set Bit(s) in Register	$Rd \leftarrow Rd \vee K$	Z,N,V	1
CBR	Rd,K	Clear Bit(s) in Register	$Rd \leftarrow Rd \bullet (0xFF - K)$	Z,N,V	1
INC	Rd	Increment	Rd ← Rd + 1	Z,N,V	1
DEC	Rd	Decrement	Rd ← Rd – 1	Z,N,V	1
TST	Rd	Test for Zero or Minus	Rd ← Rd • Rd	Z,N,V	1
CLR	Rd	Clear Register	Rd ← Rd ⊕ Rd	Z,N,V	1
SER	Rd	Set Register	Rd ← 0xFF	None	1
MUL	Rd, Rr	Multiply Unsigned	R1:R0 ← Rd x Rr	Z,C	2
MULS	Rd, Rr	Multiply Signed	R1:R0 ← Rd x Rr	Z,C	2
MULSU	Rd, Rr	Multiply Signed with Unsigned	R1:R0 ← Rd x Rr	Z,C	2
FMUL FMULS	Rd, Rr	Fractional Multiply Unsigned	R1:R0 ← (Rd x Rr) << 1	Z,C	2
FMULSU	Rd, Rr Rd, Rr	Fractional Multiply Signed	R1:R0 ← (Rd x Rr) << 1	Z,C Z,C	2
BRANCH INSTRUCT	, and the second	Fractional Multiply Signed with Unsigned	$R1:R0 \leftarrow (Rd \times Rr) << 1$	2,0	2
RJMP	k	Relative Jump	PC ← PC + k + 1	None	2
IJMP	K	Indirect Jump to (Z)	PC ← Z	None	2
JMP	k	Direct Jump	PC ← k	None	3
RCALL	k	Relative Subroutine Call	PC ← PC + k + 1	None	3
ICALL		Indirect Call to (Z)	PC ← Z	None	3
CALL	k	Direct Subroutine Call	PC ← k	None	4
RET		Subroutine Return	PC ← STACK	None	4
RETI		Interrupt Return	PC ← STACK	1	4
CPSE	Rd,Rr	Compare, Skip if Equal	if (Rd = Rr) PC ← PC + 2 or 3	None	1/2/3
CP	Rd,Rr	Compare	Rd – Rr	Z, N,V,C,H	1
CPC	Rd,Rr	Compare with Carry	Rd – Rr – C	Z, N,V,C,H	1
CPI	Rd,K	Compare Register with Immediate	Rd – K	Z, N,V,C,H	1
SBRC	Rr, b	Skip if Bit in Register Cleared	if (Rr(b)=0) PC ← PC + 2 or 3	None	1/2/3
SBRS	Rr, b	Skip if Bit in Register is Set	if (Rr(b)=1) PC ← PC + 2 or 3	None	1/2/3
SBIC	P, b	Skip if Bit in I/O Register Cleared	if (P(b)=0) PC ← PC + 2 or 3	None	1/2/3
SBIS	P, b	Skip if Bit in I/O Register is Set	if (P(b)=1) PC ← PC + 2 or 3	None	1/2/3
BRBS	s, k	Branch if Status Flag Set	if (SREG(s) = 1) then PC←PC+k + 1	None	1/2
BRBC	s, k	Branch if Status Flag Cleared	if (SREG(s) = 0) then PC←PC+k + 1	None	1/2
BREQ	k	Branch if Equal	if $(Z = 1)$ then PC \leftarrow PC + k + 1	None	1/2
BRNE	k	Branch if Not Equal	if $(Z = 0)$ then $PC \leftarrow PC + k + 1$	None	1/2
BRCS	k	Branch if Carry Set	if (C = 1) then PC ← PC + k + 1	None	1/2
BRCC	k	Branch if Carry Cleared	if (C = 0) then PC \leftarrow PC + k + 1	None	1/2
BRSH	k	Branch if Same or Higher	if (C = 0) then PC \leftarrow PC + k + 1	None	1/2
BRLO	k	Branch if Lower	if (C = 1) then PC ← PC + k + 1	None	1/2
BRMI	k	Branch if Minus	if (N = 1) then PC \leftarrow PC + k + 1	None	1/2
BRPL	k	Branch if Plus	if (N = 0) then PC \leftarrow PC + k + 1	None	1/2
BRGE	k	Branch if Greater or Equal, Signed	if (N \oplus V= 0) then PC \leftarrow PC + k + 1	None	1/2
BRLT	k	Branch if Less Than Zero, Signed	if $(N \oplus V = 1)$ then $PC \leftarrow PC + k + 1$	None	1/2
BRHS	k	Branch if Half Carry Flag Set	if (H = 1) then PC ← PC + k + 1	None	1/2
BRHC	k	Branch if Half Carry Flag Cleared	if (H = 0) then PC ← PC + k + 1	None	1/2
BRTS	k	Branch if T Flag Set	if (T = 1) then PC ← PC + k + 1	None	1/2
BRTC	k	Branch if T Flag Cleared	if (T = 0) then PC ← PC + k + 1	None	1/2
BRVS	k	Branch if Overflow Flag is Set	if $(V = 1)$ then $PC \leftarrow PC + k + 1$	None	1/2





Mnemonics	Operands	Description	Operation	Flags	#Clocks
BRVC	k	Branch if Overflow Flag is Cleared	if $(V = 0)$ then $PC \leftarrow PC + k + 1$	None	1/2
BRIE	k	Branch if Interrupt Enabled	if (I = 1) then PC ← PC + k + 1	None	1/2
BRID	k	Branch if Interrupt Disabled	if (I = 0) then PC ← PC + k + 1	None	1/2
BIT AND BIT-TEST	INSTRUCTIONS				
SBI	P,b	Set Bit in I/O Register	I/O(P,b) ← 1	None	2
CBI	P,b	Clear Bit in I/O Register	$I/O(P,b) \leftarrow 0$	None	2
LSL	Rd	Logical Shift Left	$Rd(n+1) \leftarrow Rd(n), Rd(0) \leftarrow 0$	Z,C,N,V	1
LSR	Rd	Logical Shift Right	$Rd(n) \leftarrow Rd(n+1), Rd(7) \leftarrow 0$	Z,C,N,V	1
ROL	Rd	Rotate Left Through Carry	$Rd(0)\leftarrow C,Rd(n+1)\leftarrow Rd(n),C\leftarrow Rd(7)$	Z,C,N,V	1
ROR	Rd	Rotate Right Through Carry	$Rd(7)\leftarrow C,Rd(n)\leftarrow Rd(n+1),C\leftarrow Rd(0)$	Z,C,N,V	1
ASR	Rd	Arithmetic Shift Right	$Rd(n) \leftarrow Rd(n+1), n=06$	Z,C,N,V	1
SWAP	Rd	Swap Nibbles	$Rd(30) \leftarrow Rd(74), Rd(74) \leftarrow Rd(30)$	None	1
BSET	s	Flag Set	SREG(s) ← 1	SREG(s)	1
BCLR	s	Flag Clear	$SREG(s) \leftarrow 0$	SREG(s)	1
BST	Rr, b	Bit Store from Register to T	$T \leftarrow Rr(b)$	T	1
BLD	Rd, b	Bit load from T to Register	$Rd(b) \leftarrow T$	None	1
SEC		Set Carry	C ← 1	С	1
CLC		Clear Carry	C ← 0	С	1
SEN		Set Negative Flag	N ← 1	N	1
CLN		Clear Negative Flag	N ← 0	N	1
SEZ		Set Zero Flag	Z ← 1	Z	1
CLZ		Clear Zero Flag	Z ← 0	Z	1
SEI		Global Interrupt Enable	1←1	1	1
CLI		Global Interrupt Disable	1←0	1	1
SES		Set Signed Test Flag	S ← 1	S	1
CLS		Clear Signed Test Flag	S ← 0	S	1
SEV		Set Twos Complement Overflow.	V ← 1	V	1
CLV		Clear Twos Complement Overflow	V ← 0	V	1
SET		Set T in SREG	T ← 1	Т	1
CLT		Clear T in SREG	T ← 0	Т	1
SEH		Set Half Carry Flag in SREG	H←1	H	1
CLH		Clear Half Carry Flag in SREG	H ← 0	Н	1
DATA TRANSFER		T.,		1	.
MOV	Rd, Rr	Move Between Registers	Rd ← Rr	None	1
MOVW	Rd, Rr	Copy Register Word	Rd+1:Rd ← Rr+1:Rr	None	1
LDI	Rd, K	Load Immediate	Rd ← K	None	1
LD	Rd, X	Load Indirect	$Rd \leftarrow (X)$	None	2
LD	Rd, X+	Load Indirect and Post-Inc.	$Rd \leftarrow (X), X \leftarrow X + 1$	None	2
		Local Indianata and Day Day		Maria	2
LD	Rd, - X	Load Indirect and Pre-Dec.	$X \leftarrow X - 1, Rd \leftarrow (X)$	None	
LD	Rd, - X Rd, Y	Load Indirect	$Rd \leftarrow (Y)$	None	2
LD LD	Rd, - X Rd, Y Rd, Y+	Load Indirect Load Indirect and Post-Inc.	$Rd \leftarrow (Y)$ $Rd \leftarrow (Y), Y \leftarrow Y + 1$	None None	2 2
LD LD LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec.	$\begin{aligned} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \end{aligned}$	None None None	2 2 2
LD LD LD LDD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement	$\begin{aligned} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \end{aligned}$	None None None	2 2 2 2
LD LD LDD LDD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect	$\begin{aligned} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \end{aligned}$	None None None None None	2 2 2 2 2
LD LD LD LD LD LD LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect Load Indirect and Post-Inc.	$\begin{aligned} &Rd \leftarrow (Y) \\ &Rd \leftarrow (Y), Y \leftarrow Y+1 \\ &Y \leftarrow Y-1, Rd \leftarrow (Y) \\ &Rd \leftarrow (Y+q) \\ &Rd \leftarrow (Z) \\ &Rd \leftarrow (Z), Z \leftarrow Z+1 \end{aligned}$	None None None None None None None	2 2 2 2 2 2 2
LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+ Rd, -Z	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \end{array}$	None None None None None None None None	2 2 2 2 2 2 2 2 2
LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+ Rd, -Z Rd, -Z Rd, Z+q	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \end{array}$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2
LD L	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+ Rd, -Z Rd, -Z Rd, Z+q Rd, k	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect from SRAM	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (K) \end{array}$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD LD ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+ Rd, -Z Rd, X+q Rd, k X, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (K) \\ (X) \leftarrow Rr \end{array}$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+ Rd, -Z Rd, X+q Rd, k X, Rr X+, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y+1 \\ Y \leftarrow Y-1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y+q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z+1 \\ Z \leftarrow Z-1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z+q) \\ Rd \leftarrow (K) \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr, X \leftarrow X+1 \end{array}$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD S ST ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+ Rd, -Z Rd, X+q Rd, k X, Rr X+, Rr - X, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y+1 \\ Y \leftarrow Y-1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y+q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z+1 \\ Z \leftarrow Z-1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z+q) \\ Rd \leftarrow (k) \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ X \leftarrow X-1, (X) \leftarrow Rr \\ \end{array}$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD S ST ST ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd,Y+q Rd, Z Rd, Z+ Rd, Z- Rd, Z- Rd, Z- Rd, Z- Rd, X- Rd	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Pre-Dec. Store Indirect and Pre-Dec.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (X) \\ $	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD LD LS	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z+ Rd, Z+ Rd, -Z Rd, Z+q Rd, Z+q Rd, k X, Rr X+, Rr - X, Rr Y+, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect Store Indirect Store Indirect Store Indirect Store Indirect and Post-Inc.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (X +$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD ST ST ST ST ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y-q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr - X, Rr Y+, Rr - Y, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect with Displacement Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect Store Indirect Store Indirect Store Indirect Store Indirect Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect and Pre-Dec.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (X +$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD ST ST ST ST ST ST STD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, - Z Rd, Z+q Rd, k X, Rr X+, Rr - X, Rr Y+, Rr - Y, Rr Y+q, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Rd \leftarrow (Z) \\ Rd \leftarrow (X) \\ R$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD LD ST ST ST ST ST ST ST ST ST S	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr -X, Rr Y+, Rr -Y, Rr Y+q, Rr Z, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect with Displacement Store Indirect with Displacement	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Rd \leftarrow (Z) \\ Rd \leftarrow (X) \\ R$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD S ST S	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr - X, Rr Y, Rr - Y, Rr Y+q,Rr Z+q,Rr Z+q,Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect with Displacement Store Indirect and Pre-Dec.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (X) \\ $	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD LD LS ST ST ST ST ST ST ST ST ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr X, Rr Y+, Rr Y, Rr Y+q,Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr Z-, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect with Displacement Load Direct from SRAM Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect and Post-Inc.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (K) \\ Rd \leftarrow (K$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD LD LS ST ST ST ST ST ST ST ST ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr X, Rr Y+, Rr Y, Rr Y+q,Rr Z+q,Rr Z+q,Rr Z+q,Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Post-Inc. Store Indirect with Displacement Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect and Pre-Dec.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (K) \\ Rd \leftarrow (K$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr X, Rr Y+, Rr Y, Rr Y+q,Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr Z+, Rr Z-, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect with Displacement Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec.	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Rd \leftarrow (Z) \\ Rd \leftarrow (X) \leftarrow (Z) \\ Rd \leftarrow (X) \leftarrow ($	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr - X, Rr Y+, Rr - Y, Rr Y+q,Rr Z+q,Rr Z+q,Rr Z+q,Rr Z+q,Rr L, Rr Z+q,Rr L, Rr Z+q,Rr L, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Post-Inc. Store Indirect with Displacement Store Indirect and Pre-Dec. Store Indirect with Displacement Store Direct to SRAM Load Program Memory	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (K) \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (Y) \leftarrow Rr \\ (Y + q) \leftarrow Rr \\ (Z) \leftarrow Rr \\ (Z)$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr -X, Rr Y, Rr Y+q, Rr -Y, Rr Z+q, Rr Z+q, Rr Z+q, Rr Rd, R	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect with Displacement Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect Store Indirect and Pre-Dec. Store Indirect Store Indirect and Pre-Dec. Store Indirect Store Indirect with Displacement Store Direct to SRAM Load Program Memory Load Program Memory	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (K) \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (Y) \leftarrow Rr \\ (Y + q) \leftarrow Rr \\ (Z) \leftarrow Rr \\ (Z + q) \leftarrow Rr \\ (K) \leftarrow (K) \\ (K) \leftarrow Rr \\ (K) \leftarrow (K) \\ (K)$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD LD LD LD LD LD LD LD LD LS ST ST ST ST ST ST ST ST ST	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr - X, Rr Y+, Rr - Y, Rr Y+q,Rr Z+q,Rr Z+q,Rr Z+q,Rr Z+q,Rr L, Rr Z+q,Rr L, Rr Z+q,Rr L, Rr	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect with Displacement Store Indirect and Post-Inc. Store Indirect Store	$ \begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (X) \\ Rd \leftarrow (X) \leftarrow (X) \leftarrow Rr \\ (Y) \leftarrow Rr \\ (Y + q) \leftarrow Rr \\ (Z) \leftarrow Rr \\ (Z) \leftarrow Rr \\ (Z) \leftarrow Rr \\ (Z + q) \leftarrow Rr \\ (X) \leftarrow Rr \\ (X$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2
LD	Rd, - X Rd, Y Rd, Y+ Rd, - Y Rd, Y+q Rd, Z Rd, Z+ Rd, -Z Rd, Z+q Rd, k X, Rr X+, Rr -X, Rr Y, Rr Y+q, Rr -Y, Rr Z+q, Rr Z+q, Rr Z+q, Rr Rd, R	Load Indirect Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Indirect Load Indirect and Post-Inc. Load Indirect and Post-Inc. Load Indirect and Pre-Dec. Load Indirect with Displacement Load Direct from SRAM Store Indirect Store Indirect and Post-Inc. Store Indirect and Post-Inc. Store Indirect and Pre-Dec. Store Indirect with Displacement Store Indirect and Pre-Dec. Store Indirect and Pre-Dec. Store Indirect Store Indirect and Pre-Dec. Store Indirect Store Indirect and Pre-Dec. Store Indirect Store Indirect with Displacement Store Direct to SRAM Load Program Memory Load Program Memory	$\begin{array}{c} Rd \leftarrow (Y) \\ Rd \leftarrow (Y), Y \leftarrow Y + 1 \\ Y \leftarrow Y - 1, Rd \leftarrow (Y) \\ Rd \leftarrow (Y + q) \\ Rd \leftarrow (Z) \\ Rd \leftarrow (Z), Z \leftarrow Z + 1 \\ Z \leftarrow Z - 1, Rd \leftarrow (Z) \\ Rd \leftarrow (Z + q) \\ Rd \leftarrow (K) \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (X) \leftarrow Rr \\ (Y) \leftarrow Rr \\ (Y + q) \leftarrow Rr \\ (Z) \leftarrow Rr \\ (Z + q) \leftarrow Rr \\ (K) \leftarrow (K) \\ (K) \leftarrow Rr \\ (K) \leftarrow (K) \\ (K)$	None None None None None None None None	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2

■ ATmega325P/3250P

Mnemonics	Operands	Description	Operation	Flags	#Clocks
PUSH	Rr	Push Register on Stack	STACK ← Rr	None	2
POP	Rd	Pop Register from Stack	Rd ← STACK	None	2
MCU CONTROL INS	TRUCTIONS				
NOP		No Operation		None	1
SLEEP		Sleep	(see specific descr. for Sleep function)	None	1
WDR		Watchdog Reset	(see specific descr. for WDR/timer)	None	1
BREAK		Break	For On-chip Debug Only	None	N/A





30. Ordering Information

ATmega325P 30.1

Speed (MHz) ⁽³⁾	Power Supply	Ordering Code ⁽²⁾	Package Type ⁽¹⁾	Operational Range
10	1.8 - 5.5V	ATmega325PV-10AU ATmega325PV-10MU	64A 64M1	Industrial (-40·C to 85·C)
20	2.7 - 5.5V	ATmega325P-20AU ATmega325P-20MU	64A 64M1	Industrial (-40·C to 85·C)

- Notes: 1. This device can also be supplied in wafer form. Please contact your local Atmel sales office for detailed ordering information and minimum quantities.
 - 2. Pb-free packaging complies to the European Directive for Restriction of Hazardous Substances (RoHS directive). Also Halide free and fully Green.
 - 3. For Speed vs. $V_{\rm CC}$ see Figure 26-1 on page 306 and Figure 26-2 on page 306.

	Package Type
64A	64-lead, 14 x 14 x 1.0 mm, Thin Profile Plastic Quad Flat Package (TQFP)
64M1	64-pad, 9 x 9 x 1.0 mm, Quad Flat No-Lead/Micro Lead Frame Package (QFN/MLF)

30.2 ATmega3250P

Speed (MHz) ⁽³⁾	Power Supply	Ordering Code ⁽²⁾	Package Type ⁽¹⁾	Operational Range
10	1.8 - 5.5V	ATmega3250PV-10AU	100A	Industrial (-40·C to 85·C)
20	2.7 - 5.5V	ATmega3250P-20AU	100A	Industrial (-40·C to 85·C)

Notes:

- 1. This device can also be supplied in wafer form. Please contact your local Atmel sales office for detailed ordering information and minimum quantities.
- 2. Pb-free packaging complies to the European Directive for Restriction of Hazardous Substances (RoHS directive). Also Halide free and fully Green.
- 3. For Speed vs. V_{CC} see Figure 26-1 on page 306 and Figure 26-2 on page 306.


	Package Type
100A	100-lead, 14 x 14 x 1.0 mm, 0.5 mm Lead Pitch, Thin Profile Plastic Quad Flat Package (TQFP)





31. Packaging Information

31.1 64A



protrusion is 0.25 mm per side. Dimensions D1 and E1 are maximum

plastic body size dimensions including mold mismatch.

3. Lead coplanarity is 0.10 mm maximum.

10/5/2001

2325 Orchard Pa San Jose, CA 95

64A, 64-lead, 14 x 14 mm Body Size, 1.0 mm Body Thickness, 0.8 mm Lead Pitch, Thin Profile Plastic Quad Flat Package (TQFP)

С

L

е

0.09

0.45


0.80 TYP

DRAWING NO.	REV.
64A	В

0.20


0.75

31.2 64M1





31.3 100A



COMMON DIMENSIONS

(Unit of Measure = mm)

	`		,	
SYMBOL	MIN	NOM	MAX	NOTE
Α	_	_	1.20	
A1	0.05	_	0.15	
A2	0.95	1.00	1.05	
D	15.75	16.00	16.25	
D1	13.90	14.00	14.10	Note 2
Е	15.75	16.00	16.25	
E1	13.90	14.00	14.10	Note 2
В	0.17	_	0.27	
С	0.09	_	0.20	
L	0.45	_	0.75	
е	0.50 TYP			

Notes:

- 1. This package conforms to JEDEC reference MS-026, Variation AED.
- Dimensions D1 and E1 do not include mold protrusion. Allowable protrusion is 0.25 mm per side. Dimensions D1 and E1 are maximum plastic body size dimensions including mold mismatch.
- 3. Lead coplanarity is 0.08 mm maximum.

10/5/2001

			DRAWING NO.	REV.
	2325 Orchard Parkway San Jose, CA 95131	100A , 100-lead, 14 x 14 mm Body Size, 1.0 mm Body Thickness, 0.5 mm Lead Pitch, Thin Profile Plastic Quad Flat Package (TQFP)	100A	С

32. Errata

32.1 ATmega325P rev. A

- Interrupts may be lost when writing the timer registers in the asynchronous timer.
- . Using BOD disable will make the chip reset.
- Interrupts may be lost when writing the timer registers in the asynchronous timer.

The interrupt will be lost if a timer register that is synchronous timer clock is written when the asynchronous Timer/Counter register (TCNTx) is 0x00.

Problem Fix/Workaround

Always check that the asynchronous Timer/Counter register neither have the value 0xFF nor 0x00 before writing to the asynchronous Timer Control Register (TCCRx), asynchronous Timer Counter Register (TCNTx), or asynchronous Output Compare Register (OCRx).

2. Using BOD disable will make the chip reset.

If the part enters sleep with the BOD turned off with the BOD disable option enabled, a BOD reset will be generated at wakeup and the chip will reset.

Problem Fix/Workaround

Do not use BOD disable

32.2 ATmega325P rev. B

- Interrupts may be lost when writing the timer registers in the asynchronous timer.
- 1. Interrupts may be lost when writing the timer registers in the asynchronous timer.

The interrupt will be lost if a timer register that is synchronous timer clock is written when the asynchronous Timer/Counter register (TCNTx) is 0x00.

Problem Fix/Workaround

Always check that the asynchronous Timer/Counter register neither have the value 0xFF nor 0x00 before writing to the asynchronous Timer Control Register (TCCRx), asynchronous Timer Counter Register (TCNTx), or asynchronous Output Compare Register (OCRx).

32.3 ATmega325P rev. C

- · Interrupts may be lost when writing the timer registers in the asynchronous timer.
- Interrupts may be lost when writing the timer registers in the asynchronous timer.

The interrupt will be lost if a timer register that is synchronous timer clock is written when the asynchronous Timer/Counter register (TCNTx) is 0x00.

Problem Fix/Workoround

Always check that the asynchronous Timer/Counter register neither have the value 0xFF nor 0x00 before writing to the asynchronous Timer Control Register (TCCRx), asynchronous Timer Counter Register (TCNTx), or asynchronous Output Compare Register (OCRx).





32.4 ATmega3250P rev. A

- Interrupts may be lost when writing the timer registers in the asynchronous timer.
- · Using BOD disable will make the chip reset.
- Interrupts may be lost when writing the timer registers in the asynchronous timer.

The interrupt will be lost if a timer register that is synchronous timer clock is written when the asynchronous Timer/Counter register (TCNTx) is 0x00.

Problem Fix/Workaround

Always check that the asynchronous Timer/Counter register neither have the value 0xFF nor 0x00 before writing to the asynchronous Timer Control Register (TCCRx), asynchronous Timer Counter Register (TCNTx), or asynchronous Output Compare Register (OCRx).

2. Using BOD disable will make the chip reset.

If the part enters sleep with the BOD turned off with the BOD disable option enabled, a BOD reset will be generated at wakeup and the chip will reset.

Problem Fix/Workaround

Do not use BOD disable

32.5 ATmega3250P rev. B

- Interrupts may be lost when writing the timer registers in the asynchronous timer.
- 1. Interrupts may be lost when writing the timer registers in the asynchronous timer.

The interrupt will be lost if a timer register that is synchronous timer clock is written when the asynchronous Timer/Counter register (TCNTx) is 0x00.

Problem Fix/Workaround

Always check that the asynchronous Timer/Counter register neither have the value 0xFF nor 0x00 before writing to the asynchronous Timer Control Register (TCCRx), asynchronous Timer Counter Register (TCNTx), or asynchronous Output Compare Register (OCRx).

32.6 ATmega3250P rev. C

- · Interrupts may be lost when writing the timer registers in the asynchronous timer.
- Interrupts may be lost when writing the timer registers in the asynchronous timer.

The interrupt will be lost if a timer register that is synchronous timer clock is written when the asynchronous Timer/Counter register (TCNTx) is 0x00.

Problem Fix/Workaround

Always check that the asynchronous Timer/Counter register neither have the value 0xFF nor 0x00 before writing to the asynchronous Timer Control Register (TCCRx), asynchronous Timer Counter Register (TCNTx), or asynchronous Output Compare Register (OCRx).

33. Datasheet Revision History

Please note that the referring page numbers in this section are referring to this document. The referring revision in this section are referring to the document revision.

33.1 Rev.8023F- 07/09

- 1. Updated "Errata" on page 354.
- 2. Updated the last page with Atmel's new addresses.

33.2 Rev.8023E- 06/08

- Updated description of "Stack Pointer" on page 15.
- 2. Updated description of "Low-frequency Crystal Oscillator" on page 32.
- 3. Added notes to the overview section of "External Interrupts" on page 58.
- 4. Updated address of "PORTA Port A Data Register" on page 85.
- 5. Bullet five updated in "Asynchronous Operation of Timer/Counter2" on page 147.
- 6. Updated "System and Reset Characterizations" on page 308.
- 7. Added Errata for "ATmega325P rev. C" on page 354 and "ATmega3250P rev. C" on page 355.

33.3 Rev.8023D - 08/07

- 1. Added "Data Retention" on page 10.
- 2. Updated Device and JTAG ID in "Signature Bytes" on page 274.

33.4 Rev.8023C - 08/07

1. Updated "Errata" on page 354.

33.5 Rev.8023B - 08/07

- 1. Updated "Features" on page 1.
- 2. Updated DEVICE and JTAG ID in Table 25-6 on page 274
- 3. Updated "System and Reset Characterizations" on page 308.
- 4. Updated "Typical Characteristics" on page 314

33.6 Rev.8023A - 12/06

Initial version.

