72 INCHES LENGTH



Connector A 112234 BNC Jack Straight Bulkhead - Rear Mount Brass Nickel 50 Ohm RG-316 Continuity/Hi-Pot Connector B 252145 MCX Jack Straight Bulkhead - Rear Mount Brass Gold + Heatshrink

Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

	Connector A				Cable		Connector B		
	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting:	112234 BNC Clamp BHD JK RG188 500 BNC Jack Straight Crimp Standard 50 Ohm Bulkhead - Rear Mount Brass Nickel None Beryllium Copper Silver 4 GHz BNC Jack Straight BHD		Part #: Description: Dielectric: Shielding: Diameter: Impedance: Sheathing: Testing: Length:	RG-316 RG-316 - ST 0.102 ST Braid 0.102 50 Ohm None Continuity Hi-Pot 72 Inches	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting: Clocking:	252145 MCX JK RG174 RG MCX Jack Straight Crimp Standard 50 Ohm Bulkhead - Rear Mo Brass Gold None Beryllium Copper Gold 6 GHz	MCX JK RG174 RG316 LMR100 500 MCX Jack Straight Crimp Standard 50 Ohm Bulkhead - Rear Mount Brass Gold None Beryllium Copper Gold 6 GHz MCX Jack Straight BHD	
Amphenol CUSTOM CABLE CONTROL LED DOCLIMENT DO NOT CODY CUSTOM CABLE			THIS DRAWING MAY CONTAIN PROPRIETARY INFORMATION FOR ANY PURPOSE DETRIMEN INC. IT MAY NOT BE REPRODU IN ANY FORM WITHOUT THE W CUSTOM CABLE INC. ACCEPTA ESTABLISHES AND AGREEMEN	AND MUST NOT BE U TAL TO CUSTOM CAI CED OR TRANSCRIBI /RITTEN CONSENT O .NCE OF THIS DRAWI	BLE ED F NG Part No:	BNC-ST-JK/MCX-ST-JK G316 72I		UNLESS SPECIFIED TOLERANCE: 0-18 inches +/- 1/2" over 18" +/- 2% ASSEMBLY: CENTER LABEL IF LENGTH IS LESS THAN 12 INCHES	



RoHS 2015/863 Compliance Statement

According to the manufacture of all the component parts contained in this assembly, this product has been determined to be RoHS Compliant with RoHS Directive 2011/65/EU and as amended by Directive 2015/863, and without material exceptions (RoHS3 Complaint).

For the individual component RoHS certificates used in this assembly, please contact Amphenol Custom Cable.

The RoHS Compliance of any product so designated is based upon evidence from the producer (manufacturers') that the component parts comply with the RoHS Directive. Amphenol Custom Cable has taken all reasonable steps to confirm that the OEM (Manufacturer) of the components used in this assembly have provided evidence regarding the absence of the restricted substances to support the manufacturer's claim of compliance.

To the best of our knowledge and with due diligence, we certify that the product listed herein complies with the RoHS requirements.

Date: 9/30/2023

Part Number: Q-040110005072i

Manufacturer: Amphenol Custom Cable

Description: BNC-ST-JK/MCX-ST-JK G316 72I

This information is valid as of the date indicated for the item (part number) listed.

Director of Quality Assurance

Janice Frank