Assorted Terminals



RING TERMINALS

CLOSED END CONNECTORS





FEMALE DISCONNECTS




SPADE TERMINALS







Uninsulated Ring Terminals (Brazed Seam)							
Part No.	Stud Size	d1	d2	В	L	t	
902-407-10	#4	.074	.126	.217	.453	.029	
902-406-10	#6	.074	.146	.260	.567	.029	
902-408-10	#8	.074	.169	.260	.567	.029	
902-409-10	1/4"	.074	.252	.457	.846	.029	
902-410-10	#6	0.98	.146	.335	.661	.031	
902-411-10	#8	0.98	.169	.260	.567	.031	
902-412-10	#10	0.98	.209	.335	.661	.031	
902-413-10	1/4"	0.98	.252	.472	.835	.031	
902-414-10	#10	.133	.209	.374	.768	.031	
902-415-10	#8	.141	.169	.291	.728	.039	
902-416-10	#10	.141	.209	.291	.728	.039	
902-417-10	1/4"	.141	.252	.472	1.004	.039	
	Part No. 902-407-10 902-408-10 902-408-10 902-409-10 902-410-10 902-411-10 902-412-10 902-414-10 902-415-10 902-416-10	Part No. Stud Size 902-407-10 #4 902-406-10 #6 902-408-10 #8 902-409-10 1/4" 902-410-10 #6 902-411-10 #8 902-412-10 #10 902-413-10 1/4" 902-415-10 #10 902-415-10 #8 902-416-10 #10	Part No. Stud Size d1 902-407-10 #4 .074 902-406-10 #6 .074 902-408-10 #8 .074 902-409-10 1/4" .074 902-410-10 #6 0.98 902-411-10 #8 0.98 902-412-10 #10 0.98 902-413-10 1/4" 0.98 902-414-10 #10 .133 902-415-10 #8 .141 902-416-10 #10 .141	Part No. Stud Size d1 d2 902-407-10 #4 .074 .126 902-406-10 #6 .074 .146 902-408-10 #8 .074 .169 902-409-10 1/4" .074 .252 902-410-10 #6 0.98 .146 902-411-10 #8 0.98 .169 902-412-10 #10 0.98 .209 902-413-10 1/4" 0.98 .252 902-414-10 #10 .133 .209 902-415-10 #8 .141 .169 902-416-10 #10 .141 .209	Part No. Stud Size d1 d2 B 902-407-10 #4 .074 .126 .217 902-408-10 #6 .074 .146 .260 902-408-10 #8 .074 .169 .260 902-409-10 1/4" .074 .252 .457 902-410-10 #6 0.98 .146 .335 902-411-10 #8 0.98 .169 .260 902-412-10 #10 0.98 .209 .335 902-413-10 1/4" 0.98 .252 .472 902-415-10 #8 .141 .169 .291 902-415-10 #8 .141 .169 .291	Part No. Stud Size d1 d2 B L 902-407-10 #4 .074 .126 .217 .453 902-408-10 #6 .074 .146 .260 .567 902-408-10 #8 .074 .169 .260 .567 902-409-10 1/4" .074 .252 .457 .846 902-410-10 #6 0.98 .146 .335 .661 902-411-10 #8 0.98 .169 .260 .567 902-412-10 #10 0.98 .209 .335 .661 902-413-10 1/4" 0.98 .252 .472 .835 902-415-10 #10 .133 .209 .374 .768 902-415-10 #8 .141 .169 .291 .728 902-416-10 #10 .141 .209 .291 .728	



Insulated Ring T	erminals (Vingl)					
AWG	Part No.	Stud Size	В	d	L	t
	902-437-10	#6	.217	.146	.689	.030
22-16	902-438-10	#8	.260	.169	.803	.030
(Red)	902-439-10	#10	.315	.209	.854	.030
	902-440-10	1/4"	.457	.252	1.087	.030
	902-441-10	#6	.335	.146	.906	.031
16-14	902-442-10	#8	.335	.169	.906	.031
(Blue)	902-443-10	#10	.335	.209	.906	.031
	902-444-10	1/4"	.472	.252	1.106	.031
12-10 (Yellow)	902-445-10	#8	.291	.169	1.051	.039
	902-446-10	#10	.374	.209	1.051	.039
	902-447-10	1/4"	.472	.252	1.281	.039

• Dimensions in Inches.



Closed End Connectors (Vinyl)

902-403-10

902-402-10 .244

902-404-10 .413

902-405-10 .472

.311



C L

.209 1.091

.709

.776

1.004

.014

.014

.018


.037

.102


.118

.157






Butt splices Connectors (Vinyl)								
AWG	Part No.	D	D	L	F	Т		
22-16 Red	902-418-10	.169	.067	.984	.591	.030		
16-14 Blue	902-419-10	.177	.094	.984	.591	.031		
12-10 Yellow	902-420-10	.256	.141	1.063	.591	.037		




Female	Female Disconnectors (Push-Ons) (Vinyl)						
AWG	Part No.	Tab Size	D	В	L	Т	
22-16	902-421-10	.187 x .032	.142	.197	.748	.016	
Red	902-422-10	.205 x .020	.142	.220	.787	.016	
16-14	902-423-10	.187 x .032	.173	.197	.748	.016	
Blue	902-424-10	.205 x .020	.173	.22	.787	.016	
12-10	902-425-10	.187 x .032	.213	.197	.866	.016	
Yellow	902-426-10	.250 x .032	.213	.264	.984	.016	







Spade Terminals (Vinyl)						
AWG	Part No.	Stud Size	В	D	L	Т
	902-448-10	#6	.224	.146	.866	.030
22-16 Red	902-449-10	#8	.252	.169	.866	.030
22-10 Reu	902-450-10	#10	.209	.209	.866	.030
	902-451-10	1/4"	.252	.252	.906	.030
	902-452-10	#6	.146	.146	.866	.031
16-14 Blue	902-453-10	#8	.169	.169	.866	.031
16-14 Blue	902-454-10	#10	.209	.209	.866	.031
	902-455-10	1/4"	.252	.252	.925	.031
	902-456-10	#8	.169	.169	1.051	.039
12-10 Yellow	902-457-10	#10	.209	.209	1.051	.039
	902-458-10	1/4"	.252	.252	1.209	.039





Locking Spade Terminals (Vingl)							
	(19.)						
AWG	Part No.	Stud Size	В	D	L	Т	
	902-427-10	#6	.224	.146	.866	.030	
22-16 Red	902-428-10	#8	.286	.169	.866	.030	
	902-429-10	#10	.315	.209	.906	.030	
	902-430-10	#6	.244	.146	.866	.031	
16-14 Blue	902-431-10	#8	.283	.169	.866	.031	
	902-432-10	#10	.315	.209	.866	.031	
12-10 Yellow	902-433-10	#6	.319	.146	1.051	.039	
	902-434-10	#8	.323	.169	1.051	.039	
	902-435-10	#10	.354	.209	1.051	.039	
	902-436-10	1/4"	.472	.252	1.209	.039	