


# Feed Through Terminals

## WDK 2.5 D


Diode terminal for lamp test circuits



Branch with Diode


## WDK 2.5 D

Diode terminal for lamp test circuits




Branch with Diode

## WDK 2.5 LD



Branch with LED

## WDK 2.5 LD



Branch with LED

Terminal Block Selection Data		Part No.	Part No.	Part No.	Part No.			
<b>Available Options</b>	<b>Version</b>							
	Beige Wemid	<b>102260</b>	<b>801467</b>					
	Blue Wemid							
	PA Orange 66							
	Terminal block printed 0-9 Wemid							
	Terminal block unprinted Wemid							
	6 VDC			<b>911997</b>	<b>912014</b>			
	12 VDC			<b>911998</b>	<b>912015</b>			
	24 VDC			<b>911999</b>	<b>912016</b>			
	48 VDC			<b>912011</b>	<b>912017</b>			
	60 VDC			<b>912012</b>	<b>912018</b>			
	120 VDC			<b>912013</b>	<b>912019</b>			
	6 VAC							
	12 VAC							
	24 VAC							
	48 VAC							
	60 VAC							
	115 VAC							
	120 VAC							
	230 VAC							
<b>Dimensions</b>								
Width / Length / Height mm (in.)	for TS 35	5/69/63 (.20/2.72/2.48)	5/69/63 (.20/2.72/2.48)	5/69/63 (.20/2.72/2.48)	5/69/63 (.20/2.72/2.48)			
Insulation stripping length	mm (in.)	10 (.39)	10 (.39)	10 (.39)	10 (.39)			
<b>Technical Data</b>								
Rated voltage / rated current / wire size	UL			#26...12 AWG	#26...12 AWG			
	CSA							
	VDE	380 V / 0.5...2.5 mm <sup>2</sup>	380 V / 0.5...2.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>			
Torque	Nm (lb. in.)	0.8 (7.1)	0.8 (7.1)					
Clamping screw	M	2.5	2.5					
LED current				≤ 5 mA	≤ 5 mA			
LED color				Red	Red			
Current of through busbar				10 A	10 A			
<b>Selected Accessory Data<sup>‡</sup></b>								
<b>End Plate (WAP) / Partition (WTW) (thickness mm)</b>	<b>Type</b>	<b>Part No.</b>	<b>Type</b>	<b>Part No.</b>	<b>Type</b>	<b>Part No.</b>	<b>Type</b>	<b>Part No.</b>
	Beige Wemid	WAP (1.5) <b>105910</b>	WAP (1.5) <b>105910</b>	WAP (1.5) <b>105910</b>	WAP (1.5) <b>105910</b>	WAP (1.5) <b>105910</b>	WAP (1.5) <b>105910</b>	
	Blue Wemid	WAP (1.5) <b>105918</b>	WAP (1.5) <b>105918</b>	WAP (1.5) <b>105918</b>	WAP (1.5) <b>105918</b>	WAP (1.5) <b>105918</b>	WAP (1.5) <b>105918</b>	
	Beige Wemid	WTW (3) <b>105880</b>	WTW (3) <b>105880</b>	WTW (3) <b>105880</b>	WTW (3) <b>105880</b>	WTW (3) <b>105880</b>	WTW (3) <b>105880</b>	
<b>Jumpers</b>								
Note: Final number in model indicates no. of poles (e.g. WQV 2.5/2 = 2 poles). For additional information, see pages 60-61.								
	WQV 2.5/2	<b>105366</b>	WQV 2.5/2	<b>105366</b>	WQV 2.5/2	<b>105366</b>	WQV 2.5/2	<b>105366</b>
	WQV 2.5/3	<b>105376</b>	WQV 2.5/3	<b>105376</b>	WQV 2.5/3	<b>105376</b>	WQV 2.5/3	<b>105376</b>
	WQV 2.5/4	<b>105386</b>	WQV 2.5/4	<b>105386</b>	WQV 2.5/4	<b>105386</b>	WQV 2.5/4	<b>105386</b>
	WQV 2.5/5	<b>105396</b>	WQV 2.5/5	<b>105396</b>	WQV 2.5/5	<b>105396</b>	WQV 2.5/5	<b>105396</b>
	WQV 2.5/6	<b>105406</b>	WQV 2.5/6	<b>105406</b>	WQV 2.5/6	<b>105406</b>	WQV 2.5/6	<b>105406</b>
	WQV 2.5/7	<b>105416</b>	WQV 2.5/7	<b>105416</b>	WQV 2.5/7	<b>105416</b>	WQV 2.5/7	<b>105416</b>
	WQV 2.5/8	<b>105426</b>	WQV 2.5/8	<b>105426</b>	WQV 2.5/8	<b>105426</b>	WQV 2.5/8	<b>105426</b>
	WQV 2.5/9	<b>105436</b>	WQV 2.5/9	<b>105436</b>	WQV 2.5/9	<b>105436</b>	WQV 2.5/9	<b>105436</b>
	WQV 2.5/10	<b>105446</b>	WQV 2.5/10	<b>105446</b>	WQV 2.5/10	<b>105446</b>	WQV 2.5/10	<b>105446</b>
	WQB 24/12	<b>157900</b>	WQB 24/12	<b>157900</b>	WQB 24/12	<b>157900</b>	WQB 24/12	<b>157900</b>
	ZQV		ZQV		ZQV		ZQV	
	Shield Bar LS 2.8	<b>105640</b>	Shield Bar LS 2.8	<b>105640</b>	Shield Bar LS 2.8	<b>105640</b>	Shield Bar LS 2.8	<b>105640</b>
<b>Tools</b>								
Cutting tool WAW 1 for WQV jumpers	WAW 1	<b>900450</b>	WAW 1	<b>900450</b>	WAW 1	<b>900450</b>	WAW 1	<b>900450</b>
Screwdriver	SD	<b>903701</b>	SD	<b>903701</b>	SD	<b>903701</b>	SD	<b>903701</b>
<b>Marking Tags</b>								
Note: Part numbers shown are for a single card of pre-printed tags numbered 1-50. For additional information, see Accessories section.								
Consecutive horizontal	Print	DEK 5/5 <b>473460001</b>	DEK 5/5 <b>473460001</b>	DEK 5/5 <b>473460001</b>	DEK 5/5 <b>473460001</b>	DEK 5/5 <b>473460001</b>	DEK 5/5 <b>473460001</b>	
Consecutive vertical	Print	DEK 5/5 <b>473560001</b>	DEK 5/5 <b>473560001</b>	DEK 5/5 <b>473560001</b>	DEK 5/5 <b>473560001</b>	DEK 5/5 <b>473560001</b>	DEK 5/5 <b>473560001</b>	

<sup>‡</sup>See Accessories section for additional information.

