



Specifications Installation and Operating Instructions PW1.0 DC Power Supply

DESCRIPTION & FEATURES

The PW 1.0 is a regulated 0.5 amp power supply that accepts 24 VAC at the input and provides 24 VDC at the output. Field voltage adjustments may be made using only a screwdriver. The power supply is provided with a mounting track for easy field application. These low-cost power supplies feature good regulation and have full overcurrent protection.

- Low cost
- Regulated DC output
- Snap-track mounted
- Screw terminals with pressure plates

SPECIFICATIONS

VOLTAGE

Input: Output:

Output Current: Over-current Protection:

ENVIRONMENT

Operating Temperature: Max. Humidity:

PHYSICAL Weight: MOUNTING 24 VAC, 50/60 Hz 24 VDC (full wave rectified and regulated) adjustable 1.5 V - 29 VDC 0.5 amps 1 amp fuse

0 to 55°C (32 to 130°F) 95% RH, noncondensing

0.25 lb. snap-track included

ORDERING INFO

PART NUMBER

PW1.0

DIMENSIONS & WIRING



