

BNC Crimp-On Connectors

- Bright nickel finish and a solid brass or zinc body
- Solves potential cable/connector dimensional discrepancy problems
- Will maintain proper cable retention
- No loose contacts or other parts to handle
- Available in packs of 10



301-00-75TP
Universal BNC Male 2
Pc Crimp-On, 75 Ohm



301-00TP
Universal BNC Male 2
Pc Crimp-On, 50 Ohm



301-0TP
BNC Male 2 Pc
Crimp-On, 50 Ohm



301-1TP
BNC Male 2 Pc Crimp-
On, 50 Ohm



301-4TP
BNC Male 2 Pc Crimp-
On, 50 Ohm



301-75-2TP
BNC Male
Uni-Crimp, 75 Ohm



350-00-75TP
Universal BNC Female 2 Pc
Crimp-On, 75 Ohm




GET-301-UT
Universal Crimp Tool



GST-1
Coaxial Wire Stripper Tool


BNC Crimp-On Connectors

301-00TP BNC Crimp On Assembly Procedure



1) Trim cable as shown.

2) Slide crimp ferrule onto cable.



3) Fold braide back and complete trimming the cable as shown. Trim center conductor end at 45° angle.

4) Push connector onto cable.



5) Fold braid back over crimp body.

6) Push crimp ferrule up over braid and crimp body.



7) Using iniversal crimp toll P/N GET-301-UT, crimp ferrule to connector using .320 Hex.

8) Crimp cable support with appropriate hex: .264 RG 6 PVC - .205 RG 59 PVC, RG 6 TFE - .212 RG 59 TFE, RG 58 PVC.

Ordering Information

Part Number	Description
301-00-75TP	Universal BNC Male 2 Pc Crimp-On -- 75 Ohm, RG59 PVC & RG59 TFE 20 AWG; RG59 PVC & RG TFE 22 AWG; RG58 PVC, RG6 PVC & RG6 TFE. 10 PK
301-00TP	Universal BNC Male 2 Pc Crimp-On -- 50 Ohm, RG59 PVC & RG59 TFE 20 AWG; RG59 PVC & RG59 TFE 22 AWG; RG58 PVC, RG6 PVC & RG6 TFE. 10 PK
301-0TP	BNC Male 2 Pc Crimp-On -- 50 Ohm, RG59 PVC & RG59 TFE 20 AWG; RG59 PVC &
301-1TP	BNC Male 2 Pc Crimp-On, 50 Ohm -- RG58, RG59 TFE, & RG62 TFE. 10 PK
301-4TP	BNC Male 2 Pc Crimp-On -- 50 Ohm, RG59 PVC, RG6 TFE, 10 PK
301-75-2TP	BNC Male Uni-Crimp -- 75 Ohm, RG59. 10 PK
350-00-75TP	Universal BNC Female 2 Pc Crimp-On -- 75 Ohm, RG59 PVC & RG59 TFE 20 AWG; RG59 PVC & RG TFE 22 AWG; RG58 PVC, RG6 PVC & RG6 TFE. 10 PK
GET-301-UT	Universal Crimp Tool for Crimp-On BNC for 301-00TP, 301-1TP, 301-4TP
GST-1	Wire Stripper -- RG6, RG58, RG59, RG62